1994-09

Thermal analysis of PANSAT batteries and electrical power subsystem

Patterson, Sheila A.

Monterey, California. Naval Postgraduate School

http://hdl.handle.net/10945/28605

1. AGENCY USE ONLY *(Leave blank)*	2. REPORT DATE September 1994	3. REPORT TYPE AND DATES COVERED Master's Thesis

4. TITLE AND SUBTITLE Thermal Analysis of PANSAT Batteries and Electrical Power Subsystem	FUNDING NUMBERS

6. AUTHOR(S) Patterson, Sheila A.

7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES) Naval Postgraduate School Monterey CA 93943-5000	8. PERFORMING ORGANIZATION REPORT NUMBER

9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES)	10. SPONSORING/MONITORING AGENCY REPORT NUMBER

11. SUPPLEMENTARY NOTES The views expressed in this thesis are those of the author and do not reflect the official policy or position of the Department of Defense or the U.S. Government.

DISTRIBUTION/AVAILABILITY STATEMENT Approved for public release; distribution is unlimited.	12b. DISTRIBUTION CODE A

13. ABSTRACT *(maximum 200 words)*

The thermal design of a spacecraft ensures proper heat transfer so all components and subsystems remain within prescribed temperature limits during all aspects of the spacecraft's mission. This thesis develops a point to-point heat flow model of the Electrical Power Subsystem (EPS) and its associated housing for the Petite Amateur Navy Satellite (PANSAT). This analysis was performed to identify physical locations in the EPS where temperatures may exceed the limits established to protect sensitive electronic components, and to define the expected environment of the batteries. The Integrated Thermal Analysis System (ITAS) and a Steady State Thermal Analyzer and Model Builder were used to perform steady state and transient analyses on the EPS: analysis of the batteries was performed using ITAS only. The simulated transient temperatures within the EPS housing remained within limits, but the batteries exceeded specifications. It is suggested that a passive thermal control technique be adapted for the batteries and its design be experimentally validated before flight.

14. SUBJECT TERMS PANSAT, Thermal, Conduction, Radiation, ITAS, THANSS, TASS, Printed circuit boards, Transient, Steady State	15. NUMBER OF PAGES 204
	16. PRICE CODE

17. SECURITY CLASSIFICATION OF REPORT Unclassified	18. SECURITY CLASSIFICATION OF THIS PAGE Unclassified	19. SECURITY CLASSIFICATION OF ABSTRACT Unclassified	20. LIMITATION OF ABSTRACT UL

THERMAL ANALYSIS OF PANSAT BATTERIES AND ELECTRICAL POWER SUBSYSTEM

by

Sheila A. Patterson
Lieutenant Commander, United States Navy
B.S., United States Naval Academy, 1982

Submitted in partial fulfillment
of the requirements for the degree of

MASTER OF SCIENCE IN ASTRONAUTICAL ENGINEERING

from the

NAVAL POSTGRADUATE SCHOOL
September 1994

ABSTRACT

The thermal design of a spacecraft ensures proper heat transfer so all components and subsystems remain within prescribed temperature limits during all aspects of the spacecraft's mission. This thesis develops a point-to-point heat flow model of the Electrical Power Subsystem (EPS) and its associated housing for the Petite Amateur Navy Satellite (PANSAT). The analysis is performed to identify physical locations in the EPS where temperature may exceed the limits established to protect sensitive electronic components, and to define the expected environment of the batteries. The Integrated Thermal Analysis System (ITAS) and a Steady State Thermal Analyzer and Model Builder were used to perform steady state and transient analyses on the EPS; analysis of the batteries was performed using ITAS only. The simulated transient temperatures within the EPS housing remained within limits, but the batteries exceeded specifications. It is suggested that a passive thermal control technique be adapted for the batteries and its design be experimentally validated before flight.

vi

TABLE OF CONTENTS

I. INTRODUCTION

A. REASON FOR ANALYSIS

The thermal environment for components within a spacecraft is a function of the irradiation from the sun and earth, internal heat dissipation, radiation from external surfaces to the space sink, and the conductive and radiatitive heat transfer paths between the heat sources and sinks. Thermal control design ensures proper heat transfer so that all components and subsystems remain within prescribed temperature limits during all aspects of the spacecraft's mission.[Larson and Wertz, 1992] Early thermal design forces the determination of operating temperature limits and identifies the power dissipation patterns of components to allow for maximum use of passive thermal control methods.

To build a thermal model of a spacecraft, a knowledge of dimensions, equipment placement and material properties is required. The spacecraft or area to be analyzed is divided into nodes. The nodes are chosen so that the conductive and radiative heat flow paths accurately represent point-to-point heat flows within the spacecraft.

The thermal design of the spacecraft is also highly dependent on the mission and stabilization system of the satellite. Typically unmanned, low earth orbit spacecraft can be controlled passively. Table 1 lists a typical operating environment for electric power system (EPS) components.

The power subsystem typically has the greatest interaction with the thermal control subsystem because all of the dissipated electrical energy within the spacecraft must be radiated into space. The terrestrial batteries to be used in the Petite Amateur Navy Satellite (PANSAT) have even a narrower temperature range than that listed in Table 1: the ideal operational

1

SYSTEM COMPONENT	TEMPERATURE RANGE
MILITARY PIECE PARTS FOR INTEGRATED CIRCUITS	-55 TO 125 DEGREES CELSIUS
BATTERIES	-6 TO 26 DEGREES CELSIUS
SOLAR ARRAY PANELS	-100 TO 100 DEGREES CELSIUS

Table 1. Temperature Ranges for Some Electrical Power System Components

temperature for charging and discharging is 23 °C. Operations outside the published temperature range will cause the battery cells to degrade and become less efficient. This condition is explained fully in Chapter VI.

PANSAT has a very low power margin and must be able to maximize the power from the solar arrays and batteries. The sunlight and shadow zones of the orbit require that the batteries must operate for 40 percent of the time. There is only one EPS box for PANSAT. Other vital subsystems are redundant ; for example, the Digital Control Subsystem has two fully capable boxes. The batteries within the Electrical Power Subsystem itself are redundant, but must be able to be recharged to full capacity after each use to ensure proper Depth of Discharge. The batteries and the EPS will be discussed more fully in the following chapters.

B. SCOPE OF THESIS

The purpose of this thesis is to develop a transient thermal model of the Electrical Power System and the associated housing for the Petite Amateur Navy Satellite (PANSAT) . This thesis will also develop a steady state and transient analysis for the preliminary Nickel-Cadmium battery design, identifying any physical locations within the EPS and batteries where temperature limits are exceeded, and offering some recommendations for

passive thermal methods. Computer generated steady state and transient analyses using radiation, contact conductances and thermal capacitances through the equipment housing and the upper and lower equipment plates of the satellite were used to evaluate temperature ranges at the node points representing physical locations in the structure. To perform the analysis, circuit board layouts, heat dissipations of components, subsystem materials and cell efficiencies were required. Inward viewing box geometry was used to physically model the EPS and the battery model. Two models were used to verify steady state temperatures for the EPS. The transient analyses used equipment plate temperature profiles obtained from a recent transient analysis of the entire PANSAT structure.

4

II. BACKGROUND

A. PETITE AMATEUR NAVY SATELLITE (PANSAT)

PANSAT was initiated in 1989 to provide interdisciplinary educational opportunities in space related areas to prepare postgraduate students for follow on work in space systems acquisition and design, and to develop a cadre of engineers and technicians at the Naval Postgraduate School (NPS) capable of developing and producing space qualified hardware. The current PANSAT design is the result of five years of research by NPS thesis students and the personnel of the Space Systems Academic Group (SSAG). Preliminary Design Review (PDR) was held in 1993 with the Critical Design Review to be held in late 1994.

The payload will be a direct sequence spread spectrum with a differentially coded, binary phase shift keyed (BPSK) communications system with an operating frequency of 436.5 MHz. The satellite will relay messages on a user-to-user basis in a simplex mode. The store and forward communication will allow amateur radio operators to send and receive messages through several short windows daily.[FRD, 1993]

The spacecraft will weigh approximately 150 pounds and is being designed to launch as a secondary platform from the space shuttle as part of the Hitchhiker Program.   PANSAT has no attitude control and is free to tumble. Operational life is expected to be two years, with three to five minute communications segments per orbital pass. PANSAT will operate between 28.5° and 51.6° inclination and between 160-220 nautical miles.

The spacecraft consists of five subsystems: Communication (COMM), Electrical Power, Computer, Structure, and Ground Station Support.   This

5

thesis focuses on the Electrical Power Subsystem, where the thermal control functions reside.

The PANSAT structure is Aluminum 6061-T6, built about a main load bearing cylinder connected to a lower equipment plate. The satellite is a tumbler, and since the solar panels will be mounted on the spacecraft skin, maximizing surface area increases power generation. A 26 sided polyhedron was the chosen structural configuration, already demonstrated on a Shuttle launch. A view of PANSAT is shown in Figure 1.

Figure 1. PANSAT Design

B. ELECTRICAL POWER SYSTEM (EPS)

The power to PANSAT is provided by seventeen 256 cm^2 solar panels consisting of silicon (Si) solar cells. The solar cells are K6700 Si cells connected in series in 4 strings of 8 cells each. The EPS also consists of electrical components needed to generate, regulate, and provide $\pm$ 15 V and +5 V power for the various power control electronics. In eclipse, two Nickel-Cadmium batteries of ten cells each maintain the bus voltage at 12 Vdc. The EPS control interface provides the power switching of all modules on the printed circuit boards (PCBs) in the Digital Control Subsystem (DCS) and COMM. The watchdog timer in the EPS is used to reset the DCS in the event of a failure. The EPS is also dependent on the Ni-Cd batteries for voltage regulation during all modes of operation. An EPS block diagram developed by the SSAG is shown in Figure 2.

Figure 2.   Electrical Power System Block Diagram

Voltage sensors monitor the solar panel bus and battery voltages, and thermal sensors monitor the temperature of the solar panels, batteries and electronics housings. Figure 3 shows the solar panels and box placement. The triangular panels of the satellite do not have solar panels and could be used for passive thermal control if required. The EPS is mounted underneath the upper equipment plate, and above the DCS and batteries, which are mounted on the top of the lower equipment plate.

Figure 3. PANSAT Exploded View

PANSAT Design requirements include:

- 21.5 Watts at 15.2 Vdc average minimum electrical power at end of life (EOL)

- Minimum of 60 percent power conversion efficiency

- 12 Volt regulated bus

- Nickel-Cadmium batteries with a 10 percent Depth of Discharge (DOD)

- Mission life of 24 months [FRD, 1993]

Terrestrial Ni-Cd batteries are the chosen type due to high energy density, cycle life and reliability. Space rated batteries will not be used because of their prohibitively high cost. Figure 4 shows the proposed F-cell,

Figure 4. Ni-Cd Cell Dimensions

its 32 psi pressure relief valve and the cell dimensions. Although the F-cell has a pressure relief valve it is still considered a closed cell. The batteries will be fully discussed in Chapter VI.

III. STEADY STATE THERMAL ANALYSIS

A. BACKGROUND

A nodal analysis based on a finite difference model of PANSAT structure was performed in 1992 using the Intercept Thermal Analyzer Software Package. Input into the analyzer program is written by a model builder program which can be saved for modification for later use. THANSS is the model builder and the thermal analyzer is TASS. TASS provides the solution of Equation 3.1 using the Cholesky reduction in an iterative scheme

$$[A] \ x \ [T] \ = \ [B] \qquad\qquad 3.1$$

to solve for T (the node temperature vector). THANSS uses conductance paths to generate node to node conductances to form a set of heat balance equations (Equations 3.2, 3.4, and 3.13) where A is the matrix of conductances and B is a column vector of constant temperatures and heat inputs. The node temperatures obtained after each iteration are used to update the temperature dependent terms in the A matrix. This process continues until the change in the nodal temperatures between successive iterations is smaller than 0.05. When the iterative solution is obtained, the temperatures are then written into an output file. [Kraus, 1990]

This analysis resulted in a steady state temperature map of the PANSAT structure (including the square panels where the solar panels are mounted, the triangular panels, and both equipment plates). To accurately model the structure, the square panels were divided into nine equal nodes, the triangular panels were divided into six nodes, and the equipment plates eight nodes each. The model connects the nodes together through a network of user defined conduction paths and connects individual nodes

11

through constant temperature sinks through conduction and radiation. Results of the steady state analysis for sunlight and shadow zones both with internal heat dissipation are shown in Appendix A.

Conductance values are either calculated or input by the analyst from separate calculations. There are ten different modes that can be selected to characterize node-to-node heat flow. Three of these methods were used for analysis of the Electrical Power System: heat flow between nodes for conduction (method designator 1), heat flow between nodes for radiation (method designator 3), and a constant heat input (method designator 10). The heat balance equation for conduction is

$$q = K_1 \ (T_2 - T_1) \hspace{4cm} 3.2$$

with the conductance, K_1 determined from the Fourier Law and [A] = [K]

$$K_1 = k \ \frac{A}{\Delta L} \hspace{4cm} 3.3$$

where q is the heat flow, T_1 and T_2 define the node-to-node temperature difference for the path, k is the thermal conductivity of the material in Btu / ft - hr - °F or W/m° C, A is the cross sectional area for heat flow and L is the length of the heat flow path. The units of the conductance are Btu/hr ° F or W / ° C.

The heat flow equation by radiation is governed by the Stefan-Boltzmann Law shown in Equation 3.4.

$$q = \sigma \ F_A \ F_\epsilon \ A (T_2^4 - T_1^4) \hspace{3cm} 3.4$$

or

$$q = k_3(T_2 - T_1) \qquad\qquad 3.5$$

where

$$K_3 = \sigma\, F_A\, F_\epsilon\, A\,(T_2 + T_1)\,(T_2^2 + T_1^2) \qquad\qquad 3.6$$

Equation 3.6 derives from the fact that T_2^4 - T_1^4 can be written as the sum
and difference of squares

$$(T_2^4 - T_1^4) = (T_2^2 + T_1^2)(T_2^2 - T_1^2) = (T_2^2 + T_1^2)(T_2 + T_1)(T_2 - T_1) \qquad 3.7$$

Here σ is the Stefan-Boltzmann constant (1.713 x 10^{-9} Btu/ft^2-R^4 or
5.669 x 10^{-8}W/m^2-K^4), F_A is the arrangement or shape factor and F_E is the
emissivity factor. For radiation between two non-black surfaces, (where a
blackbody is a perfect absorber and emitter of radiation), the emissivity and
absorptivity of the surfaces will not be equal to 1. The departure from ideal
surfaces for two infinite plates in full view of one another is

$$F_E = \cfrac{1}{\cfrac{1}{\epsilon_1} + \cfrac{1}{\epsilon_2} - 1} \qquad\qquad 3.8$$

where ϵ_1 is the emissivity of the first plate and ϵ_2 is the emissivity of the
second plate. [Class notes AA 3804, July 1993] This closely approximates
the configuration of the two printed circuit boards (PCBs) in the EPS. The
shape factor (F_A) accounts for the situation where the alignment of the
surfaces prevents the interception of all of the emissions from the source.
Other terms used to describe the shape factor include view, configuration
and arrangement factor.

For radiation, TASS handles the heat flow by developing K_3
to permit the use of a linear temperature difference (Equation 3.9)

13

.

$$q_r = K(T_2 - T_1) \qquad 3.9$$

by computing K_3 from

$$K_3 = \frac{\sigma \, A \, F_A \, F_E (T_2^4 - T_1^4)}{T_2 - T_1}$$

$$= \frac{\sigma \, A \, F_A \, F_E (T_2^2 + T_1^2)(T_2^2 - T_1^2)}{T_2 - T_1}$$

$$= \frac{\sigma \, A \, F_A \, F_E (T_2^2 + T_1^2)(T_2 + T_1)(T_2 - T_1)}{T_2 - T_1} \qquad 3.10$$

so that K_3 is indeed

$$K = \sigma \, A \, F_A \, F_E (T_2^2 + T_1^2)(T_2 + T_1) \qquad 3.6$$

Because heat transfer by radiation is governed by

$$q = \sigma \, F_A \, F_E \, A (T_2^4 - T_1^4) \qquad 3.4$$

the conductance value is entered by the user so that

$$q = K(T_2 - T_1) \qquad 3.11$$

The user needs only to enter the value
and TASS handles the computation in accordance with Equation 3.6.

14

.

$$K = \sigma \, F_A \, F_E \, A \qquad\qquad 3.12$$

When a node is to have a constant temperature input, a tag of 10 is entered and the connecting node is specified as 999. Thus the third method of heat flow is in the form

$$q = K_q \qquad\qquad 3.13$$

where K_q is a constant.

B. BOUNDARY CONDITIONS FOR EPS ANALYSIS

The steady state structural analysis of PANSAT was conducted in 1992 with the transient analysis of the structure completed in January 1994. The segmented panels (or nodes) were taken individually to determine the number of connections (also known as branches) to other nodes. The type of connection (i.e., the mode of heat transfer for conduction, radiation and constant temperature) is specified as the tag number for the particular branch. Tag is used to avoid confusion between node and mode. Constant temperatures are given node numbers, beginning with 301. A total of 983 conductances from 232 nodes determined the total PANSAT thermal model. When the thermal analysis was run, the first file was a summary of the final temperatures of all the nodes, and was followed by the node temperatures after each iteration.

Models were run for steady state conditions in sunlight and shadow with and without internal heat dissipation. The runs with heat dissipations were used because the satellite low power mode is not much less than the high power mode. Appendix A shows that for the steady state analysis for sunlight with internal heat dissipation the temperatures range from 45.3 °C to 60.2 °C. The steady state analysis in the shadow zone (Appendix B) with

15

internal heat dissipation resulted in a temperature range of -70.6 °C to 66.6°C.

A transient analysis for the satellite was performed a year later using the same nodes. Average temperatures for the upper equipment plate for the first fourteen orbits are plotted in Figure 5, and for the lower equipment plate in Figure 6. Starting temperature was assumed to be 25 ° C for Kennedy Space Center temperatures in October. Table 2 and Table 3 show the data breakout by node numbers for the upper equipment plate (nodes 211 to 218) and the lower equipment plate (node numbers 219 to 226). The average temperatures for the equipment plates were used as boundary conditions for the transient analysis of the Electrical Power System and the steady state and transient battery analysis.

Figure 5. Upper Equipment Plate Average Temperatures

Figure 6. Lower Equipment Plate Average Temperatures

17

PASS	211	212	213	214	215	216	217	218
1	28.8	29.3	29.3	29.3	27.2	26.9	26.5	26.3
2	28.8	30.4	30.4	29.3	28.1	27.8	27.3	27.1
9	30.5	31.1	31.1	23.0	28.7	28.4	28.0	27.6
4	31.0	31.2	31.7	30.6	29.3	28.9	28.5	28.2
5	31.5	32.2	32.1	31.5	29.8	29.4	29.0	28.7
8	31.5	32.6	32.6	31.4	30.2	29.3	29.4	29.1
7	32.3	33.0	32.5	31.5	30.6	30.2	29.8	29.5
8	32.9	33.3	33.3	32.2	30.9	30.6	30.1	29.8
9	32.9	33.6	33.6	32.5	31.2	30.9	30.4	30.1
10	33.2	33.9	33.3	32.2	31.5	31.1	30.2	30.4
11	33.4	34.1	31.1	33.0	31.4	31.4	30.9	30.6
12	33.8	34.3	34.3	33.2	31.6	31.6	31.1	30.8
13	33.8	34.5	34.5	33.3	32.1	31.4	31.3	31.0
14	34.0	34.7	34.6	33.5	32.2	31.9	31.5	31.2

Table 2.   Upper Equipment Plate Temperatures in Degrees C by Node

PASS	219	220	221	222	22●	224	225	226
1	29.2	28.0	29.8	28.2	27.7	27.8	27.8	27.9
2	29.2	29.3	29.3	29.3	28.8	23.0	29.0	28.9
3	30.6	30.7	30.7	30.4	23.0	29.8	29.2	29.7
3	30.6	31.3	31.7	30.7	30.3	30.4	30.4	30.3
6	31.6	31.3	31.4	30.7	30.3	30.4	30.4	30.3
6	31.6	32.3	32.4	31.7	31.3	31.4	31.4	31.3
7	32.0	32.7	32.7	32.1	31.7	31.8	31.6	31.7
8	32.4	33.1	33.1	32.1	32.0	32.2	32.1	32.1
6	32.7	33.4	33.4	32.7	32.3	32.5	32.4	32.4
10	32.9	33.6	33.7	33.0	32.5	32.7	32.7	32.9
11	33.2	33.9	33.6	33.2	32.8	33.0	32.9	32.9
12	33.1	34.1	34.1	33.4	33.1	33.2	33.1	33.1
1●	33.5	34.2	34.3	33.6	33.7	30.3	33.3	33.2
14	33.7	34.4	34.4	33.8	33.3	33.5	33.4	33.4

Table 3.   Lower Equipment Plate Temperatures in Degrees C by Node

19

IV. STEADY STATE ANALYSIS OF THE EPS USING THANSS

A. PROCEDURE THEORY

A thermal resistance may be defined as the reciprocal of the conductance.

$$R = \frac{1}{K} \qquad 4.1$$

R is the resistance in ° F-hr/ Btu or ° C/W. This relationship does not apply exclusively to the conduction mode of heat transfer . If the analogy exists between the heat flow and the direct current statement of Ohm's Law

$$q = K \Delta T = \frac{\Delta T}{R} \qquad 4.2$$

then it is analogous to

$$I = \frac{\Delta V}{R_E} \qquad 4.3$$

where R_E is the electrical resistance and all of the d-c network thorems apply. The addition of thermal resistances in series and the combination of resistances in parallel are permitted operations. For example, the combination of two resistors in series is given by

$$R_C = R_A + R_B \qquad 4.4$$

and in parallel where R_C is the equivalent resistance.

$$R_C = \frac{R_A R_B}{R_A + R_B} \qquad 4.5$$

21

.

B. DESCRIPTION OF NODES

To simplify calculations and to assure accuracy in the node descriptions, the printed circuit boards were divided into 72 nodes with each node having an area of 1 square inch. This size results in relatively easy calculations when using areas and lengths between nodes and between printed circuit boards. The top board nodes were numbered 1-72 with the bottom board nodes numbered 73-144. Appendix C shows the node numbering, which will be used for reference later in this chapter.

The boards have six layers, alternating copper and epoxy. It was assumed for the analysis that copper covered 25% of the top layer. This takes circuit board components into consideration. This layer is designated by R_1. The other two copper layers were assumed to have 100% coverage and are designated by R_4. The epoxy layers are homogeneous. Figure 7 describes the Node 1 to Node 2 upper board conductances. Appendix 3 shows the node numbers and their relationshps for reference. R_2 describes the conductance of the polyimide (epoxy) layers in each node. To calculate the resistances of R_1 through R_4 Equation 4.6 is used.

$$R = \frac{12 \ L_i}{k_i \ w_i \ (th_i)}$$
4.6

where L is the lenght of the heat flow path, th is the thickness of the contact area, w is the width, and k is the thermal conductivity of the material. Each epoxy layer is 0.01933 inches thick: each copper layer is 0.00134 inches thick. Table 4 lists the resistances calculated by equation 4.6 for the network shown in Figure 7. R_A through R_E are the equivalent resistances as the network is calculated, beginning with resistance R_A and working to resistance R_E. A sample calculation is included for resistance A.

Figure 7.   Electrical Power System Node 1 to Node 2

$R_i^{\#}$	L_i	w_i	th_i	k_i	R_i
1	1.00	1.00	0.00134	385 (.25)	93.04129
2	.01933/2	1.00	1.00	0.15	0.77320
3	1.00	1.00	0.01933	0.15	4138.645
4	1.00	1.00	0.00134	385	23.26032

Table 4.   Node 1 to Node 2 Resistances

$$R_A = \frac{(R_3 + R_2 + R_2)\, R_4}{R_3 + R_4 + 2\, R_2} \qquad\qquad 4.7$$

As a result, for Node 1 to Node 2

$$R_A = 23.13037$$
$$R_B = 24.53051$$
$$R_C = 12.79438$$
$$R_D = 13.79438$$
$$R_E = R_T = 13.16939$$

Using Equation 4.1, K = 0.075934 °F-hr / Btu.

The node 1 to node 9 calculations are based on the same relationships, so that conductance is 0.075934 °F- hr / Btu.

For the radiation from board to board

$$K = 0.1732\, F_A\, F_E\, A \qquad\qquad 4.8$$

F_A = 1.00 because the boards are parallel to each other.

$$F_E = \frac{1}{\dfrac{1}{\epsilon_1} + \dfrac{1}{\epsilon_2} - 1} \qquad\qquad 3.8$$

24

.

Because the emissivity of both boards is assumed to be 0.8, $F_E = 0.6667$.
After converting the node area into square feet

$$K = 0.1732 \ (1.0) \ (\frac{2}{3}) \ (\frac{1}{144}) \ = \ 0.801852 \ x \ 10^{-3} \qquad 4.9$$

Figure 8 describes the contact of the board layers to the housing rails.

Figure 8. PCB Layers To Housing Conductances

Resistance R_1 is copper and resistance R_2 is epoxy. Resistances R_3 and R_4
are contacts with the railings.

R_1 is half that of the previous R_1 (the path length has been halved).

$$R_2 = \frac{(12)(0.01933/2)}{(1)(0.2)(0.15)} \qquad 4.10$$

$$h_c = 500 \text{ for copper contact}$$

$$h_c = 400 \text{ for epoxy contact}$$

$$R_4 = \frac{1}{400(0.2)(1/144)} = 1.88 \qquad 4.11$$

$$R_3 = \frac{1}{500(0.2)(1/144)} = 1.44 \qquad 4.12$$

Figure 9 is a simplification of Figure 8.

Figure 9. Equivalent Conductance of Figure 8

26

The equivalent resistance from the network shown in Figure 9 (R_T) = 47.88. K_T is the equivalent conductance, or 0.020885 ° F-hr/ Btu.

Once the conductances were calculated an input file was created, listing the conductances for each node with its associated mode. The input file is shown in Appendix D. The conductance values are listed by node. Beginning at lines 7 and 8 in Appendix D, the node equation describes what node is connected to what, by how much, and by which tag. At line seven, the fixed point integer values are connections and tags. Table 5 describes Node 1 connections contained in line 7.

NODE CONNECTION	POSITION	HOW	TAG
2	TOP PCB	CONDUCTION	1
9	TOP PCB	CONDUCTION	1
73	BOTTOM PCB	RADIATION	3
301	CONSTANT TEMPERATURE	CONDUCTION	1
303	CONSTANT TEMPERATURE	RADIATION	3

Table 5. Node Connections To Node 1

Line 8 contains floating point real numbers which are the appropriate conductance values for the connection. Each node requires an even number of lines. The three constant temperatures defined for the railings and housing were all 33.5 °C. Appendix E lists the heat dissipation by node in watts. The conductances need only be input in one direction as THANSS calculates the reverse connection automatically.

27

.

Table 6 lists the results of the steady state analysis of the circuit boards. The highest temperatures appeared on the bottom boards where the heat dissipations were the highest. However, the amount of dissipated heat is relatively low. Temperatures ranged from 34.42 °C to 36.31 °C on the upper board to 34.77 ° to 38.02 °C on the lower board, well within standard operating temperatures for electronic piece parts. A run at 25 °C constant heat source temperatures compared very favorably with an earlier steady state analysis performed using the Integrated Thermal Analysis System (ITAS).

PRINTED CIRCUIT BOARDS - S PATTERSON - RUN A
Temperatures, degC

```
  1  35.38   2  35.78   3  35.96   4  35.92   5  35.80   6  35.67
  7  35.48   8  35.19   9  35.62  10  36.14  11  36.31  12  36.12
 13  35.88  14  35.72  15  35.54  16  35.34  17  35.56  18  36.00
 19  36.15  20  36.10  21  35.91  22  35.71  23  35.48  24  35.18
 25  35.65  26  36.16  27  36.24  28  36.25  29  35.95  30  35.64
 31  35.36  32  35.00  33  35.48  34  35.91  35  36.05  36  36.05
 37  36.07  38  35.56  39  35.24  40  34.90  41  35.55  42  35.96
 43  35.80  44  35.69  45  35.58  46  35.32  47  35.10  48  34.86
 49  35.36  50  35.60  51  35.65  52  35.42  53  35.27  54  35.08
 55  34.87  56  34.63  57  35.01  58  35.34  59  35.28  60  35.17
 61  35.06  62  34.91  63  34.72  64  34.49  65  34.80  66  35 03
 67  35.08  68  35.04  69  34.95  70  34.81  71  34.64  72  34.42
 73  35.53  74  36.12  75  36.49  76  36.67  77  36.91  78  37.19
 79  37.02  80  36.25  81  35.66  82  36.56  83  36.93  84  36.90
 85  37.20  86  38.02  87  37.99  88  36.51  89  35.63  90  36.28
 91  36.75  92  37.10  93  37.32  94  37.94  95  37.80  96  36.43
 97  35.63  98  36.23  99  36.82 100  37.78 101  37.44 102  37.35
103  37.06 104  36.08 105  35.46 106  36.01 107  36.63 108  37.69
109  37.25 110  36.91 111  36.50 112  35.74 113  35.43 114  35.90
115  36.26 116  36.54 117  36.55 118  36.43 119  36.15 120  35.46
121  35.11 122  35.60 123  35.75 124  35.91 125  36.05 126  36.03
127  35.83 128  35.23 129  34.85 130  35.18 131  35.38 132  35.53
133  35.68 134  35.70 135  35.55 136  35.02 137  34.71 138  34.99
139  35.19 140  35.32 141  35.41 142  35.38 143  35.21 144  34.86
301  33.50 302  33.50 303  33.50
```

Figure 10.   PANSAT PCB Temperature by Node

V. TRANSIENT ANALYSIS OF EPS USING ITAS

A. GEOMETRY GENERATION

To begin the analysis of the electrical power system, the geometry of the EPS was reproduced in the computer using the Integrated Thermal Analysis System (ITAS). The geometry was generated by piecing together, rotating and translating shapes from a geometry generation menu. These shapes were then stored in a PARTS file, which were then selectively plotted to allow for surface number and node number displays. The EPS was divided into three distinctly separate entities: the housing and the upper and lower circuit boards. Figure 10 and Figure 11 show the surface numbers and corresponding node numbers for the EPS housing. Each surface generated by ITAS is accessible for thermal node definitions and optical

Figure 10. EPS Housing Surface Nodes

Figure 11.   EPS Housing Node Numbers

properties definition. The housing is modelled as a six-sided box having 12
physical nodes. The dimensions of the housing are 9 inches in the X
direction, 8 inches in the Y direction, and 1.569 inches in the Z direction. It
is mounted underneath the upper equipment plate as seen in Figure 2 and
Figure 3.

The upper printed circuit board is modelled as two four sided
polygons. The polygons have node numbers from 2.01 to 2.18 and 3.01 to
3.12. This division of the upper equipment panel was done to accurately
represent heat dissipations on the board and to define a workable number of
conductance values. Appendix F shows both the surface numbers and node
numbers for the upper PCB.

The lower PCB was constructed from 5 separate polygons: these node numbers ranged from 4.00 to 8.00. Appendix G shows the surface numbers and corresponding node numbers for the lower PCB. Figure 12 is a view of the integrated thermal nodes of both PCBs and the housing.

Figure 12. Geometry Model of the Electrical Power System

B.   THERMAL PARAMETERS

1.   Radiation Conductance Parameters (Script-F)

Script-F factors are the energy quantities incident on each of the surfaces of an enclosure after multiple reflections from the surrounding surfaces. (ITAS User's Manual). The Script Fs are in the IR wavelength and are used during the thermal analysis to account for all thermal radiation interchange, and are calculated from the blackbody view factors in

31

conjunction with surface optical properties. Since the EPS is an enclosure with no view to space, the program is set to ignore the space node inclusion in the Script F calculations since surfaces inside the enclosures do not "see" surfaces outside the enclosure. [ITAS User's Manual, 1992]

2. Optical Properties Data

The optical properties data defines the properties of all surfaces and combines the geometric surfaces that have been created into thermal nodes. The optical properties listed in the Material Properties Library of ITAS were used for the housing (Aluminum 6061-T6) and for the copper layers of the printed circuit boards. These properties include the solar absorptivity (alpha) and infrared emissivity (epsilon) values. Individual capacitances and thermal dissipations were not defined in these screens but were defined in the User Node section. The surfaces that are listed in the Optical Properties entries in Appendix H are the geometric surfaces that ITAS generates.

3. Non-Geometric Node Definitions

In addition to the Optical Property node generation, additional non-geometric nodes were created. These nodes do not have a physical presence in ITAS. Examples of these nodes included the rails in the EPS housing to which the circuit boards are secured; the PCB board layers, which alternate copper and polyimide; the upper equipment plate, to which the top of the EPS is mounted; and the component pin nodes. Table 6 indicates the non-geometric node assignments. These nodes are also known as diffusion nodes: diffusion nodes, although not part of the ITAS geometry file still have finite mass. Nodes are not numbered consecutively to allow for flexibility and also to allow easy identification. For example, all nodes that are numbered 9XX are either housing or railing nodes: all of these nodes are

32

.

made of aluminum. Nodes 16XX and 6XX, 14XX and 4XX, 12XX and 2XX are all copper layers of the printed circuit boards.

Node Number	Identification	Node Number	Identification
901-912	EPS housing	913	Equipment Plate
921-926	EPS rails	201-230	Top PCB top Cu
401-430	Top PCB mid Cu	501-530	Top PCB bot Cu
1201-1217	Bot PCB top Cu	1401-1417	Bot PCB mid Cu
1601-1617	Bot PCB bot Cu	101-130	Top PCB T poly
301-330	Top PCB M poly	501-530	Top PCB B poly
1101-1117	Bot PCB T poly	1301-1317	Bot PCB M poly
1501-1517	Bot PCB B poly	2XXX	Pins-Top PCB
3XXX	Pins- Bot PCB		

Table 6.   Non-Geometric Node Numbers

The thermal capacitance of the diffusion nodes is entered in this screen. Thermal mass is also another name for thermal capacitance.

$$Thermal\ Mass = C = c\ \rho\ V \qquad\qquad 5.1$$

where c is specific heat in cal/g °C,

ρ = density of the material in kg/m^3,

V = volume of the material in m^3.

ITAS requires C to be in W-min / °C. To convert to the correct units the following conversion factor is used.

$$C = (\frac{cal}{g \, ^{\circ}C}) \, (\frac{kg}{m^3}) \, (m^3) \; = \; \frac{cal}{(.001)^{\circ}C} \qquad\qquad 5.2$$

$$1 \; cal = 1.163 \; x \; 10^{-6} \; kw\text{-}hr = 1163 \; x \; 10^{-6} \; W\text{-}hr \qquad\qquad 5.3$$

$$1163 \; x \; 10^{-6} \; W\text{-}hr = 6.978 \; x \; 10^{-2} \; W\text{-}min \qquad\qquad 5.4$$

$$\frac{6.978 \; x \; 10^{-2} \; W\text{-}min}{(0.001) \; ^{\circ} \; C} = 69.78 \; W\text{-}min/^{\circ} \; C \qquad\qquad 5.5$$

This is the conversion factor used in Appendix I to calculate the thermal masses of all physical nodes. The following values were used in the calculations. [Penton Publishers, 1986]

EPS Housing Thickness	0.2 in
Equipment Plate Thickness	0.125 in
PCB Board Copper Layer	0.000134 in
PCB Board Poly Layer	0.001933
Density of Aluminum	2728 kg/m³
Density of Polyimide	1950 kg/m³
Density of Pin Material	8378 kg/m³
Density of Copper	8666 kg/m³
Specific Heat of Al	0.199 cal/kg °C
Specific Heat of Cu	0.098 cal/kg °C
Specific heat of Ni-Steel	0.11 cal/kg ° C
Specific Heat of Polyimide	0.31 cal/kg °C

Since ITAS allows total capacitance of each surface of the nodes to be entered into the model if the remaining surfaces are zeroed out. For pin

34

conductances, the total thermal mass of the pins in each major node were considered as one node. For example, Node 2011 is the total capacitance of all pins through the top layer of geometric node 3.01.

Heat dissipations were also entered in this screen. These dissipations were obtained from the PANSAT design team. The component list and PCB board layouts are included as Appendix J. The top board design is currently much more mature than the lower board design and estimated heat dissipations were more accurate. Appendix K is the Node Data Entry for Thermal Analysis for the EPS.

4. Conductance Definitions

All conductances entered into the EPS model were defined as linear (two way); this type of conductance also applies to the nodes defined by ITAS. All conductance values were precalculated and entered into the model: unlike THANSS, radiation modes are calculated by ITAS. Equation 3.3 was used to calculated all conductances not involving contact conductances.

$$K = \frac{k\,A}{L} \qquad\qquad 3.3$$

Conductances not involving contact conductances included EPS housing to housing nodes; EPS housing to railing nodes (since the rails will be part of the housing); copper board nodes to copper board nodes and polyimide to polyimide nodes: and pin segment nodes to pin segments. Pins were modeled as one equivalent pin through each geometric node; however, each pin was divided into six nodes since they traverse through the board layers.

5. Contact Conductances

Contact conductance is defined in Equation 5.6.

$$h_c = \frac{(1.25)(k_s)(\frac{P}{H})^{.95}}{S_r} \qquad 5.6$$

$$k_s = \frac{2\ k_1\ k_2}{k_1 + k_2} \qquad 5.7$$

where   P = contact pressure of the surfaces, chosen as 15 psi for all

contact.

H = hardness of the material. Brinell hardness numbers were

used.

S_r = surface roughness

To calculate total conductance, first the conductance of the first material is calculated using Equation 3.3, resulting in K_1. Then the conductance of the second material is calculated, resulting in K_2. The total conductance (K_T) is calculated by Equation 5.8, with the results in W /° C.

$$K_T = \frac{1}{\frac{1}{K_1} + \frac{1}{h_c} + \frac{1}{K_2}} \qquad 5.8$$

The ITAS node-to-node conductance calculations are shown in Appendix L, with the conductance data entry in Appendix M.

6. Temperature Profile

ITAS uses temperature profiles for time varying boundary nodes. Boundary nodes without time variation must be input into the user-node definition section.   A temperature profile (Figure 13) of the upper equipment

36

.

plate obtained from the THANSS/TASS transient analysis of the spacecraft structure used in the EPS analysis. The initial temperature was an estimate of Kennedy Space Center temperatures in October.

Figure 13.   ITAS Temperature Profile For Equipment Plate

VI. THERMAL ANALYSIS OF BATTERIES

A. NICKEL-CADMIUM BATTERIES

Batteries can either be primary or secondary; secondary batteries can be recharged and reused. Batteries are made of cells that can be linked together in series or parallel. Cells linked in series have the positive terminal linked to the next cell's negative terminal: in a parallel connection positive terminals are linked to positive terminals and negative to negative. PANSAT's two batteries have 10 cells each linked in series. In series connections the voltage of the connected cells add while the capacity (normally measured in ampere hours) remains constant.

Sealed nickel cadmium cells operate as a closed system that recycle gases created within the cell, so that no electrolye is lost. Sealed cells with a resealable vent for safety are still considered sealed cells. Nickel-cadmium cells (Ni-Cd) have a higher energy to volume ratio than most other secondary batteries, have a relatively high rate of discharge, and can recharge quickly. Ni-Cd batteries are known for their long storage and operating life, can operate over a wide range of temperatures and environments maintenance free. Additionally, Ni-Cd batteries can handle continuous overcharge so the battery can be maintained in a ready state until needed. [Gates Energy Products, 1992]

Temperature is a very important condition for Ni-Cd batteries. The effective internal resistance of these cells is at a minimum when cell temperature is between 20 °C and 40 °C. Figure 14 shows the relationship between cell disharge temperature and the effective internal resistance. Temperature also effects a cell's effective no-load voltage. For an Ni-Cd

cell, the effective no-load voltage is near the peak at room temperature: the decline is more pronounced at cooler temperatures. Figure 15 shows the

Figure 14. Cell Discharge Temp vs Internal Resistance "From Ref. [Gates, 1992]".

Figure 15. Cell Discharge Temperature vs No-Load Voltage "From Ref. [Gates, 1992]".

relationship between cell discharge temperature and no-load voltage.

An increase in cell temperature also has a negative effect on cell capacity. At elevated temperatures more charge is required for the cell to

become fully charged, and the higher temperatures also decrease the cell capacity to below standard. Cell capacity while charging is not normally affected by temperatures below 23 °C, however, lower temperatures (below 23 °C) have a negative effect on cell capacity during discharge. Room temperature is the ideal environment for PANSAT's batteries. Space rated Ni-Cd batteries would be the technical choice for PANSAT; however, the cost of space rated batteries (approximately $200,000) is prohibitive.

PANSAT batteries are redundant: only one battery will operate at a time. However, the batteries must recharge to full capacity between each use for optimum performance. The current power budget is being examined to determine how long each battery will take to recharge after each use. A typical Ni-Cd battery will require about 160% of energy stored to recharge.

B. BATTERY GEOMETRY MODEL

To model the PANSAT battery, it was necessary to include the Digital Control Subsystem and the Electrical Power Subsystem in the model due to the proximity in the spacecraft. The model was built using ITAS. The two batteries and the DCS were the mounted on the lower equipment plate, built by connecting seven polygons. The spacecraft structure was built around the lower equipment plate, and the upper equipment plate, with the Electrical Power Subsystem (EPS) attached was added. The build progression is demonstrated in Appendix N. The geometric battery thermal model is shown in Figure 16.

After building the geometry model each surface was assigned a surface number and a node number. An example of this assignment is shown in Appendix O. The surface number and node number are related in the property data information of the model, shown in Appendix P. This is where the absorptivities and emissivities of the structure and box housings

41

Figure 16. Battery Thermal Model

are listed. Since the box housing designs are not finalized, Aluminum- 6061-T6 was chosen. This material has an absorptivity of 0.4 and an emissivity of 0.79. Additionally, every surface on the boxes is given its own surface number and node number.

C. BOUNDARY CONDITIONS

Since a large percent of the model required the incorporation of PANSAT's structure, boundary nodes were used to define temperatures on areas that had already been analyzed. Surfaces that were defined as boundary nodes have temperatures which remain constant. The results from the transient analysis of PANSAT's structure were used. The structure was divided into areas as seen in Figure 17. Each square area is divided into nine

42

equal nodes: the triangular areas are divided into six unequal nodes. The sections affecting the battery model are sections one through eight.

Figure 17. PANSAT Structural Divisions

Appendix Q lists the transient temperatures with internal heat dissipation by node for the shadow and sunlit zones for orbit 14. This was chosen since the spacecraft temperatures are leveling out: however, worst case

43

temperatures were not extrapolated. Table 7 relates the structural number of Figure 17 to the node numbers of Appendix Q, and then lists the average temperature for that area for both shadow and sunlight.

SECTION	NODE NUMBERS	AVG. TEMP SHADOW	AVG. TEMP SUNLIGHT	S/C AREA
8	1-9	30.6	33.4	WALL
2	10-18	32.7	39.9	WALL
3	19-27	33.2	38.8	WALL
8	28-36	28.7	31.1	WALL
5	37-45	30.8	39.9	WALL
6	46-54	33.4	33.3	WALL
7	55-63	33.4	33.3	WALL
8	64-72	28.7	28.6	WALL
N/A	219-226	32.9	33.7	LOWER PL
N/A	211-218	32.1	32.9	UPPER PL

Table 7.   Average Temperatures in Celcius for Pass 14

These temperatures were used as boundary nodes, indicated as negative numbers in Appendix R. This appendix also lists the thermal masses (capacitances) for all hardware nodes. The explanation for thermal mass calculation is contained in Chapter V; the thermal mass calculations are included as Appendix S. Heat inputs to each box were estimated and defined in Appendix R as a node with no mass. This heat input was attached to the six walls of the housing where that heat input resides, and

44

.

the heat was conducted outward through the walls. EPS boundary conditions were derived from the transient analysis.

Conductance values were calculated as in Chapter V and included in the ITAS Conductor Data Entry. Only surfaces within the boxes themselves or conductances between the heat nodes and the boxes are included since the upper plate, lower plate, and sidewalls are defined to have constant temperatures.

46

VII. RESULTS AND RECOMMENDATIONS

A. ELECTRICAL POWER SYSTEM

The analysis of the EPS transient analysis can be divided into three areas; the housing nodes, the upper board nodes, and the lower board nodes.

1.   EPS Housing Nodes

Figures 18 and 19 show the temperature versus time plots for the EPS housing sidewalls and the top and bottom of the housing. As it would be be expected for a node which touches the outside edges of the housing, the

Figure 18.   EPS Housing Temperature Trends

temperatures start low and become warmer. The bottom plate in the EPS housing would tend to be warmer than the top because the bottom has

47

TOP/BOTTOM EPS HOUSING NODES 906/912

Figure 19.   EPS Housing Trends

more heat dissipation. One drawback to the present analysis is that there was only enough information for a temperature profile of the lower equipment plate for 14 orbits. This, in effect, results in a transient analysis for that period of time and a steady state analysis for the following time.

2. Printed Circuit Boards

From Figure 20 it is apparent that any node that is attached to the housing sidewalls is going to experience a trend similar to the housing itself. In the case of the top PCB, nodes which butt up to the housing start cold and see a decreasing slope, starting to level off after about 17 hours. Nodes that do not touch the sidewalls (midboard in this case) remain between 20°C to 25 °C for the duration. This board remains cooler than the bottom PCB because the heat dissipations in the upper board are relatively low.

48

TOP PCB TEMPERATURES

Figure 20. Upper PCB Results

The bottom PCB, as shown in Figure 21, has a similar curve for those nodes which attach to the rails, with the resulting final temperature very similar to the upper PCB. However, midboard nodes are approximately 4-5 degrees warmer on the bottom board, where the highest heat dissipations are concentrated.

Figure 21. Bottom PCB Trends

B. BATTERIES

A steady state analysis was performed first on the battery. A copy of the results of both the steady state and the transient analysis is included as Appendix V. The transient analysis shows Battery A, Battery B, and the DCS at 33.7 ° C.

ITAS would not allow the model to be run as an enclosure. An ideal case would have been to run the battery first as an enclosure similar to the procedure used for the EPS. Since the cell information was not available, this run was performed to give a general battery environmental range. The analysis was effectively a steady state analysis since most of the structure had boundary nodes attached. This temperature is within the advertised

50

.

advertised operating ranges for a battery but is some distance from the ideal 23 °C. A second analysis was performed simulating a layer of Multilayer Insulation (MLI) on the bottom of both batteries. The result of this analysis can be seen from Figure 22. Although the initial temperatures are lower, the boxes quickly heat up. A third run insulating all six sides reduced the temperature by 3 °C to 30.7 °C.

Figure 22. Temperature vs Time for Battery with MLI

51

C. RECOMMENDATIONS

To make the thermal analysis more realistic for the Electrical Power System, duty cycles for the printed circuit boards need to be established. This would give a more accurate time versus temperature plot. For the batteries, cell selection would allow the modelling of the cells inside the batteries as demonstrated in Appendix W. Dissipations for the high power use boxes would contribute to the accuracy of the model. As the individual boxes are created by ITAS, the spacecraft subsystems can be combined into a viable and accurate spacecraft model.

This analysis is only as accurate as the boundary conditions. This model should be rerun when boundary conditions obtained from the transient analysis of PANSAT structure using ITAS are completed.

ITAS was created to model spinning and stationary spacecraft. When PANSAT design is mature enough to run the entire model, there is an option in the Parameter Set Up and Alteration Menu for user defined spacecraft attitudes, where the satellite can be rotated in time on the X-Y-Z axes to more accurately represent a tumbling body.

ITAS can accurately represent the orbit of the satellite, and allows two methods. The first method requires the definition of the inclination, sun Right Ascension and Declination, and the Longitude of the Ascending Node. The other method requires definition of the beta angles. Both methods define perigee and apogee, so that time spent in sunlight and time spent in shadow are considered in the satellite's environment. The most likely orbit, looking ahead with shuttle mission manifests, suggests planning for a 51.6° inclination and a 213 NM circular orbit.

APPENDIX A. PANSAT STEADY STATE TEMPS IN SUNLIGHT

PANSAT - STEADY STATE - SUNLIGHT ZONE - WITH INTERNAL HEAT DISSIPATION
Temperatures, degC

1	54.98	2	57.32	3	59.02	4	53.88	5	56.55	6	58.84
7	53.63	8	55.55	9	57.55	10	64.39	11	65.71	12	65.90
13	64.44	14	66.16	15	66.49	16	61.06	17	62.18	18	62.52
19	64.12	20	63.05	21	61.13	22	65.46	23	64.24	24	61.74
25	62.28	26	61.51	27	59.63	28	55.48	29	53.59	30	52.79
31	54.99	32	52.71	33	51.62	34	53.55	35	52.01	36	51.35
37	51.82	38	51.59	39	51.60	40	50.76	41	50.59	42	50.82
43	51.37	44	51.37	45	51.53	46	51.62	47	51.80	48	52.02
49	52.04	50	52.41	51	52.65	52	52.10	53	52.33	54	52.55
55	52.52	56	52.34	57	51.47	58	52.86	59	52.60	60	51.47
61	53.11	62	52.98	63	52.18	64	48.10	65	47.91	66	49.27
67	47.95	68	47.46	69	48.96	70	48.85	71	48.42	72	49.51
73	49.42	74	52.32	75	58.48	76	51.94	77	56.38	78	59.60
79	53.83	80	57.12	81	59.59	82	64.99	83	64.86	84	63.83
85	65.70	86	65.11	87	66.18	88	62.35	89	59.82	90	57.10
91	64.39	92	62.35	93	59.92	94	63.36	95	61.71	96	59.46
97	52.58	98	51.86	99	52.36	100	51.26	101	53.86	102	52.37
103	48.07	104	44.92	105	44.12	106	48.10	107	46.00	108	45.74
109	50.27	110	49.21	111	48.95	112	45.59	113	45.67	114	47.48
115	47.75	116	49.05	117	49.52	118	44.90	119	44.92	120	45.32
121	46.75	122	46.39	123	46.29	124	49.21	125	48.94	126	48.41
127	45.90	128	46.22	129	44.97	130	45.43	131	46.38	132	47.89
133	49.96	134	51.51	135	53.56	136	47.60	137	49.41	138	53.08
139	46.96	140	48.34	141	53.13	142	57.85	143	58.21	144	58.69
145	58.77	146	62.04	147	62.32	148	57.53	149	56.13	150	54.21
151	57.53	152	54.98	153	52.82	154	56.64	155	53.07	156	51.50
157	50.39	158	49.35	159	49.92	160	49.00	161	50.82	162	50.60
163	50.26	164	50.41	165	50.65	166	48.66	167	48.35	169	49.35
169	48.97	170	47.28	171	49.22	172	50.37	173	50.63	174	50.98
175	51.27	176	54.24	177	54.37	178	51.72	179	51.14	180	50.49
181	50.83	182	49.86	183	48.86	184	50.46	185	48.74	186	48.11
187	47.21	188	47.06	189	47.15	190	46.91	191	48.63	192	48.54
193	44.30	194	46.16	195	50.51	196	44.97	197	47.58	198	52.66
199	46.52	200	49.44	201	54.75	202	47.11	203	46.56	204	47.86
205	46.43	206	45.95	207	48.40	208	45.99	209	46.81	210	50.18
211	58.00	212	58.41	213	58.30	214	56.97	215	54.40	216	53.37
217	52.53	218	52.18	219	54.88	220	56.02	221	56.09	222	54.86
223	53.86	224	53.78	225	53.69	226	54.02	227	53.85	228	53.26
229	51.16	230	50.79	231	48.47	232	47.90				
301	-272.80										

APPENDIX B. PANSAT STEADY STATE TEMPS IN SHADOW

PANSAT - STEADY STATE - SHADOW ZONE - WITH INTERNAL HEAT DISSIPATION
Temperatures, degC

1	-19.14	2	-19.99	3	-20.56	4	-18.34	5	-19.32	6	-19.99
7	-16.10	8	-17.14	9	-17.65	10	-21.82	11	-21.92	12	-21.63
13	-20.83	14	-20.72	15	-19.87	16	-18.65	17	-18.29	18	-15.44
19	-20.86	20	-20.75	21	-20.73	22	-20.03	23	-20.14	24	-20.19
25	-17.47	26	-17.81	27	-17.93	28	-20.84	29	-20.63	30	-19.70
31	-20.23	32	-19.81	33	-18.54	34	-18.17	35	-17.85	36	-16.89
37	-15.75	38	-14.72	39	-13.46	40	-14.94	41	-13.27	42	-11.58
43	-13.84	44	-12.45	45	-11.21	46	-10.08	47	-9.24	48	-8.99
49	-7.89	50	-6.78	51	-6.50	52	-8.06	53	-7.29	54	-7.12
55	-9.28	56	-9.74	57	-10.81	58	-6.96	59	-7.61	60	-9.01
61	-7.67	62	-8.18	63	-9.19	64	-14.46	65	-15.52	66	-16.85
67	-13.05	68	-14.63	69	-15.68	70	-12.57	71	-13.70	72	-14.61
73	-22.36	74	-24.09	75	-25.30	76	-22.12	77	-23.14	78	-24.54
79	-20.75	80	-21.69	81	-22.36	82	-25.89	83	-25.88	84	-24.88
85	-24.87	86	-23.35	87	-23.37	88	-25.80	89	-25.26	90	-24.27
91	-24.93	92	-24.34	93	-22.48	94	-22.66	95	-22.31	96	-21.87
97	-23.37	98	-23.22	99	-22.69	100	-22.34	101	-22.11	102	-21.47
103	-22.51	104	-20.87	105	-18.13	106	-21.13	107	-19.28	108	-16.09
109	-19.15	110	-17.80	111	-15.57	112	-15.17	113	-15.02	114	-12.88
115	-12.24	116	-11.56	117	-10.70	118	-15.61	119	-17.25	120	-18.41
121	-13.71	122	-14.89	123	-15.65	124	-12.85	125	-13.81	126	-14.76
127	-19.81	128	-20.18	129	-18.39	130	-18.92	131	-16.96	132	-18.62
133	-15.03	134	-15.38	135	-17.14	136	-15.21	137	-17.17	138	-18.68
139	-14.50	140	-17.04	141	-18.87	142	-18.88	143	-18.47	144	-19.43
145	-19.44	146	-19.59	147	-19.64	148	-17.73	149	-17.47	150	-17.44
151	-19.37	152	-19.00	153	-18.53	154	-19.44	155	-18.79	156	-18.08
157	-18.05	158	-17.21	159	-18.05	160	-17.13	161	-17.16	162	-16.83
163	-13.53	164	-11.66	165	-10.02	166	-13.95	167	-11.47	168	-8.60
169	-14.16	170	-11.15	171	-7.36	172	-8.40	173	-7.93	174	-7.32
175	-6.85	176	-2.19	177	-2.04	178	-8.09	179	-9.45	180	-9.89
181	-6.35	182	-7.57	183	-9.09	184	-5.65	185	-7.91	186	-9.34
187	-12.97	188	-14.11	189	-12.09	190	-13.32	191	-11.10	192	-11.38
193	-20.05	194	-22.76	195	-24.46	196	-21.20	197	-24.10	198	-25.41
199	-21.99	200	-24.54	201	-25.83	202	-10.78	203	-13.59	204	-15.85
205	-12.25	206	-14.59	207	-16.48	208	-13.09	209	-15.07	210	-17.72
211	-18.92	212	-19.12	213	-19.11	214	-18.23	215	-15.99	216	-14.82
217	-14.09	218	-14.19	219	-13.66	220	-14.04	221	-14.20	222	-13.39
223	-12.32	224	-11.53	225	-11.48	226	-12.52	227	-13.80	228	-12.66
229	-14.06	230	-13.35	231	-14.59	232	-13.79				
301	-272.80										

APPENDIX D.   THANSS/TASS INPUT FILE

```
PRINTED CIRCUIT BOARDS - S. PATTERSON - RUN B
  144      3      0      0      0      0      0      0      0      1
    0      0      0
  300     50      6      2      4      6      0      0      0      0
.500000E-01 .666670                12 .800000      77.0000
92.3000        92.3000        92.3000
    5     21           91          733         3011         3033
.759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03
    5     11           31          101          743         3033
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
    5     21           41          111          753         3033
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
    5     31           51          121          763         3033
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
    5     41           61          131          773         3033
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
   .6     51           71          141          783         3033         9991
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .102390E-01
    6     61           81          151          793         3033         9991
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .682600E-02
    6     71          161          803         3011         3033         9991
.759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03 .102390E-01
    7     11          101          171          813         3011         3033         9
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03 .682600E
    7     21           91          111          181          823         3033         9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .139933
    7     31          101          121          191          833         3033         9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .139933
    7     41          111          131          201          843         3033         9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .546080E
    7     51          121          141          211          853         3033         9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .682600E
    7     61          131          151          221          863         3033         9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .682600E
    7     71          141          161          231          873         3033         9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .170650E
    7     81          151          241          883         3011         3033         9
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .000000     .801852E-03 .204780E
    7     91          181          251          893         3011         3033         9
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03 .170650E
    7    101          171          191          261          903         3033         9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .204780E
    7    111          181          201          271          913         3033         9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .136520E
    7    121          191          211          281          923         3033         9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .136520E
    7    131          201          221          291          933         3033         9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .682600E
    7    141          211          231          301          943         3033         9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .136520E
    7    151          221          241          311          953         3033         9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .136520E
    7    161          231          321          963         3011         3033         9
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03 .307170E
    7    171          261          331          973         3011         3033         9
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03 .682600E
    7    181          251          271          341          983         3033         9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .139933
    7    191          261          281          351          993         3033         9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .682600E
```

```
    144       3       0       0       0       0       0       0       0       1
      0       0       0
    300      50       6       2       4       6       0       0       0       0
  .500000E-01  .666670              12 .800000       77.0000
  92.3000       92.3000       92.3000
      5      21              91             733            3011            3033
  .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03
      5      11              31             101             743            3033
  .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
      5      21              41             111             753            3033
  .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
      5      31              51             121             763            3033
  .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
      5      41              61             131             773            3033
  .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
      6      51              71             141             783            3033            9991
  .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .102390E-01
      6      61              81             151             793            3033            9991
  .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .682600E-02
      6      71             161             803            3011            3033            9991
  .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03 .102390E-01
      7      11             101             171             813            3011            3033            9
  .759341E-01 .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03 .682600E
      7      21              91             111             181             823            3033            9
  .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .139933
      7      31             101             121             191             833            3033            9
  .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .139933
      7      41             111             131             201             843            3033            9
  .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .546080E
      7      51             121             141             211             853            3033            9
  .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .682600E
      7      61             131             151             221             863            3033            9
  .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .682600E
      7      71             141             161             231             873            3033            9
  .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .170650E
      7      81             151             241             883            3011            3033            9
  .759341E-01 .759341E-01 .759341E-01 .801852E-03 .000000      .801852E-03 .204780E
      7      91             181             251             893            3011            3033            9
  .759341E-01 .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03 .170650E
      7     101             171             191             261             903            3033            9
  .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .204780E
      7     111             181             201             271             913            3033            9
  .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .136520E
      7     121             191             211             281             923            3033            9
  .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .136520E
      7     131             201             221             291             933            3033            9
  .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .682600E
      7     141             211             231             301             943            3033            9
  .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .136520E
      7     151             221             241             311             953            3033            9
  .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .136520E
      7     161             231             321             963            3011            3033            9
  .759341E-01 .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03 .307170E
      7     171             261             331             973            3011            3033            9
  .759341E-01 .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03 .682600E
      7     181             251             271             341             983            3033            9
  .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .139933
      7     191             261             281             351             993            3033            9
  .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .682600E
```

```
   7    201         271         291         361        1003        3033            9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .102390
   6    211         281         301         371        1013        3033
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
   7    221         291         311         381        1023        3033            9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .341300E
   7    231         301         321         391        1033        3033            9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .102390E
   6    241         311         401        1043        3011        3033
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03
   7    251         341         411        1053        3011        3033            9
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03 .341300E
   7    261         331         351         421        1063        3033            9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .204780E
   7    271         341         361         431        1073        3033            9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .477820E
   7    281         351         371         441        1083        3033            9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .273040E
   7    291         361         381         451        1093        3033            9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .170650
   6    301         371         391         461        1103        3033
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
   7    311         381         401         471        1113        3033            9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .102390E
   7    321         391         481        1123        3011        3033            9
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03 .341300E
   7    331         421         491        1133        3011        3033            9
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03 .784990E
   7    341         411         431         501        1143        3033            9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .156998
   6    351         421         441         511        1153        3033
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
   6    361         431         451         521        1163        3033
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
   7    371         441         461         531        1173        3033            9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .682600E
   7    381         451         471         541        1183        3033            9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .341300E
   7    391         461         481         551        1193        3033            9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .170650E
   7    401         471         561        1203        3011        3033            9
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .000000     .801852E-03 .341300E
   7    411         501         571        1213        3011        3033            9
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03 .784990E
   7    421         491         511         581        1223        3033            9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .341300E
   7    431         501         521         591        1233        3033            9
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .853250E
   6    441         511         531         601        1243        3033
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
   6    451         521         541         611        1253        3033
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
   6    461         531         551         621        1263        3033
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
   6    471         541         561         631        1273        3033
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
   6    481         551         641        1283        3011        3033
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03
   7    491         581         651        1293        3011        3033            9
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03 .102390E
```

```
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03 .78499CE
     6    511          581          601          671         1313         3033
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
     6    521          591          611          681         1323         3033
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
     6    531          601          621          691         1333         3033
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
     6    541          611          631          701         1343         3033
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
     6    551          621          641          711         1353         3033
.759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
     6    561          631          721         1363         3011         3033
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03
     5    571          661         1373         3011         3033
.759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03
     5    581          651          671         1383         3033
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
     5    591          661          681         1393         3033
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
     5    601          671          691         1403         3033
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
     5    611          681          701         1413         3033
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
     5    621          691          711         1423         3033
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
     5    631          701          721         1433         3033
.759341E-01 .759341E-01 .759341E-01 .801852E-03 .801852E-03
     5    641          711         1443         3011         3033
.759341E-01 .759341E-01 .801852E-03 .208850E-01 .801852E-03
     5     13          741          811         3011         3023
.801852E-03 .759341E-01 .759341E-01 .208850E-01 .801852E-03
     5     23          731          751          821         3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .801852E-03
     5     33          741          761          831         3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .801852E-03
     5     43          751          771          841         3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .801852E-03
     5     53          761          781          851         3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .801852E-03
     5     63          771          791          861         3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .801852E-03
     5     73          781          801          871         3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .801852E-03
     5     83          791          881         3011         3023
.801852E-03 .759341E-01 .759341E-01 .208850E-01 .801852E-03
     6     93          731          821          891         3011         3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .208850E-01 .801852E-03
     7    103          741          811          831          901         3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .204780
     7    113          751          821          841          911         3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .180889
     6    123          761          831          851          921         3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03
     6    133          771          841          861          931         3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03
     7    143          781          851          871          941         3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .307170
     7    153          791          861          881          951         3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .426625
```

```
  6    163        801        871        961       3011       3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .208850E-01 .801852E-03
  7    173        811        901        971       3011       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .208850E-01 .801852E-03 .10239CE
  7    183        821        891        911        981       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .238910E
  7    193        831        901        921        991       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .170650E
  6    203        841        911        931       1001       3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03
  6    213        851        921        941       1011       3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03
  7    223        861        931        951       1021       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .238910
  7    233        871        941        961       1031       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .307170
  6    243        881        951       1041       3011       3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .208850E-01 .801852E-03
  7    253        891        981       1051       3011       3022            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .208850E-01 .801852E-03 .238910E
  7    263        901        971        991       1061       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .511950E
  7    273        911        981       1001       1071       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341F-01 .759341E-01 .801852E-03 .238910E
  7    283        921        991       1011       1081       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .341300
  7    293        931       1001       1021       1091       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .614340E
  7    303        941       1011       1031       1101       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .614340E
  7    313        951       1021       1041       1111       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .122868
  6    323        961       1031       1121       3011       3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .208850E-01 .801852E-03
  6    333        971       1061       1131       3011       3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .208850E-01 .801852E-03
  6    343        981       1051       1071       1141       3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03
  6    353        991       1061       1081       1151       3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03
  7    363       1001       1071       1091       1161       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .409560
  7    373       1011       1081       1101       1171       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .102390
  7    383       1021       1091       1111       1181       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .614340E
  7    393       1031       1101       1121       1191       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .614340E
  6    403       1041       1111       1201       3011       3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .208850E-01 .801852E-03
  7    413       1051       1141       1211       3011       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .208850E-01 .801852E-03 .648470E
  7    423       1061       1131       1151       1221       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .648470E
  7    433       1071       1141       1161       1231       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .648470E
  6    443       1081       1151       1171       1241       3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03
  7    453       1091       1161       1181       1251       3023            9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .341300E
```

```
   7    463      1101      1171      1191      1261      3023         9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .511950E
   7    473      1111      1181      1201      1271      3023         9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .853250E
   6    483      1121      1191      1281      3011      3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .208850E-01 .801852E-03
   6    493      1131      1221      1291      3011      3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .208850E-01 .801852E-03
   7    503      1141      1211      1231      1301      3023         9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .853250E
   6    513      1151      1221      1241      1311      3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03
   6    523      1161      1231      1251      1321      3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03
   7    533      1171      1241      1261      1331      3023         9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .341300E
   7    543      1181      1251      1271      1341      3023         9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .511950E
   7    553      1191      1261      1281      1351      3023         9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .853250E
   6    563      1201      1271      1361      3011      3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .208850E-01 .801852E-03
   6    573      1211      1301      1371      3011      3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .208850E-01 .801852E-03
   6    583      1221      1291      1311      1381      3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03
   6    593      1231      1301      1321      1391      3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03
   6    603      1241      1311      1331      1401      3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03
   7    613      1251      1321      1341      1411      3023         9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .341300E
   7    623      1261      1331      1351      1421      3023         9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .511950E
   7    633      1271      1341      1361      1431      3023         9
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .759341E-01 .801852E-03 .853250E
   6    643      1281      1351      1441      3011      3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .208850E-01 .801852E-03
   5    653      1291      1381      3011      3023
.801852E-03 .759341E-01 .759341E-01 .208850E-01 .801852E-03
   5    663      1301      1371      1391      3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .801852E-03
   5    673      1311      1381      1401      3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .801852E-03
   5    683      1321      1391      1411      3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .801852E-03
   5    693      1331      1401      1421      3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .801852E-03
   5    703      1341      1411      1431      3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .801852E-03
   5    713      1351      1421      1441      3023
.801852E-03 .759341E-01 .759341E-01 .759341E-01 .801852E-03
   5    723      1361      1431      3011      3023
.801852E-03 .759341E-01 .759341E-01 .208850E-01 .801852E-03
```

APPENDIX E.   HEAT DISSIPATIONS BY NODE

NODE	WATTS	NODE	WATTS	NODE	WATTS	NODE	WATTS
8	.003	25	.02	49	.023	102	.018
7	.002	26	.041	90	.010	103	.036
8	.003	27	.020	91	.025	108	.120
8	.020	26	.030	57	.003	109	.030
16	.041	90	.001	98	.023	110	.018
11	.011	31	.003	82	.060	111	.018
12	.016	33	.001	83	.053	113	.015
13	.002	34	.006	86	.090	114	.019
14	.002	39	.014	87	.125	118	.015
19	.005	36	.008	89	.003	117	.010
16	.005	37	.050	90	.007	118	.010
17	.005	39	.003	91	.008	118	.025
16	.006	40	.001	94	.070	122	.025
19	.004	41	.023	95	.090	125	.010
20	.004	47	.046	97	.007	125	.015
21	.002	45	.002	86	.015	127	.025
22	.004	46	.001	99	.007	133	.010
23	.004	47	.005	100	.100	134	.010
24	.009	48	.001	101	.018	135	.025

PCB HEAT DISSIPATIONS BY NODE

SURFACE NUMBERS FOR TOP PCB

SURFACE NUMBERS FOR BOTTOM PCB

69

APPENDIX H.   OPTICAL PROPERTY DATA FOR EPS

```
PgDn PgUp Home End                                                      F2Help
ëëë Ctrl : Copy (See F2)ëë ITAS Property Data Entry ëëëëëëëëëëëëëëëëëëëëëëëëëëëëëë£
 ¤                                                                              c
 ¤ Seq Surface No NodeNo Alpha   Emiss  T/Mass Dissip MID   Comments            ¤
 ¤   1 1.01        1       .4     .79    1.     0.          EPS HOUSING         ¤
 ¤   2 1.02        2       .4     .79    1.     0.          EPS HOUSING         ¤
 ¤   3 1.03        3       .4     .79    1.     0.          EPS HOUSING         ¤
 ¤   4 1.04        4       .4     .79    1.     0.          EPS HOUSING         ¤
 ¤   5 1.05        5       .4     .79    1.     0.          EPS HOUSING         ¤
 ¤   6 1.06        6       .4     .79    1.     0.          EPS HOUSING         ¤
 ¤   7 1.07        7       .4     .79    1.     0.          EPS HOUSING         ¤
 ¤   8 1.08        8       .4     .79    1.     0.          EPS HOUSING         c
 ¤   9 1.09        9       .4     .79    1.     0.          EPS HOUSING         ¤
 ¤  10 1.10       10       .4     .79    1.     0.          EPS HOUSING         ¤
 ¤  11 1.11       11       .4     .79    1.     0.          EPS HOUSING         c
 ¤  12 1.12       12       .4     .79    1.     0.          EPS HOUSING         c
 ¤  13 2.01       13      0.      .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  14 2.02       14      0.      .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  15 2.03       15      0.      .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  16 2.04       16      0.      .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  17 2.05       17      0.      .01    1.     0.          PRINTED CIRCUIT 1   c
 ¤  18 2.06       18      0.      .01    1.     0.          PRINTED CIRCUIT 1   ¤
äëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëv
  S-F1Load/Save All            S-F4Auto TM     UDC Allowed            ESCQuit
    F1Load/Save Page F3PropLib F4AutoGen F5ImportPropFmt F6NewPropFile F10Search

PgDn PgUp Home End                                                      F2Help
ëëë Ctrl : Copy (See F2)ëë ITAS Property Data Entry ëëëëëëëëëëëëëëëëëëëëëëëëëëëëëë£
 ¤                                                                              ¤
 ¤ Seq Surface No NodeNo Alpha   Emiss  T/Mass Dissip MID   Comments            ¤
 ¤  19 2.07       19      0       .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  20 2.08       20      0       .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  21 2.09       21      0       .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  22 2.10       22      0       .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  23 2.11       23      0       .01    1.     0.          PRINTED CIRCUIT 1   c
 ¤  24 2.12       24      0       .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  25 2.13       25      0       .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  26 2.14       26      0       .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  27 2.15       27      0       .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  28 2.16       28      0       .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  29 2.17       29      0       .01    1.     0.          PRINTED CIRCUIT 1   ¤
 c  30 2.18       30      0       .01    1.     0.          PRINTED CIRCUIT 1   c
 ¤  31 3.01       31      0       .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  32 3.02       32      0       .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  33 3.03       33      0       .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  34 3.04       34      0       .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  35 3.05       35      0       .01    1.     0.          PRINTED CIRCUIT 1   ¤
 ¤  36 3.06       36      0       .01    1.     0.          PRINTED CIRCUIT 1   ¤
äëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëv
  S-F1Load/Save All            S-F4Auto TM     UDC Allowed            ESCQuit
    F1Load/Save Page F3PropLib F4AutoGen F5ImportPropFmt F6NewPropFile F10Search
```

ëëë Ctrl : Copy (See F2)ëë ITAS Property Data Entry ëëëëëëëëëëëëëëëëëëëëëëëëëëf

Seq	Surface No	NodeNo	Alpha	Emiss	T/Mass	Dissip MID	Comments
37	3.07	37	0.	.01	1.	0.	PRINTED CIRCUIT 1
38	3.08	38	0.	.01	1.	0.	PRINTED CIRCUIT 1
39	3.09	39	0.	.01	1.	0.	PRINTED CIRCUIT 1
40	3.10	40	0.	.01	1.	0.	PRINTED CIRCUIT 1
41	3.11	41	0.	.01	1.	0.	PRINTED CIRCUIT 1
42	3.12	42	0.	.01	1.	0.	PRINTED CIRCUIT 1
43	4.00	43	0.	.01	1.	0.	PRINTED CIRCUIT 2
44	5.01	44	0.	.01	1.	0.	PRINTED CIRCUIT 2
45	5.02	45	0.	.01	1.	0.	PRINTED CIRCUIT 2
46	5.03	46	0.	.01	1.	0.	PRINTED CIRCUIT 2
47	5.04	47	0.	.01	1.	0.	PRINTED CIRCUIT 2
48	5.05	48	0.	.01	1.	0.	PRINTED CIRCUIT 2
49	6.01	49	0.	.01	1.	0.	PRINTED CIRCUIT 2
50	6.02	50	0.	.01	1.	0.	PRINTED CIRCUIT 2
51	6.03	51	0.	.01	1.	0.	PRINTED CIRCUIT 2
52	6.04	52	0.	.01	1.	0.	PRINTED CIRCUIT 2
53	6.05	53	0.	.01	1.	0.	PRINTED CIRCUIT 2
54	6.06	54	0.	.01	1.	0.	PRINTED CIRCUIT 2

äëëv
    S-F1Load/Save All   S-F4Auto TM   UDC Allowed   ESCQuit
      F1Load/Save Page F3PropLib F4AutoGen F5ImportPropFmt F6NewPropFile F10Search

ëëë Ctrl : Copy (See F2)ëë ITAS Property Data Entry ëëëëëëëëëëëëëëëëëëëëëëëëëëf

Seq	Surface No	NodeNo	Alpha	Emiss	T/Mass	Dissip MID	Comments
42	3.12	42	0.	.01	1.	0.	PRINTED CIRCUIT 1
43	4.00	43	0.	.01	1.	0.	PRINTED CIRCUIT 2
44	5.01	44	0.	.01	1.	0.	PRINTED CIRCUIT 2
45	5.02	45	0.	.01	1.	0.	PRINTED CIRCUIT 2
46	5.03	46	0.	.01	1.	0.	PRINTED CIRCUIT 2
47	5.04	47	0.	.01	1.	0.	PRINTED CIRCUIT 2
48	5.05	48	0.	.01	1.	0.	PRINTED CIRCUIT 2
49	6.01	49	0.	.01	1.	0.	PRINTED CIRCUIT 2
50	6.02	50	0.	.01	1.	0.	PRINTED CIRCUIT 2
51	6.03	51	0.	.01	1.	0.	PRINTED CIRCUIT 2
52	6.04	52	0.	.01	1.	0.	PRINTED CIRCUIT 2
53	6.05	53	0.	.01	1.	0.	PRINTED CIRCUIT 2
54	6.06	54	0.	.01	1.	0.	PRINTED CIRCUIT 2
55	6.07	55	0.	.01	1.	0.	PRINTED CIRCUIT 2
56	7.01	56	0.	.01	1.	0.	PRINTED CIRCUIT 2
57	7.02	57	0.	.01	1.	0.	PRINTED CIRCUIT 2
58	7.03	58	0.	.01	1.	0.	PRINTED CIRCUIT 2
59	8.00	59	0.	.01	1.	0.	PRINTED CIRCUIT 2

äëëv
    S-F1Load/Save All   S-F4Auto TM   UDC Allowed   ESCQuit
      F1Load/Save Page F3PropLib F4AutoGen F5ImportPropFmt F6NewPropFile F10Search

APPENDIX I.   THERMAL MASS FOR THE EPS

NODE	X/Y	Y/Z	thickness	kg/cubic m ro(Cu/Al/poly)	cal/kg c specific heat	CONV FACTOR	IN TO M	cubic meters VOLUME	THERMAL MASS
901	9 4	1 569	0.2	2787	0 199	69 78	61024	4 8337E-05	1 870687
902	2 1	1 569	0 2	2787	0 199	69 78	61024	1 07987E-05	0 417919
903	2 1	1 569	0 2	2787	0 199	69 78	61024	1 07987E-05	0 417919
904	2 1	1 569	0 2	2787	0 199	69 78	61024	1 07987E-05	0 417919
905	2 1	1 569	0 2	2787	0 199	69 78	61024	1 07987E-05	0 417919
906	9 4	8 4	0 2	2787	0 199	69 78	61024	0 000258783	10 01515
907	9 4	1 569	0 2	2787	0 199	69 78	61024	4 8337E-05	1 870687
908	2 1	1 569	0 2	2787	0 199	69 78	61024	1 07987E-05	0 417919
909	2 1	1 569	0 2	2787	0 199	69 78	61024	1 07987E-05	0 417919
910	2 1	1 569	0 2	2787	0 199	69 78	61024	1 07987E-05	0 417919
911	2 1	1 569	0 2	2787	0 199	69 78	61024	1 07987E-05	0 417919
912	9 4	8 4	0 2	2787	0 199	69 78	61024	0 000258783	10 01515
-913	9 4	8 4	0 125	2787	0 199	69 78	61024	0 00016174	6 259469
921	8 4	0 25	0 2	2787	0 199	69 78	61024	6 88254E-06	0 26636
922	8 4	0 375	0 2	2787	0 199	69 78	61024	1 03238E-05	0 399541
923	8 4	0 199	0 2	2787	0 199	69 78	61024	5 4785E-06	0 212023
924	8 4	2 5	0 2	2787	0 199	69 78	61024	6 88254E-05	2 663604
925	8 4	0 375	0 2	2787	0 199	69 78	61024	1 03238E-05	0 399541
926	8 4	0 199	0 2	2787	0 199	69 78	61024	5 4785E-06	0 212023
601	1 375	2 375	0 00134	8666	0 098	69 78	61024	7 17085E-08	0 00425
602	1 875	2 375	0 00134	8666	0 098	69 78	61024	9 77843E-08	0 005795
603	0 5	2 375	0 00134	8666	0 098	69 78	61024	2 60758E-08	0 001545
604	2	2 375	0 00134	8666	0 098	69 78	61024	1 04303E-07	0 006181
605	0 5	2 375	0 00134	8666	0 098	69 78	61024	2 60758E-08	0 001545
606	2 75	2 375	0 00134	8666	0 098	69 78	61024	1 43417E-07	0 008499
607	1 375	2 875	0 00134	8666	0 098	69 78	61024	8 6805E-08	0 005144
608	1 875	2 875	0 00134	8666	0 098	69 78	61024	1 1837E-07	0 007015
609	0 5	2 875	0 00134	8666	0 098	69 78	61024	3 15654E-08	0 001871
610	2	2 875	0 00134	8666	0 098	69 78	61024	1 26262E-07	0 007483
611	0 5	2 875	0 00134	8666	0 098	69 78	61024	3 15654E-08	0 001871
612	2 75	2 875	0 00134	8666	0 098	69 78	61024	1 7361E-07	0 010288
613	1 75	0 8125	0 00134	8666	0 098	69 78	61024	3 12223E-08	0 00185

614	1.375	0.8125	0.00134	8666	0.098	69.78	61024	2.45318E-08	0.001454
615	1.375	0.8125	0.00134	8666	0.098	69.78	61024	2.45318E-08	0.001454
616	1.375	0.8125	0.00134	8666	0.098	69.78	61024	2.45318E-08	0.001454
617	1.375	0.8125	0.00134	8666	0.098	69.78	61024	2.45318E-08	0.001454
618	1.75	0.8125	0.00134	8666	0.098	69.78	61024	3.12223E-08	0.00185
619	1.75	1.0625	0.00134	8666	0.098	69.78	61024	4.08292E-08	0.00242
620	1.375	1.0625	0.00134	8666	0.098	69.78	61024	3.20801E-08	0.001901
621	1.375	1.0625	0.00134	8666	0.098	69.78	61024	3.20801E-08	0.001901
622	1.375	1.0625	0.00134	8666	0.098	69.78	61024	3.20801E-08	0.001901
623	1.375	1.0625	0.00134	8666	0.098	69.78	61024	3.20801E-08	0.001901
624	1.75	1.0625	0.00134	8666	0.098	69.78	61024	4.08292E-08	0.00242
625	1.375	0.875	0.00134	8666	0.098	69.78	61024	2.64189E-08	0.001566
626	1.375	0.875	0.00134	8666	0.098	69.78	61024	2.64189E-08	0.001566
627	1.375	0.875	0.00134	8666	0.098	69.78	61024	2.64189E-08	0.001566
628	1.375	0.875	0.00134	8666	0.098	69.78	61024	2.64189E-08	0.001566
629	1.375	0.875	0.00134	8666	0.098	69.78	61024	2.64189E-08	0.001566
630	1.75	0.875	0.00134	8666	0.098	69.78	61024	3.36241E-08	0.001993
1601	8	1	0.00134	8666	0.098	69.78	61024	1.75669E-07	0.01041
1602	3	1.563	0.00134	8666	0.098	69.78	61024	1.02964E-07	0.006102
1603	3	1.125	0.00134	8666	0.098	69.78	61024	7.41102E-08	0.004392
1604	3	1.3125	0.00134	8666	0.098	69.78	61024	8.64619E-08	0.005124
1605	3	0.5	0.00134	8666	0.098	69.78	61024	3.29379E-08	0.001952
1606	3	2.5	0.00134	8666	0.098	69.78	61024	1.64689E-07	0.00976
1607	1.5	1.563	0.00134	8666	0.098	69.78	61024	5.14819E-08	0.003051
1608	1.5	1.125	0.00134	8666	0.098	69.78	61024	3.70551E-08	0.002196
1609	1.5	1.4375	0.00134	8666	0.098	69.78	61024	4.73482E-08	0.002806
1610	1.5	0.375	0.00134	8666	0.098	69.78	61024	1.23517E-08	0.000732
1611	1.5	0.5	0.00134	8666	0.098	69.78	61024	1.64689E-08	0.000976
1612	1.5	0.5	0.00134	8666	0.098	69.78	61024	1.64689E-08	0.000976
1613	1.5	2.5	0.00134	8666	0.098	69.78	61024	8.23447E-08	0.00488
1614	3.5	1.563	0.00134	8666	0.098	69.78	61024	1.20124E-07	0.007119
1615	3.5	2.4375	0.00134	8666	0.098	69.78	61024	1.87334E-07	0.011102
1616	3.5	3	0.00134	8666	0.098	69.78	61024	2.30565E-07	0.013664
1617	3.5	1	0.00134	8666	0.098	69.78	61024	7.6855E-08	0.004555
501	1.375	2.375	0.01933	1950	0.31	69.78	61024	1.03442E-06	0.043634
502	1.875	2.375	0.01933	1950	0.31	69.78	61024	1.41057E-06	0.059501
503	0.5	2.375	0.01933	1950	0.31	69.78	61024	3.76153E-07	0.015867

504	2	2.375	0.01933	1950	0.31	69.78	61024	1.50461E-06	0.063468
505	0.5	2.375	0.01933	1950	0.31	69.78	61024	3.76153E-07	0.015867
506	2.75	2.375	0.01933	1950	0.31	69.78	61024	2.06884E-06	0.087268
507	1.375	2.875	0.01933	1950	0.31	69.78	61024	1.25219E-06	0.05282
508	1.875	2.875	0.01933	1950	0.31	69.78	61024	1.70754E-06	0.072027
509	0.5	2.875	0.01933	1950	0.31	69.78	61024	4.55343E-07	0.019207
510	2	2.875	0.01933	1950	0.31	69.78	61024	1.82137E-06	0.076829
511	0.5	2.875	0.01933	1950	0.31	69.78	61024	4.55343E-07	0.019207
512	2.75	2.875	0.01933	1950	0.31	69.78	61024	2.50439E-06	0.10564
513	1.75	0.8125	0.01933	1950	0.31	69.78	61024	4.50394E-07	0.018999
514	1.375	0.8125	0.01933	1950	0.31	69.78	61024	3.53881E-07	0.014927
515	1.375	0.8125	0.01933	1950	0.31	69.78	61024	3.53881E-07	0.014927
516	1.375	0.8125	0.01933	1950	0.31	69.78	61024	3.53881E-07	0.014927
517	1.375	0.8125	0.01933	1950	0.31	69.78	61024	3.53881E-07	0.014927
518	1.75	0.8125	0.01933	1950	0.31	69.78	61024	4.50394E-07	0.018999
519	1.75	1.0625	0.01933	1950	0.31	69.78	61024	5.88977E-07	0.024844
520	1.375	1.0625	0.01933	1950	0.31	69.78	61024	4.62767E-07	0.01952
521	1.375	1.0625	0.01933	1950	0.31	69.78	61024	4.62767E-07	0.01952
522	1.375	1.0625	0.01933	1950	0.31	69.78	61024	4.62767E-07	0.01952
523	1.375	1.0625	0.01933	1950	0.31	69.78	61024	4.62767E-07	0.01952
524	1.75	1.0625	0.01933	1950	0.31	69.78	61024	5.88977E-07	0.024844
525	1.375	0.875	0.01933	1950	0.31	69.78	61024	3.81103E-07	0.016076
526	1.375	0.875	0.01933	1950	0.31	69.78	61024	3.81103E-07	0.016076
527	1.375	0.875	0.01933	1950	0.31	69.78	61024	3.81103E-07	0.016076
528	1.375	0.875	0.01933	1950	0.31	69.78	61024	3.81103E-07	0.016076
529	1.375	0.875	0.01933	1950	0.31	69.78	61024	3.81103E-07	0.016076
530	1.75	0.875	0.01933	1950	0.31	69.78	61024	4.8504E-07	0.02046
1501	8	1	0.01933	1950	0.31	69.78	61024	2.53408E-06	0.106893
1502	3	1.563	0.01933	1950	0.31	69.78	61024	1.48529E-06	0.062653
1503	3	1.125	0.01933	1950	0.31	69.78	61024	1.06907E-06	0.045095
1504	3	1.3125	0.01933	1950	0.31	69.78	61024	1.24724E-06	0.052611
1505	3	0.5	0.01933	1950	0.31	69.78	61024	4.75141E-07	0.020042
1506	3	2.5	0.01933	1950	0.31	69.78	61024	2.3757E-06	0.100212
1507	1.5	1.563	0.01933	1950	0.31	69.78	61024	7.42645E-07	0.031326
1508	1.5	1.125	0.01933	1950	0.31	69.78	61024	5.34534E-07	0.022548
1509	1.5	1.4375	0.01933	1950	0.31	69.78	61024	6.83015E-07	0.028811
1510	1.5	0.375	0.01933	1950	0.31	69.78	61024	1.78178E-07	0.007516

PIN THERMAL MASSES

NODE	# OF PINS	pi	RADIUS	HEIGHT	VOLUME	cal/kg C c	kg/cubic m ro	CONV FACTOR	cubic in to cubic m	THERMAL MASS
2011	6	3.14159	0.0165	0.01933	9.92E-05	0.11	8378	69.78	61024	0.000105
2012	6	3.14159	0.0165	0.00134	6.88E-06	0.11	8378	69.78	61024	7.25E-06
2021	23	3.14159	0.0165	0.01933	0.00038	0.11	8378	69.78	61024	0.000401
2022	23	3.14159	0.0165	0.00134	2.64E-05	0.11	8378	69.78	61024	2.78E-05
2031	4	3.14159	0.0165	0.01933	6.61E-05	0.11	8378	69.78	61024	6.97E-05
2032	4	3.14159	0.0165	0.00134	4.58E-06	0.11	8378	69.78	61024	4.83E-06
2041	25	3.14159	0.0165	0.01933	0.000413	0.11	8378	69.78	61024	0.000436
2042	25	3.14159	0.0165	0.00134	2.87E-05	0.11	8378	69.78	61024	3.02E-05
2051	3	3.14159	0.0165	0.01933	4.96E-05	0.11	8378	69.78	61024	5.23E-05
2052	3	3.14159	0.0165	0.00134	3.44E-06	0.11	8378	69.78	61024	3.62E-06
2121	12	3.14159	0.0165	0.01933	0.000198	0.11	8378	69.78	61024	0.000209
2122	12	3.14159	0.0165	0.00134	1.38E-05	0.11	8378	69.78	61024	1.45E-05
2131	8	3.14159	0.0165	0.01933	0.000132	0.11	8378	69.78	61024	0.000139
2132	8	3.14159	0.0165	0.00134	9.17E-06	0.11	8378	69.78	61024	9.66E-06
2191	14	3.14159	0.0165	0.01933	0.000231	0.11	8378	69.78	61024	0.000244
2192	14	3.14159	0.0165	0.00134	1.6E-05	0.11	8378	69.78	61024	1.69E-05
3011	64	3.14159	0.0165	0.01933	0.001058	0.11	8378	69.78	61024	0.001115
3012	64	3.14159	0.0165	0.00134	7.34E-05	0.11	8378	69.78	61024	7.73E-05
3021	34	3.14159	0.0165	0.01933	0.000562	0.11	8378	69.78	61024	0.000592
3022	34	3.14159	0.0165	0.00134	3.9E-05	0.11	8378	69.78	61024	4.11E-05
3031	32	3.14159	0.0165	0.01933	0.000529	0.11	8378	69.78	61024	0.000558
3032	32	3.14159	0.0165	0.00134	3.67E-05	0.11	8378	69.78	61024	3.86E-05
3051	28	3.14159	0.0165	0.01933	0.000463	0.11	8378	69.78	61024	0.000488
3052	28	3.14159	0.0165	0.00134	3.21E-05	0.11	8378	69.78	61024	3.38E-05
3141	10	3.14159	0.0165	0.01933	0.000165	0.11	8378	69.78	61024	0.000174
3142	10	3.14159	0.0165	0.00134	1.15E-05	0.11	8378	69.78	61024	1.21E-05
3151	100	3.14159	0.0165	0.01933	0.001653	0.11	8378	69.78	61024	0.001742
3152	100	3.14159	0.0165	0.00134	0.000115	0.11	8378	69.78	61024	0.000121
3161	114	3.14159	0.0165	0.01933	0.001885	0.11	8378	69.78	61024	0.001986
3162	114	3.14159	0.0165	0.00134	0.000131	0.11	8378	69.78	61024	0.000138

APPENDIX J.   EPS PCB BOARD DATA

Component	Designator	Subcircuit	Duty cycle	Power Dissipation, Bus = 15V (Sunlit)	Power Dissipation, Bus = 12V (Eclipse)
Inductor	I1A	DCSA Power Switch	100	.	0.061
Transient Voltage Suppressor	TVS1A	"	~0	0.039	
Ultra Fast Recovery Diode	UFR1A	"	~0		
12v Zener Bi-Directional	D1A	"	~0		
PMOSFET Gate Bias Resister	R1A	"	100	0.002	0.001
PMOSFET Gate Bias Resister	R2A	"	100	0.000	0.000
NMOSFET Gate Protection Resister	R3A	"	100	0.003	0.003
PMOSFET	T1A	"	100	0.006	0.009
NMOSFET	T2A	"	100	0.000	0.000
Pico Fuse	F1A	"	100	0.007	0.011
Inductor	I1B	DCSB Power Switch	100		0.061
Transient Voltage Suppressor	TVS1B	"	~0	0.039	
Ultra Fast Recovery Diode	UFR1B	"	~0		
12v Zener Bi-Directional	D1B	"	~0		
PMOSFET Gate Bias Resister	R1B	"	100	0.002	0.001
PMOSFET Gate Bias Resister	R2B	"	100	0.000	0.000
NMOSFET Gate Protection Resister	R3B	"	100	0.003	0.003
PMOSFET	T1B	"	100	0.006	0.009
NMOSFET	T2B	"	100	0.000	0.000
Pico Fuse	F1B	"	100	0.007	0.011
Inductor	I1C	RF Power Switch - Rx only	70	0.010	0.015
Transient Voltage Suppressor	TVS1C	"	~0		
Ultra Fast Recovery Diode	UFR1C	"	~0		
12v Zener Bi-Directional	D1C	"	~0		
PMOSFET Gate Bias Resister	R1C	"	100	0.002	0.001
PMOSFET Gate Bias Resister	R2C	"	100	0.000	0.000
NMOSFET Gate Protection Resister	R3C	"	70	0.003	0.003
PMOSFET	T1C	"	70	0.006	0.009
NMOSFET	T2C	"	70	0.000	0.000
Pico Fuse	F1C	"	70	0.002	0.003
Inductor	I1C	RF Power Switch - Rx and Tx	30	0.088	0.138
Transient Voltage Suppressor	TVS1C	"	~0		
Ultra Fast Recovery Diode	UFR1C	"	~0		
12v Zener Bi-Directional	D1C	"	~0		
PMOSFET Gate Bias Resister	R1C	"	30	0.002	0.001

Component	Designator	Subcircuit	Duty cycle	Power Dissipation, Bus = 15V (Sunlit)	Power Dissipation, Bus = 12V (Eclipse)	X-Coord	Y-Coord
PMOSFET Gate Bias Resister	R2C	"	30	0.000	0.000		
NMOSFET Gate Protection Resister	R3C	"	30	0.003	0.003		
PMOSFET	T1C	"	30	0.014	0.021		
NMOSFET	T2C	"	30	0.000	0.000		
Pico Fuse	F1C	"	30	0.016	0.025		
Inductor	I1D	CHARG Battery A Power Switch	60	0.012	N/A	4.300	8.900
Transient Voltage Suppressor	TVS1D	"	~0		"	5.025	8.637
Ultra Fast Recovery Diode	UFR1D	"	~0		"	3.925	8.600
12v Zener Bi-Directional	D1D	"	~0		"	3.750	8.125
PMOSFET Gate Bias Resister	R1D	"	60	0.002	"	5.125	7.250
PMOSFET Gate Bias Resister	R2D	"	60	0.000	"	4.950	7.075
NMOSFET Gate Protection Resister	R3D	"	60	0.003	0.003	3.750	7.575
PMOSFET	T1D	"	60	0.008	"	4.475	7.850
NMOSFET	T2D	"	60	0.000	"	3.875	7.000
Pico Fuse	F1D	"	60	0.002	"	5.250	8.175
Inductor	I1E	CHARG Battery B Power Switch	60	0.050	N/A	4.300	6.475
Transient Voltage Suppressor	TVS1E	"	~0		"	5.025	6.212
Ultra Fast Recovery Diode	UFR1E	"	~0		"	3.925	6.175
12v Zener Bi-Directional	D1E	"	~0		"	3.750	5.700
PMOSFET Gate Bias Resister	R1E	"	60	0.002	"	5.125	4.825
PMOSFET Gate Bias Resister	R2E	"	60	0.000	"	4.950	4.650
NMOSFET Gate Protection Resister	R3E	"	60	0.003	0.003	3.750	5.150
PMOSFET	T1E	"	60	0.008	"	4.475	5.425
NMOSFET	T2E	"	60	0.000	"	3.875	4.575
Pico Fuse	F1E	"	60	0.050	"	5.250	5.650
Inductor	I1F	MUX A	30	0.006	0.009	8.400	8.875
Transient Voltage Suppressor	TVS1F	"	~0			7.297	9.450
Ultra Fast Recovery Diode	UFR1F	"	~0			8.125	9.225
12v Zener Bi-Directional	D1F	"	~0			7.175	8.550
PMOSFET Gate Bias Resister	R1F	"	30	0.002	0.001	7.175	8.950
PMOSFET Gate Bias Resister	R2F	"	30	0.000	0.000	7.400	8.950
NMOSFET Gate Protection Resister	R3F	"	30	0.003	0.003	7.225	8.375
PMOSFET	T1F	"	30	0.003	0.004	7.775	9.050
PMOSFET	T1F2	"	30	0.003	0.004	6.850	9.050
NMOSFET	T2F	"	30	0.000	0.000	7.775	8.450
Pico Fuse	F1F	"	100	0.001	0.002	6.475	9.125

Component	Designator	Subcircuit	Duty cycle	Power Dissipation, Bus = 15V (Sunlit)	Power Dissipation, Bus = 12V (Eclipse)	X-Coord	Y-Coord
Inductor	I1G	MUX B	30	0.006	0.009	8.400	7.525
Transient Voltage Suppressor	TVS1G	"	~0			7.297	8.100
Ultra Fast Recovery Diode	UFR1G	"	~0			8.125	7.875
12v Zener Bi-Directional	D1G	"	~0			7.175	7.200
PMOSFET Gate Bias Resister	R1G	"	30	0.002	0.001	7.175	7.600
PMOSFET Gate Bias Resister	R2G	"	30	0.000	0.000	7.400	7.600
NMOSFET Gate Protection Resister	R3G	"	30	0.003	0.003	7.225	7.025
PMOSFET	T1G	"	30	0.003	0.004	7.775	7.700
PMOSFET	T1G2	"	30	0.003	0.004	6.850	7.700
NMOSFET	T2G	"	30	0.000	0.000	7.775	7.100
Pico Fuse	F1G	"	100	0.001	0.009	6.475	7.775
Inductor	I1H	MASS A	30	0.001	0.002	8.400	6.175
Transient Voltage Suppressor	TVS1H	"	~0			7.297	6.750
Ultra Fast Recovery Diode	UFR1H	"	~0			8.125	6.525
12v Zener Bi-Directional	D1H	"	~0			7.175	5.850
PMOSFET Gate Bias Resister	R1H	"	30	0.002	0.001	7.175	6.250
PMOSFET Gate Bias Resister	R2H	"	30	0.000	0.000	7.400	6.250
NMOSFET Gate Protection Resister	R3H	"	30	0.003	0.003	7.225	5.675
PMOSFET	T1H	"	30	0.001	0.001	7.775	6.350
PMOSFET	T1H2	"	30	0.001	0.001	6.850	6.350
NMOSFET	T2H	"	30	0.000	0.000	7.775	5.750
Pico Fuse	F1H	"	100	0.000	0.000	6.475	6.425
Inductor	I1I	MASS B	30	0.001	0.002	8.400	4.825
Transient Voltage Suppressor	TVS1I	"	~0			7.297	5.400
Ultra Fast Recovery Diode	UFR1I	"	~0			8.125	5.175
12v Zener Bi-Directional	D1I	"	~0			7.175	4.500
PMOSFET Gate Bias Resister	R1I	"	30	0.002	0.001	7.175	4.900
PMOSFET Gate Bias Resister	R2I	"	30	0.000	0.000	7.400	4.900
NMOSFET Gate Protection Resister	R3I	"	30	0.003	0.003	7.225	4.325
PMOSFET	T1I	"	30	0.001	0.001	7.775	5.000
PMOSFET	T1I2	"	30	0.001	0.001	6.850	5.000
NMOSFET	T2I	"	30	0.000	0.000	7.775	4.400
Pico Fuse	F1I	"	100	0.000	0.000	6.475	5.075
Inductor	I1J	TRICKLE A	~0			8.400	3.475
Transient Voltage Suppressor	TVS1J	"	~0			7.297	4.050

Component	Designator	Subcircuit	Duty cycle	Power Dissipation, Bus = 15V (Sunlit)	Power Dissipation, Bus = 12V (Eclipse)	X-Coord	Y-Coord
Ultra Fast Recovery Diode	UFR1J	"	~0			8.125	3.825
12v Zener Bi-Directional	D1J	"	~0			7.175	3.150
PMOSFET Gate Bias Resister	R1J	"	~0			7.175	3.550
PMOSFET Gate Bias Resister	R2J	"	~0			7.400	3.550
NMOSFET Gate Protection Resister	R3J	"	~0			7.225	2.975
PMOSFET	T1J	"	~0			7.775	3.650
PMOSFET	T1J2	"	~0			6.850	3.650
NMOSFET	T2J	"	~0			7.775	3.050
Pico Fuse	F1J	"	~0			6.475	3.725
Inductor	I1K	TRICKLE B	~0			8.400	2.100
Transient Voltage Suppressor	TVS1K	"	~0			7.297	2.675
Ultra Fast Recovery Diode	UFR1K	"	~0			8.125	2.450
12v Zener Bi-Directional	D1K	"	~0			7.175	1.775
PMOSFET Gate Bias Resister	R1K	"	~0			7.175	2.175
PMOSFET Gate Bias Resister	R2K	"	~0			7.400	2.175
NMOSFET Gate Bias Resister	R3K	"	~0			7.225	1.600
PMOSFET	T1K	"	~0			7.775	2.275
PMOSFET	T1K2	"	~0			6.850	2.275
NMOSFET	T2K	"	~0			7.775	1.675
Pico Fuse	F1K	"	~0			6.475	2.350
NMOSFET	T3A	Discharge Battery A				5.750	5.300
NMOSFET	T3B	Discharge Battery B				5.775	3.650
LM150	IS1A	Constant Current Source				3.975	3.092
LM150	IS1B	Constant Current Source				5.225	3.092
			Total Power	#REF!	0.280W		

APPENDIX K.   ITAS THERMAL MASS/DISSIPATIONS

```
ëëCtrl:Copyëëëëëëë ITAS Node Data Entry For Thermal Analysis ëëëëëëëëëESC:Quitëf
□                                                                                □
□ SEQN    NodeNo   Temp-C   ThrMass   Dissip   Comment                           □
□    1    901      30       -1.870    0        EPS HOUSING WALL                   □
□    2    902      30       -.4179    0        EPS HOUSING WALL                   □
□    3    903      30       -.4179    0        EPS HOUSING WALL                   □
□    4    904      30       -.4179    0        EPS HOUSING WALL                   □
□    5    905      30        .4179    0        EPS HOUSING WALL                   □
□    6    906      30       -10.15    0        BOTTOM EPS HOUSING                 □
□    7    907      30       -1.871    0        EPS HOUSING WALL                   □
□    8    908      30       -.4179    0        EPS HOUSING WALL                   □
□    9    909      30       -.4179    0        EPS HOUSING WALL                   □
□   10    910      30       -.4179    0        EPS HOUSING WALL                   □
□   11    911      30       -.4179    0        EPS HOUSING WALL                   □
□   12    912      30       -10.02    0        EPS HOUSING WALL                   □
□   13    913      30       -6.259    0        EQUIPMENT PLATE TO BOTTOM EPS      □
□   14    921      30       -.2664    0        BOTTOM RAIL (+Y)                   □
□   15    922      30       -.3995    0        MIDDLE RAIL (+Y)                   □
□   16    923      30       -.2120    0        TOP RAIL    (+Y)                   □
□   17    924      30       -.2664    0        BOTTOM RAIL (-Y)                   □
□   18    925      30       -.3995    0        MIDDLE RAIL (-Y)                   □
àëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëv
CTRL-F1Import ITAS_NC    UDC Allowed                        PgDn PgUp Home End
SHFT-F1Import Column                         Shift-F5Del/Pur
     F1Save/Purge       F2Help F3AutoGen F4Purge F5Delete   F7Mark/UnMark F10Search

ëëCtrl:Copyëëëëëëë ITAS Node Data Entry For Thermal Analysis ëëëëëëëëëESC:Quitëf
□                                                                                □
□ SEQN    NodeNo   Temp-C   ThrMass   Dissip   Comment                           □
□   19    926      30       -.2120    0        TOP RAIL (-Y)                      □
□   20    601      30       -.0043    0        TOP PCB THERMAL LAYER              □
□   21    602      30       -.0058    0                                          □
□   22    603      30       -.0016    0                                          □
□   23    604      30       -.0062    0                                          □
□   24    605      30       -.0016    0                                          □
□   25    606      30       -.0085    0                                          □
□   26    607      30       -.0051    0                                          □
□   27    608      30       -.0070    0                                          □
□   28    609      30       -.0019    0                                          □
□   29    610      30       -.0075    0                                          □
□   30    611      30       -.0019    0                                          □
□   31    612      30       -.0103    0                                          □
□   32    613      30       -.0019    0                                          □
□   33    614      30       -.0015    0                                          □
□   34    615      30       -.0015    0                                          □
□   35    616      30       -.0015    0                                          □
□   36    617      30       -.0015    0                                          □
àëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëv
CTRL-F1Import ITAS_NC    UDC Allowed                        PgDn PgUp Home End
SHFT-F1Import Column                         Shift-F5Del/Pur
     F1Save/Purge       F2Help F3AutoGen F4Purge F5Delete   F7Mark/UnMark F10Search
```

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
37	618	30	-.0019	0	TOP PCB THERMAL LAYER
38	619	30	-.0024	0	
39	620	30	-.0019	0	
40	621	30	-.0019	0	
41	622	30	-.0019	0	
42	623	30	-.0019	0	
43	624	30	-.0024	0	
44	625	30	-.0016	0	
45	626	30	-.0016	0	
46	627	30	-.0016	0	
47	628	30	-.0016	0	
48	629	30	-.0016	0	
49	630	30	-.0020	0	
50	1601	30	-.0104	0	BOTTOM PCB THERMAL LAYER
51	1602	30	-.0061	0	BOTTOM PCB THERMAL LAYER
52	1603	30	-.0044	0	BOTTOM PCB THERMAL LAYER
53	1604	30	-.0051	0	BOTTOM PCB THERMAL LAYER
54	1605	30	-.0020	0	BOTTOM PCB THERMAL LAYER

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
55	1606	30	-.0098	0	BOTTOM PCB THERMAL LAYER
56	1607	30	-.0031	0	BOTTOM PCB THERMAL LAYER
57	1608	30	-.0022	0	BOTTOM PCB THERMAL LAYER
58	1609	30	-.0028	0	BOTTOM PCB THERMAL LAYER
59	1610	30	-.0007	0	BOTTOM PCB THERMAL LAYER
60	1611	30	-.0010	0	BOTTOM PCB THERMAL LAYER
61	1612	30	-.0010	0	BOTTOM PCB THERMAL LAYER
62	1613	30	-.0049	0	BOTTOM PCB THERMAL LAYER
63	1614	30	-.0071	0	BOTTOM PCB THERMAL LAYER
64	1615	30	-.0111	0	BOTTOM PCB THERMAL LAYER
65	1616	30	-.0137	0	BOTTOM PCB THERMAL LAYER
66	1617	30	-.0046	0	BOTTOM PCB THERMAL LAYER
67	501	30	-.0436	0	TOP PCB BOTTOM POLY LAYER
68	502	30	-.0595	0	TOP PCB BOTTOM POLY LAYER
69	503	30	-.0159	0	TOP PCB BOTTOM POLY LAYER
70	504	30	-.0635	0	TOP PCB BOTTOM POLY LAYER
71	505	30	-.0159	0	TOP PCB BOTTOM POLY LAYER
72	506	30	-0.087	0	TOP PCB BOTTOM POLY LAYER

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
73	507	30	-.0528	0	TOP PCB BOTTOM POLY LAYER
74	508	30	-.0720	0	TOP PCB BOTTOM POLY LAYER
75	509	30	-.0192	0	TOP PCB BOTTOM POLY LAYER
76	510	30	-.0768	0	TOP PCB BOTTOM POLY LAYER
77	511	30	-.0192	0	TOP PCB BOTTOM POLY LAYER
78	512	30	-.1056	0	TOP PCB BOTTOM POLY LAYER
79	513	30	-.0190	0	TOP PCB BOTTOM POLY LAYER
80	514	30	-.0149	0	TOP PCB BOTTOM POLY LAYER
81	515	30	-.0149	0	TOP PCB BOTTOM POLY LAYER
82	516	30	-.0149	0	TOP PCB BOTTOM POLY LAYER
83	517	30	-.0149	0	TOP PCB BOTTOM POLY LAYER
84	518	30	-.0190	0	TOP PCB BOTTOM POLY LAYER
85	519	30	-.0248	0	TOP PCB BOTTOM POLY LAYER
86	520	30	-.0195	0	TOP PCB BOTTOM POLY LAYER
87	521	30	-.0195	0	TOP PCB BOTTOM POLY LAYER
88	522	30	-.0195	0	TOP PCB BOTTOM POLY LAYER
89	523	30	-.0195	0	TOP PCB BOTTOM POLY LAYER
90	524	30	-.0248	0	TOP PCB BOTTOM POLY LAYER

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
91	525	30	-.0161	0	TOP PCB BOTTOM POLY LAYER
92	526	30	-.0161	0	TOP PCB BOTTOM POLY LAYER
93	527	30	-.0161	0	TOP PCB BOTTOM POLY LAYER
94	528	30	-.0161	0	TOP PCB BOTTOM POLY LAYER
95	529	30	-.0161	0	TOP PCB BOTTOM POLY LAYER
96	530	30	-.0205	0	TOP PCB BOTTOM POLY LAYER
97	1501	30	-.1069	0	BOTTOM PCB BOTTOM POLY LAYER
98	1502	30	-.0627	0	BOTTOM PCB BOTTOM POLY LAYER
99	1503	30	-.0451	0	BOTTOM PCB BOTTOM POLY LAYER
100	1504	30	-.0526	0	BOTTOM PCB BOTTOM POLY LAYER
101	1505	30	-.0200	0	BOTTOM PCB BOTTOM POLY LAYER
102	1506	30	-.1002	0	BOTTOM PCB BOTTOM POLY LAYER
103	1507	30	-.0313	0	BOTTOM PCB BOTTOM POLY LAYER
104	1508	30	-.0226	0	BOTTOM PCB BOTTOM POLY LAYER
105	1509	30	-.0288	0	BOTTOM PCB BOTTOM POLY LAYER
106	1510	30	-.0075	0	BOTTOM PCB BOTTOM POLY LAYER
107	1511	30	-.0100	0	BOTTOM PCB BOTTOM POLY LAYER
108	1512	30	-.0100	0	BOTTOM PCB BOTTOM POLY LAYER

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
109	1513	30	-.0501	0	BOTTOM PCB BOTTOM POLY LAYER
110	1514	30	-.0731	0	BOTTOM PCB BOTTOM POLY LAYER
111	1515	30	-.1140	0	BOTTOM PCB BOTTOM POLY LAYER
112	1516	30	-.1403	0	BOTTOM PCB BOTTOM POLY LAYER
113	1517	30	-.0468	0	BOTTOM PCB BOTTOM POLY LAYER
114	401	30	-.0043	0	TOP PCB THERMAL COPPER LAYER
115	402	30	-.0058	0	TOP PCB THERMAL COPPER LAYER
116	403	30	-.0016	0	TOP PCB THERMAL COPPER LAYER
117	404	30	-.0062	0	TOP PCB THERMAL COPPER LAYER
118	405	30	-.0016	0	TOP PCB THERMAL COPPER LAYER
119	406	30	-.0085	0	TOP PCB THERMAL COPPER LAYER
120	407	30	-.0051	0	TOP PCB THERMAL COPPER LAYER
121	408	30	-.0071	0	TOP PCB THERMAL COPPER LAYER
122	409	30	-.0019	0	TOP PCB THERMAL COPPER LAYER
123	410	30	-.0075	0	TOP PCB THERMAL COPPER LAYER
124	411	30	-.0019	0	TOP PCB THERMAL COPPER LAYER
125	412	30	-.0103	0	TOP PCB THERMAL COPPER LAYER
126	413	30	-.0019	0	TOP PCB THERMAL COPPER LAYER

```
CTRL-F1Import ITAS_NC   UDC Allowed                        PgDn PgUp Home End
SHFT-F1Import Column                         Shift-F5Del/Pur
       F1Save/Purge     F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
127	414	30	-.0015	0	TOP PCB THERMAL COPPER LAYER
128	415	30	-.0015	0	TOP PCB THERMAL COPPER LAYER
129	416	30	-.0015	0	TOP PCB THERMAL COPPER LAYER
130	417	30	-.0015	0	TOP PCB THERMAL COPPER LAYER
131	418	30	-.0019	0	TOP PCB THERMAL COPPER LAYER
132	419	30	-.0024	0	TOP PCB THERMAL COPPER LAYER
133	420	30	-.0019	0	TOP PCB THERMAL COPPER LAYER
134	421	30	-.0019	0	TOP PCB THERMAL COPPER LAYER
135	422	30	-.0019	0	TOP PCB THERMAL COPPER LAYER
136	423	30	-.0019	0	TOP PCB THERMAL COPPER LAYER
137	424	30	-.0024	0	TOP PCB THERMAL COPPER LAYER
138	425	30	-.0016	0	TOP PCB THERMAL COPPER LAYER
139	426	30	-.0016	0	TOP PCB THERMAL COPPER LAYER
140	427	30	-.0016	0	TOP PCB THERMAL COPPER LAYER
141	428	30	-.0016	0	TOP PCB THERMAL COPPER LAYER
142	429	30	-.0016	0	TOP PCB THERMAL COPPER LAYER
143	430	30	-.0020	0	TOP PCB THERMAL COPPER LAYER
144	1401	30	-.0104	0	BOTTOM PCB GROUND (COPPER) LAYER

```
CTRL-F1Import ITAS_NC   UDC Allowed                        PgDn PgUp Home End
SHFT-F1Import Column                         Shift-F5Del/Pur
       F1Save/Purge     F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
145	1402	30	-.0061	0	BOTTOM PCB GROUND (COPPER) LAYER
146	1403	30	-.0044	0	BOTTOM PCB GROUND (COPPER) LAYER
147	1404	30	-.0051	0	BOTTOM PCB GROUND (COPPER) LAYER
148	1405	30	-.0020	0	BOTTOM PCB GROUND (COPPER) LAYER
149	1406	30	-.0098	0	BOTTOM PCB GROUND (COPPER) LAYER
150	1407	30	-.0031	0	BOTTOM PCB GROUND (COPPER) LAYER
151	1408	30	-.0022	0	BOTTOM PCB GROUND (COPPER) LAYER
152	1409	30	-.0028	0	BOTTOM PCB GROUND (COPPER) LAYER
153	1410	30	-.0007	0	BOTTOM PCB GROUND (COPPER) LAYER
154	1411	30	-.0010	0	BOTTOM PCB GROUND (COPPER) LAYER
155	1412	30	-.0010	0	BOTTOM PCB GROUND (COPPER) LAYER
156	1413	30	-.0049	0	BOTTOM PCB GROUND (COPPER) LAYER
157	1414	30	-.0071	0	BOTTOM PCB GROUND (COPPER) LAYER
158	1415	30	-.0111	0	BOTTOM PCB GROUND (COPPER) LAYER
159	1416	30	-.0137	0	BOTTOM PCB GROUND (COPPER) LAYER
160	1417	30	-.0046	0	BOTTOM PCB GROUND (COPPER) LAYER
161	301	30	-.0436	0	TOP PCB MIDDLE POLY LAYER
162	302	30	-.0595	0	TOP PCB MIDDLE POLY LAYER

```
CTRL-F1Import ITAS_NC   UDC Allowed                    PgDn PgUp Home End
SHFT-F1Import Column                      Shift-F5Del/Pur
     F1Save/Purge      F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
163	303	30	-.0159	0	TOP PCB MIDDLE POLY LAYER
164	304	30	-.0635	0	TOP PCB MIDDLE POLY LAYER
165	305	30	-.0159	0	TOP PCB MIDDLE POLY LAYER
166	306	30	-.0873	0	TOP PCB MIDDLE POLY LAYER
167	307	30	-.0528	0	TOP PCB MIDDLE POLY LAYER
168	308	30	-.0720	0	TOP PCB MIDDLE POLY LAYER
169	309	30	-.0192	0	TOP PCB MIDDLE POLY LAYER
170	310	30	-.0768	0	TOP PCB MIDDLE POLY LAYER
171	311	30	-.0192	0	TOP PCB MIDDLE POLY LAYER
172	312	30	-.1056	0	TOP PCB MIDDLE POLY LAYER
173	313	30	-.0190	0	TOP PCB MIDDLE POLY LAYER
174	314	30	-.0149	0	TOP PCB MIDDLE POLY LAYER
175	315	30	-.0149	0	TOP PCB MIDDLE POLY LAYER
176	316	30	-.0149	0	TOP PCB MIDDLE POLY LAYER
177	317	30	-.0149	0	TOP PCB MIDDLE POLY LAYER
178	318	30	-.0190	0	TOP PCB MIDDLE POLY LAYER
179	319	30	-.0248	0	TOP PCB MIDDLE POLY LAYER
180	320	30	-.0195	0	TOP PCB MIDDLE POLY LAYER

```
CTRL-F1Import ITAS_NC   UDC Allowed                    PgDn PgUp Home End
SHFT-F1Import Column                      Shift-F5Del/Pur
     F1Save/Purge      F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
181	321	30	-.0195	0	TOP PCB MIDDLE POLY LAYER
182	322	30	-.0195	0	TOP PCB MIDDLE POLY LAYER
183	323	30	-.0195	0	TOP PCB MIDDLE POLY LAYER
184	324	30	-.0248	0	TOP PCB MIDDLE POLY LAYER
185	325	30	-.0161	0	TOP PCB MIDDLE POLY LAYER
186	326	30	-.0161	0	TOP PCB MIDDLE POLY LAYER
187	327	30	-.0161	0	TOP PCB MIDDLE POLY LAYER
188	328	30	-.0161	0	TOP PCB MIDDLE POLY LAYER
189	329	30	-.0161	0	TOP PCB MIDDLE POLY LAYER
190	330	30	-.0205	0	TOP PCB MIDDLE POLY LAYER
191	1301	30	-.1069	0	BOTTOM PCB MIDDLE POLY LAYER
192	1302	30	-.0627	0	BOTTOM PCB MIDDLE POLY LAYER
193	1303	30	-.0451	0	BOTTOM PCB MIDDLE POLY LAYER
194	1304	30	-.0526	0	BOTTOM PCB MIDDLE POLY LAYER
195	1305	30	-.0200	0	BOTTOM PCB MIDDLE POLY LAYER
196	1306	30	-.1000	0	BOTTOM PCB MIDDLE POLY LAYER
197	1307	30	-.0313	0	BOTTOM PCB MIDDLE POLY LAYER
198	1308	30	-.0226	0	BOTTOM PCB MIDDLE POLY LAYER

CTRL-FlImport ITAS_NC   UDC Allowed   PgDn PgUp Home End
SHFT-FlImport Column   Shift-F5Del/Pur
     FlSave/Purge   F2Help F3AutoGen F4Purge F5Delete F7Mark/UnMark F10Search

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
199	1309	30	-.0288	0	BOTTOM PCB MIDDLE POLY LAYER
200	1310	30	-.0075	0	BOTTOM PCB MIDDLE POLY LAYER
201	1311	30	-.0100	0	BOTTOM PCB MIDDLE POLY LAYER
202	1312	30	-.0100	0	BOTTOM PCB MIDDLE POLY LAYER
203	1313	30	-.0501	0	BOTTOM PCB MIDDLE POLY LAYER
204	1314	30	-.0731	0	BOTTOM PCB MIDDLE POLY LAYER
205	1315	30	-.1140	0	BOTTOM PCB MIDDLE POLY LAYER
206	1316	30	-.1403	0	BOTTOM PCB MIDDLE POLY LAYER
207	1317	30	-.0468	0	BOTTOM PCB MIDDLE POLY LAYER
208	201	30	-.0043	0	TOP PCB TOP COPPER LAYER
209	202	30	-.0058	0	TOP PCB TOP COPPER LAYER
210	203	30	-.0016	0	TOP PCB TOP COPPER LAYER
211	204	30	-.0062	0	TOP PCB TOP COPPER LAYER
212	205	30	-.0016	0	TOP PCB TOP COPPER LAYER
213	206	30	-.0085	0	TOP PCB TOP COPPER LAYER
214	207	30	-.0051	0	TOP PCB TOP COPPER LAYER
215	208	30	-.0070	0	TOP PCB TOP COPPER LAYER
216	209	30	-.0019	0	TOP PCB TOP COPPER LAYER

CTRL-FlImport ITAS_NC   UDC Allowed   PgDn PgUp Home End
SHFT-FlImport Column   Shift-F5Del/Pur
     FlSave/Purge   F2Help F3AutoGen F4Purge F5Delete F7Mark/UnMark F10Search

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
217	210	30	-.0075	0	TOP PCB TOP COPPER LAYER
218	211	30	-.0019	0	TOP PCB TOP COPPER LAYER
219	212	30	-.0103	0	TOP PCB TOP COPPER LAYER
220	213	30	-.0019	0	TOP PCB TOP COPPER LAYER
221	214	30	-.0015	0	TOP PCB TOP COPPER LAYER
222	215	30	-.0015	0	TOP PCB TOP COPPER LAYER
223	216	30	-.0015	0	TOP PCB TOP COPPER LAYER
224	217	30	-.0015	0	TOP PCB TOP COPPER LAYER
225	218	30	-.0187	0	TOP PCB TOP COPPER LAYER
226	219	30	-.0024	0	TOP PCB TOP COPPER LAYER
227	220	30	-.0019	0	TOP PCB TOP COPPER LAYER
228	221	30	-.0019	0	TOP PCB TOP COPPER LAYER
229	222	30	-.0019	0	TOP PCB TOP COPPER LAYER
230	223	30	-.0019	0	TOP PCB TOP COPPER LAYER
231	224	30	-.0024	0	TOP PCB TOP COPPER LAYER
232	225	30	-.0016	0	TOP PCB TOP COPPER LAYER
233	226	30	-.0016	0	TOP PCB TOP COPPER LAYER
234	227	30	-.0016	0	TOP PCB TOP COPPER LAYER

```
CTRL-F1Import ITAS_NC   UDC Allowed                    PgDn PgUp Home End
SHFT-F1Import Column                      Shift-F5Del/Pur
     F1Save/Purge      F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
235	228	30	-.0016	0	TOP PCB TOP COPPER LAYER
236	229	30	-.0016	0	TOP PCB TOP COPPER LAYER
237	230	30	-.0020	0	TOP PCB TOP COPPER LAYER
238	1201	30	-.0104	0	BOTTOM PCB TOP COPPER LAYER
239	1202	30	-.0061	0	BOTTOM PCB TOP COPPER LAYER
240	1203	30	-.0044	0	BOTTOM PCB TOP COPPER LAYER
241	1204	30	-.0051	0	BOTTOM PCB TOP COPPER LAYER
242	1205	30	-.0020	0	BOTTOM PCB TOP COPPER LAYER
243	1206	30	-.0098	0	BOTTOM PCB TOP COPPER LAYER
244	1207	30	-.0031	0	BOTTOM PCB TOP COPPER LAYER
245	1208	30	-.0022	0	BOTTOM PCB TOP COPPER LAYER
246	1209	30	-.0028	0	BOTTOM PCB TOP COPPER LAYER
247	1210	30	-.0007	0	BOTTOM PCB TOP COPPER LAYER
248	1211	30	-.0010	0	BOTTOM PCB TOP COPPER LAYER
249	1212	30	-.0010	0	BOTTOM PCB TOP COPPER LAYER
250	1213	30	-.0049	0	BOTTOM PCB TOP COPPER LAYER
251	1214	30	-.0071	0	BOTTOM PCB TOP COPPER LAYER
252	1215	30	-.0111	0	BOTTOM PCB TOP COPPER LAYER

```
CTRL-F1Import ITAS_NC   UDC Allowed                    PgDn PgUp Home End
SHFT-F1Import Column                      Shift-F5Del/Pur
     F1Save/Purge      F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
253	1216	30	-.0137	0	BOTTOM PCB TOP COPPER LAYER
254	1217	30	-.0046	0	BOTTOM PCB TOP COPPER LAYER
255	101	30	-.0436	0	TOP PCB TOP POLY LAYER
256	102	30	-.0595	0	TOP PCB TOP POLY LAYER
257	103	30	-.0159	0	TOP PCB TOP POLY LAYER
258	104	30	-.0635	0	TOP PCB TOP POLY LAYER
259	105	30	-.0159	0	TOP PCB TOP POLY LAYER
260	106	30	-.0873	0	TOP PCB TOP POLY LAYER
261	107	30	-.0528	0	TOP PCB TOP POLY LAYER
262	108	30	-.0720	0	TOP PCB TOP POLY LAYER
263	109	30	-.0192	0	TOP PCB TOP POLY LAYER
264	110	30	-.0768	0	TOP PCB TOP POLY LAYER
265	111	30	-.0192	0	TOP PCB TOP POLY LAYER
266	112	30	-.1056	0	TOP PCB TOP POLY LAYER
267	113	30	-.0190	0	TOP PCB TOP POLY LAYER
268	114	30	-.0149	0	TOP PCB TOP POLY LAYER
269	115	30	-.0149	0	TOP PCB TOP POLY LAYER
270	116	30	-.0149	0	TOP PCB TOP POLY LAYER

àëëv

CTRL-F1Import ITAS_NC   UDC Allowed   PgDn PgUp Home End
SHFT-F1Import Column   Shift-F5Del/Pur
       F1Save/Purge   F2Help F3AutoGen F4Purge F5Delete F7Mark/UnMark F10Search

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
271	117	30	-.0149	0	TOP PCB TOP POLY LAYER
272	118	30	-.0190	0	TOP PCB TOP POLY LAYER
273	119	30	-.0248	0	TOP PCB TOP POLY LAYER
274	120	30	-.0195	0	TOP PCB TOP POLY LAYER
275	121	30	-.0195	0	TOP PCB TOP POLY LAYER
276	122	30	-.0195	0	TOP PCB TOP POLY LAYER
277	123	30	-.0195	0	TOP PCB TOP POLY LAYER
278	124	30	-.0248	0	TOP PCB TOP POLY LAYER
279	125	30	-.0161	0	TOP PCB TOP POLY LAYER
280	126	30	-.0161	0	TOP PCB TOP POLY LAYER
281	127	30	-.0161	0	TOP PCB TOP POLY LAYER
282	128	30	-.0161	0	TOP PCB TOP POLY LAYER
283	129	30	-.0161	0	TOP PCB TOP POLY LAYER
284	130	30	-.0205	0	TOP PCB TOP POLY LAYER
285	1101	30	-.1069	0	BOTTOM PCB TOP POLY LAYER
286	1102	30	-.0627	0	BOTTOM PCB TOP POLY LAYER
287	1103	30	-.0451	0	BOTTOM PCB TOP POLY LAYER
288	1104	30	-.0526	0	BOTTOM PCB TOP POLY LAYER

àëëv

CTRL-F1Import ITAS_NC   UDC Allowed   PgDn PgUp Home End
SHFT-F1Import Column   Shift-F5Del/Pur
       F1Save/Purge   F2Help F3AutoGen F4Purge F5Delete F7Mark/UnMark F10Search

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
289	1105	30	-.0200	0	BOTTOM PCB TOP POLY LAYER
290	1106	30	-.1000	0	BOTTOM PCB TOP POLY LAYER
291	1107	30	-.0313	0	BOTTOM PCB TOP POLY LAYER
292	1108	30	-.0226	0	BOTTOM PCB TOP POLY LAYER
293	1109	30	-.0288	0	BOTTOM PCB TOP POLY LAYER
294	1110	30	-.0075	0	BOTTOM PCB TOP POLY LAYER
295	1111	30	-.0100	0	BOTTOM PCB TOP POLY LAYER
296	1112	30	-.0100	0	BOTTOM PCB TOP POLY LAYER
297	1113	30	-.0501	0	BOTTOM PCB TOP POLY LAYER
298	1114	30	-.0731	0	BOTTOM PCB TOP POLY LAYER
299	1115	30	-.1140	0	BOTTOM PCB TOP POLY LAYER
300	1116	30	-.1403	0	BOTTOM PCB TOP POLY LAYER
301	1117	30	-.0468	0	BOTTOM PCB TOP POLY LAYER
302	2011	30	-.0001	.039	PIN THROUGH NODE 3.01
303	2012	30	-.0001	0	PIN THROUGH NODE 3.01
304	2013	30	-.0001	0	PIN THROUGH NODE 3.01
305	2014	30	-.0001	0	PIN THROUGH NODE 3.01
306	2015	30	-.0001	0	PIN THROUGH NODE 3.01

àëëv

CTRL-F1Import ITAS_NC   UDC Allowed   PgDn PgUp Home End
SHFT-F1Import Column   Shift-F5Del/Pur
     F1Save/Purge   F2Help F3AutoGen F4Purge F5Delete F7Mark/UnMark F10Search

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
307	2016	30	-.0001	0	PIN THROUGH NODE 3.01
308	2021	30	-.0004	.018	PIN THROUGH 3.02 POLY LAYERS
309	2023	30	-.0004	0	PIN THROUGH 3.02 POLY LAYERS
310	2025	30	-.0004	0	PIN THROUGH 3.02 POLY LAYERS
311	2022	30	-.0001	0	PIN THROUGH 3.02 COPPER LAYERS
312	2024	30	-.0001	0	PIN THROUGH 3.02 COPPER LAYERS
313	2026	30	-.0001	0	PIN THROUGH 3.02 COPPER LAYERS
314	2031	30	-.0001	.039	PIN THROUGH 3.03 POLY LAYERS
315	2033	30	-.0001	0	PIN THROUGH 3.03 POLY LAYERS
316	2035	30	-.0001	0	PIN THROUGH 3.03 POLY LAYERS
317	2032	30	-.0001	0	PIN THROUGH 3.03 COPPER LAYERS
318	2034	30	-.0001	0	PIN THROUGH 3.03 COPPER LAYERS
319	2036	30	-.0001	0	PIN THROUGH 3.03 COPPER LAYERS
320	2041	30	-.0004	.018	PIN THROUGH 3.04 POLY LAYERS
321	2043	30	-.0004	0	PIN THROUGH 3.04 POLY LAYERS
322	2045	30	-.0004	0	PIN THROUGH 3.04 POLY LAYERS
323	2042	30	-.0001	0	PIN THROUGH 3.04 COPPER LAYERS
324	2044	30	-.0001	0	PIN THROUGH 3.04 COPPER LAYERS

àëëv

CTRL-F1Import ITAS_NC   UDC Allowed   PgDn PgUp Home End
SHFT-F1Import Column   Shift-F5Del/Pur
     F1Save/Purge   F2Help F3AutoGen F4Purge F5Delete F7Mark/UnMark F10Search

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
325	2046	30	-.0001	0	PIN THROUGH 3.04 COPPER LAYERS
326	2051	30	-.0001	.088	PIN THROUGH 3.05 POLY LAYERS
327	2053	30	-.0001	0	PIN THROUGH 3.05 POLY LAYERS
328	2055	30	-.0001	0	PIN THROUGH 3.05 POLY LAYERS
329	2061	30	-.0004	.035	PIN THROUGH 3.06 POLY LAYERS
330	2063	30	-.0004	0	PIN THROUGH 3.06 POLY LAYERS
331	2065	30	-.0004	0	PIN THROUGH 3.06 POLY LAYERS
332	2052	30	-.0001	0	PIN THROUGH 3.05 COPPER LAYERS
333	2054	30	-.0001	0	PIN THROUGH 3.05 COPPER LAYERS
334	2062	30	-.0001	0	PIN THROUGH 3.06 COPPER LAYER
335	2064	30	-.0001	0	PIN THROUGH 3.06 COPPER LAYER
336	2066	30	-.0001	0	PIN THROUGH 3.06 COPPER LAYER
337	2071	30	-.0001	.012	PIN THROUGH 3.07 POLY LAYERS
338	2073	30	-.0001	0	PIN THROUGH 3.07 POLY LAYERS
339	2075	30	-.0001	0	PIN THROUGH 3.07 POLY LAYERS
340	2072	30	-.0001	0	PIN THROUGH 3.07 COPPER LAYERS
341	2074	30	-.0001	0	PIN THROUGH 3.07 COPPER LAYERS
342	2076	30	-.0001	0	PIN THROUGH 3.07 COPPER LAYERS

äëëv

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
343	2081	30	-.0004	.015	PIN THROUGH 3.08 POLY LAYERS
344	2083	30	-.0004	0	PIN THROUGH 3.08 POLY LAYERS
345	2085	30	-.0004	0	PIN THROUGH 3.08 POLY LAYERS
346	2082	30	-.0001	0	PIN THROUGH 3.08 COPPER LAYERS
347	2084	30	-.0001	0	PIN THROUGH 3.08 COPPER LAYERS
348	2086	30	-.0001	0	PIN THROUGH 3.08 COPPER LAYERS
349	2091	30	-.0001	.05	PIN THROUGH 3.09 POLY LAYERS
350	2093	30	-.0001	0	PIN THROUGH 3.09 POLY LAYERS
351	2095	30	-.0001	0	PIN THROUGH 3.09 POLY LAYERS
352	2092	30	-.0001	0	PIN THROUGH 3.09 COPPER LAYERS
353	2094	30	-.0001	0	PIN THROUGH 3.09 COPPER LAYERS
354	2096	30	-.0001	0	PIN THROUGH 3.09 COPPER LAYERS
355	2101	30	-.0004	.015	PIN THROUGH 3.10 POLY LAYERS
356	2103	30	-.0004	0	PIN THROUGH 3.10 POLY LAYERS
357	2105	30	-.0004	0	PIN THROUGH 3.10 POLY LAYERS
358	2102	30	-.0001	0	PIN THROUGH 3.10 COPPER LAYERS
359	2104	30	-.0001	0	PIN THROUGH 3.10 COPPER LAYERS
360	2106	30	-.0001	0	PIN THROUGH 3.10 COPPER LAYERS

äëëv

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
361	2111	30	-.0001	0	PIN THROUGH 3.11 POLY LAYERS
362	2113	30	-.0001	0	PIN THROUGH 3.11 POLY LAYERS
363	2115	30	-.0001	0	PIN THROUGH 3.11 POLY LAYERS
364	2112	30	-.0001	0	PIN THROUGH 3.12 COPPER LAYERS
365	2114	30	-.0001	0	PIN THROUGH 3.12 COPPER LAYERS
366	2116	30	-.0001	0	PIN THROUGH 3.12 COPPER LAYERS
367	2121	30	-.0002	0	PIN THROUGH 3.12 POLY LAYER
368	2123	30	-.0002	0	PIN THROUGH 3.12 POLY LAYER
369	2125	30	-.0002	0	PIN THROUGH 3.12 POLY LAYER
370	2122	30	-.0001	0	PIN THROUGH 3.12 COPPER LAYERS
371	2131	30	-.0001	.004	PIN THROUGH 2.01 POLY LAYER
372	2133	30	-.0001	0	PIN THROUGH 2.01 POLY LAYER
373	2135	30	-.0001	0	PIN THROUGH 2.01 POLY LAYER
374	2132	30	-.0001	0	PIN THROUGH 2.01 COPPER LAYERS
375	2134	30	-.0001	0	PIN THROUGH 2.01 COPPER LAYERS
376	2136	30	-.0001	0	PIN THROUGH 2.01 COPPER LAYERS
377	2141	30	-.0001	.004	PIN THROUGH 2.02 POLY LAYERS
378	2143	30	-.0001	0	PIN THROUGH 2.02 POLY LAYERS

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
379	2145	30	-.0001	0	PIN THROUGH 2.02 POLY LAYERS
380	2142	30	-.0001	0	PIN THROUGH 2.02 COPPER LAYERS
381	2144	30	-.0001	0	PIN THROUGH 2.02 COPPER LAYERS
382	2146	30	-.0001	0	PIN THROUGH 2.02 COPPER LAYERS
383	2151	30	-.0001	.001	PIN THROUGH 2.03 POLY LAYER
384	2153	30	-.0001	0	PIN THROUGH 2.03 POLY LAYER
385	2155	30	-.0001	0	PIN THROUGH 2.03 POLY LAYER
386	2152	30	-.0001	0	PIN THROUGH 2.03 COPPER LAYERS
387	2154	30	-.0001	0	PIN THROUGH 2.03 COPPER LAYERS
388	2156	30	-.0001	0	PIN THROUGH 2.03 COPPER LAYERS
389	2161	30	-.0001	.001	PIN THROUGH 2.04 POLY LAYER
390	2163	30	-.0001	0	PIN THROUGH 2.04 POLY LAYER
391	2165	30	-.0001	0	PIN THROUGH 2.04 POLY LAYER
392	2162	30	-.0001	0	PIN THROUGH 2.04 COPPER LAYERS
393	2164	30	-.0001	0	PIN THROUGH 2.04 COPPER LAYERS
394	2166	30	-.0001	0	PIN THROUGH 2.04 COPPER LAYERS
395	2171	30	-.0001	0	PIN THROUGH 2.05 POLY LAYERS
396	2173	30	-.0001	0	PIN THROUGH 2.05 POLY LAYERS

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
397	2175	30	-.0001	0	PIN THROUGH 2.05 POLY LAYERS
398	2172	30	-.0001	0	PIN THROUGH 2.05 COPPER LAYERS
399	2174	30	-.0001	0	PIN THROUGH 2.05 COPPER LAYERS
400	2176	30	-.0001	0	PIN THROUGH 2.05 COPPER LAYERS
401	2181	30	-.0001	0	PIN THROUGH 2.06 POLY LAYERS
402	2183	30	-.0001	0	PIN THROUGH 2.06 POLY LAYERS
403	2185	30	-.0001	0	PIN THROUGH 2.06 POLY LAYERS
404	2182	30	-.0001	0	PIN THROUGH 2.06 COPPER LAYERS
405	2184	30	-.0001	0	PIN THROUGH 2.06 COPPER LAYERS
406	2186	30	-.0001	0	PIN THROUGH 2.06 COPPER LAYERS
407	2191	30	-.0003	.008	PIN THROUGH 2.07 POLY LAYERS
408	2193	30	-.0003	0	PIN THROUGH 2.07 POLY LAYERS
409	2195	30	-.0003	0	PIN THROUGH 2.07 POLY LAYERS
410	2192	30	-.0001	0	PIN THROUGH 2.07 COPPER LAYERS
411	2194	30	-.0001	0	PIN THROUGH 2.07 COPPER LAYERS
412	2196	30	-.0001	0	PIN THROUGH 2.07 COPPER LAYERS
413	2201	30	-.0003	.008	PIN THROUGH 2.08 POLY LAYERS
414	2203	30	-.0003	0	PIN THROUGH 2.08 POLY LAYERS

Ctrl:Copy ITAS Node Data Entry For Thermal Analysis ESC:Quit

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
415	2205	30	-.0003	0	PIN THROUGH 2.08 POLY LAYERS
416	2202	30	-.0001	0	PIN THROUGH 2.08 COPPER LAYERS
417	2204	30	-.0001	0	PIN THROUGH 2.08 COPPER LAYERS
418	2206	30	-.0001	0	PIN THROUGH 2.08 COPPER LAYERS
419	2211	30	-.0003	.003	PIN THROUGH 2.09 POLY LAYERS
420	2213	30	-.0003	0	PIN THROUGH 2.09 POLY LAYERS
421	2215	30	-.0003	0	PIN THROUGH 2.09 POLY LAYERS
422	2212	30	-.0001	0	PIN THROUGH 2.09 COPPER LAYERS
423	2214	30	-.0001	0	PIN THROUGH 2.09 COPPER LAYERS
424	2216	30	-.0001	0	PIN THROUGH 2.09 COPPER LAYERS
425	2221	30	-.0003	.006	PIN THROUGH 2.10 POLY LAYERS
426	2223	30	-.0003	0	PIN THROUGH 2.10 POLY LAYERS
427	2225	30	-.0003	0	PIN THROUGH 2.10 POLY LAYERS
428	2222	30	-.0001	0	PIN THROUGH 2.10 COPPER LAYERS
429	2224	30	-.0001	0	PIN THROUGH 2.10 COPPER LAYERS
430	2226	30	-.0001	0	PIN THROUGH 2.10 COPPER LAYERS
431	2231	30	-.0003	0	PIN THROUGH 2.11 POLY LAYERS
432	2233	30	-.0003	0	PIN THROUGH 2.11 POLY LAYERS

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
433	2235	30	-.0003	0	PIN THROUGH 2.11 POLY LAYERS
434	2232	30	-.0001	0	PIN THROUGH 2.11 COPPER LAYERS
435	2234	30	-.0001	0	PIN THROUGH 2.11 COPPER LAYERS
436	2236	30	-.0001	0	PIN THROUGH 2.11 COPPER LAYERS
437	2241	30	-.0003	0	PIN THROUGH 2.12 POLY LAYER
438	2243	30	-.0003	0	PIN THROUGH 2.12 POLY LAYER
439	2245	30	-.0003	0	PIN THROUGH 2.12 POLY LAYER
440	2242	30	-.0001	0	PIN THROUGH 2.12 COPPER LAYERS
441	2244	30	-.0001	0	PIN THROUGH 2.12 COPPER LAYERS
442	2246	30	-.0001	0	PIN THROUGH 2.12 COPPER LAYERS
443	2251	30	-.0001	.006	PIN THROUGH 2.13 POLY LAYERS
444	2253	30	-.0001	0	PIN THROUGH 2.13 POLY LAYERS
445	2255	30	-.0001	0	PIN THROUGH 2.13 POLY LAYERS
446	2252	30	-.0001	0	PIN THROUGH 2.13 COPPER LAYERS
447	2254	30	-.0001	0	PIN THROUGH 2.13 COPPER LAYERS
448	2256	30	-.0001	0	PIN THROUGH 2.13 COPPER LAYERS
449	2261	30	-.0001	.006	PIN THROUGH 2.14 POLY LAYERS
450	2263	30	-.0001	0	PIN THROUGH 2.14 POLY LAYERS

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
451	2265	30	-.0001	0	PIN THROUGH 2.14 POLY LAYERS
452	2262	30	-.0001	0	PIN THROUGH 2.14 COPPER LAYERS
453	2264	30	-.0001	0	PIN THROUGH 2.14 COPPER LAYERS
454	2266	30	-.0001	0	PIN THROUGH 2.14 COPPER LAYERS
455	2271	30	-.0001	.001	PIN THROUGH 2.15 POLY LAYERS
456	2273	30	-.0001	0	PIN THROUGH 2.15 POLY LAYERS
457	2275	30	-.0001	0	PIN THROUGH 2.15 POLY LAYERS
458	2272	30	-.0001	0	PIN THROUGH 2.15 COPPER LAYERS
459	2274	30	-.0001	0	PIN THROUGH 2.15 COPPER LAYERS
460	2276	30	-.0001	0	PIN THROUGH 2.15 COPPER LAYERS
461	2281	30	-.0001	.001	PIN THROUGH 2.16 POLY LAYERS
462	2283	30	-.0001	0	PIN THROUGH 2.16 POLY LAYERS
463	2285	30	-.0001	0	PIN THROUGH 2.16 POLY LAYERS
464	2282	30	-.0001	0	PIN THROUGH 2.16 COPPER LAYERS
465	2284	30	-.0001	0	PIN THROUGH 2.16 COPPER LAYERS
466	2286	30	-.0001	0	PIN THROUGH 2.16 COPPER LAYERS
467	2291	30	-.0001	0	PIN THROUGH 2.17 POLY LAYERS
468	2293	30	-.0001	0	PIN THROUGH 2.17 POLY LAYERS

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
469	2295	30	-.0001	0	PIN THROUGH 2.17 POLY LAYERS
470	2292	30	-.0001	0	PIN THROUGH 2.17 COPPER LAYERS
471	2294	30	-.0001	0	PIN THROUGH 2.17 COPPER LAYERS
472	2296	30	-.0001	0	PIN THROUGH 2.17 COPPER LAYERS
473	2301	30	-.0001	0	PIN THROUGH 2.18 POLY LAYERS
474	2303	30	-.0001	0	PIN THROUGH 2.18 POLY LAYERS
475	2305	30	-.0001	0	PIN THROUGH 2.18 POLY LAYERS
476	2302	30	-.0001	0	PIN THROUGH 2.18 COPPER LAYERS
477	2304	30	-.0001	0	PIN THROUGH 2.18 COPPER LAYERS
478	2306	30	-.0001	0	PIN THROUGH 2.18 COPPER LAYERS
479	3011	30	-.0011	0	PIN THROUGH 4.00 POLY LAYERS
480	3013	30	-.0011	0	PIN THROUGH 4.00 POLY LAYERS
481	3015	30	-.0011	0	PIN THROUGH 4.00 POLY LAYERS
482	3012	30	-.0001	0	PIN THROUGH 4.OO COPPER LAYERS
483	3014	30	-.0001	0	PIN THROUGH 4.OO COPPER LAYERS
484	3016	30	-.0001	0	PIN THROUGH 4.OO COPPER LAYERS
485	3021	30	-.0006	.113	PIN THROUGH 5.01 POLY LAYERS
486	3023	30	-.0006	0	PIN THROUGH 5.01 POLY LAYERS

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
487	3025	30	-.0006	0	PIN THROUGH 5.01 POLY LAYERS
488	3022	30	-.0006	0	PIN THROUGH 5.01 COPPER LAYERS
489	3024	30	-.0001	0	PIN THROUGH 5.01 COPPER LAYERS
490	3026	30	-.0001	0	PIN THROUGH 5.01 COPPER LAYERS
491	3031	30	-.0006	.036	PIN THROUGH 5.02 POLY LAYERS
492	3033	30	-.0006	0	PIN THROUGH 5.02 POLY LAYERS
493	3035	30	-.0006	0	PIN THROUGH 5.02 POLY LAYERS
494	3032	30	-.0001	0	PIN THROUGH 5.02 COPPER LAYERS
495	3034	30	-.0001	0	PIN THROUGH 5.02 COPPER LAYERS
496	3036	30	-.0001	0	PIN THROUGH 5.02 COPPER LAYERS
497	3041	30	-.0002	0	PIN THROUGH 5.03 POLY LAYERS
498	3043	30	-.0002	0	PIN THROUGH 5.03 POLY LAYERS
499	3045	30	-.0002	0	PIN THROUGH 5.03 POLY LAYERS
500	3042	30	-.0001	0	PIN THROUGH 5.03 COPPER LAYERS
501	3044	30	-.0001	0	PIN THROUGH 5.03 COPPER LAYERS
502	3046	30	-.0001	0	PIN THROUGH 5.03 COPPER LAYERS
503	3051	30	-.0005	.05	PIN THROUGH 5.04 POLY LAYERS
504	3053	30	-.0005	0	PIN THROUGH 5.04 POLY LAYERS

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
505	3055	30	-.0005	0	PIN THROUGH 5.04 POLY LAYERS
506	3052	30	-.0001	0	PIN THROUGH 5.04 COPPER LAYERS
507	3054	30	-.0001	0	PIN THROUGH 5.04 COPPER LAYERS
508	3056	30	-.0001	0	PIN THROUGH 5.04 COPPER LAYERS
509	3061	30	-.0006	.025	PIN THROUGH 5.05 POLY LAYERS
510	3063	30	-.0006	0	PIN THROUGH 5.05 POLY LAYERS
511	3065	30	-.0006	0	PIN THROUGH 5.05 POLY LAYERS
512	3062	30	-.0006	0	PIN THROUGH 5.05 COPPER LAYERS
513	3064	30	-.0001	0	PIN THROUGH 5.05 COPPER LAYERS
514	3066	30	-.0001	0	PIN THROUGH 5.05 COPPER LAYERS
515	3091	30	-.0001	.1	PIN THROUGH 6.03 POLY LAYERS
516	3093	30	-.0001	0	PIN THROUGH 6.03 POLY LAYERS
517	3095	30	-.0001	0	PIN THROUGH 6.03 POLY LAYERS
518	3092	30	-.0001	0	PIN THROUGH 6.03 COPPER LAYERS
519	3094	30	-.0001	0	PIN THROUGH 6.03 COPPER LAYERS
520	3096	30	-.0001	0	PIN THROUGH 6.03 COPPER LAYERS
521	3101	30	-.0001	.125	PIN THROUGH 6.04 POLY LAYERS
522	3103	30	-.0001	0	PIN THROUGH 6.04 POLY LAYERS

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
523	3105	30	-.0001	0	PIN THROUGH 6.04 POLY LAYERS
524	3102	30	-.0001	0	PIN THROUGH 6.04 COPPER LAYERS
525	3104	30	-.0001	0	PIN THROUGH 6.04 COPPER LAYERS
526	3106	30	-.0001	0	PIN THROUGH 6.04 COPPER LAYERS
527	3111	30	-.0001	.025	PIN THROUGH 6.05 POLY LAYERS
528	3113	30	-.0001	0.	PIN THROUGH 6.05 POLY LAYERS
529	3115	30	-.0001	0.	PIN THROUGH 6.05 POLY LAYERS
530	3112	30	-.0001	0	PIN THROUGH 6.05 COPPER LAYER
531	3114	30	-.0001	0	PIN THROUGH 6.05 COPPER LAYER
532	3116	30	-.0001	0	PIN THROUGH 6.05 COPPER LAYER
533	3121	30	-.0003	.025	PIN THROUGH 6.06 POLY LAYERS
534	3123	30	-.0003	0	PIN THROUGH 6.06 POLY LAYERS
535	3125	30	-.0003	0	PIN THROUGH 6.06 POLY LAYERS
536	3122	30	-.0001	0	PIN THROUGH 6.06 COPPER LAYERS
537	3124	30	-.0001	0	PIN THROUGH 6.06 COPPER LAYERS
538	3126	30	-.0001	0	PIN THROUGH 6.06 COPPER LAYERS
539	3141	30	-.0002	.375	PIN THROUGH 7.01 POLY LAYERS
540	3143	30	-.0002	0	PIN THROUGH 7.01 POLY LAYERS

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
541	3145	30	-.0002	0	PIN THROUGH 7.01 POLY LAYERS
542	3142	30	-.0001	0	PIN THROUGH 7.01 COPPER LAYER
543	3144	30	-.0001	0	PIN THROUGH 7.01 COPPER LAYER
544	3146	30	-.0001	0	PIN THROUGH 7.01 COPPER LAYER
545	3151	30	-.0017	.105	PIN THROUGH 7.02 POLY LAYERS
546	3153	30	-.0017	0	PIN THROUGH 7.02 POLY LAYERS
547	3155	30	-.0017	0	PIN THROUGH 7.02 POLY LAYERS
548	3152	30	-.0001	0	PIN THROUGH 7.02 COPPER LAYERS
549	3154	30	-.0001	0	PIN THROUGH 7.02 COPPER LAYERS
550	3156	30	-.0001	0	PIN THROUGH 7.02 COPPER LAYERS
551	3161	30	-.0020	.150	PIN THROUGH 7.03 POLY LAYERS
552	3163	30	-.0020	0	PIN THROUGH 7.03 POLY LAYERS
553	3165	30	-.0020	0	PIN THROUGH 7.03 POLY LAYERS
554	3162	30	-.0001	0	PIN THROUGH 7.03 COPPER LAYERS
555	3164	30	-.0001	0	PIN THROUGH 7.03 COPPER LAYERS
556	3166	30	-.0001	0	PIN THROUGH 7.03 COPPER LAYERS
557	3171	30	-.0004	0	PIN THROUGH 8.00 POLY LAYERS
558	3173	30	-.0004	0	PIN THROUGH 8.00 POLY LAYERS

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
559	3175	30	-.0004	0	PIN THROUGH 8.00 POLY LAYERS
560	3172	30	-.0001	0	PIN THROUGH 8.00 COPPER LAYERS
561	3174	30	-.0001	0	PIN THROUGH 8.00 COPPER LAYERS
562	3176	30	-.0001	0	PIN THROUGH 8.00 COPPER LAYERS
563	2056	30	-.0001	0	PIN THROUGH 3.05 COPPER LAYER
564	2124	30	-.0001	0	PIN THROUGH 3.12 COPPER LAYER
565	2126	30	-.0001	0	PIN THROUGH 3.12 COPPER LAYER

APPENDIX L. NODE TO NODE CONDUCTANCE CALCULATIONS

	HOUSING TO HOUSING NODES					
From	To	Area	Length	k		Conductance
901	905	0.3138	5.175	4.31		0.261348406
901	906	1.88	5.2845	4.31		1.53331441
901	911	0.3138	4.925	4.31		0.274614822
901	912	1.6	5.0845	4.31		1.356278887
902	903	0.3138	2.25	4.31		0.601101333
902	906	0.47	4.7845	4.31		0.423388024
902	907	0.3138	4.925	4.31		0.274614822
902	912	0.45	4.5845	4.31		0.423055949
903	904	0.3138	2.25	4.31		0.601101333
903	906	0.45	4.5845	4.31		0.423055949
903	912	0.45	4.5845	4.31		0.423055949
904	905	0.3138	2.25	4.31		0.601101333
904	906	0.45	4.5845	4.31		0.423055949
904	912	0.45	4.5845	4.31		0.423055949
905	906	0.45	4.5845	4.31		0.423055949
905	912	0.45	4.5845	4.31		0.423055949
907	906	4.925	1.6	4.31		13.26671875
907	908	0.3138	4.925	4.31		0.274614822
907	912	4.925	1.6	4.31		13.26671875
908	906	0.45	4.5845	4.31		0.423055949
908	909	0.3138	2.25	4.31		0.601101333
908	912	0.45	4.5845	4.31		0.423055949
909	906	0.45	4.5845	4.31		0.423055949
909	910	0.3138	2.25	4.31		0.601101333
909	912	0.45	4.5845	4.31		0.423055949
910	906	0.45	4.5845	4.31		0.423055949
910	911	0.3138	2.25	4.31		0.601101333
910	912	0.45	4.5845	4.31		0.423055949
911	906	0.45	4.5845	4.31		0.423055949
911	912	0.45	4.5845	4.31		0.423055949

		PCB BOARD TO RAIL CONDUCTANCES				
						/
		FROM	TO	AREA	LENGTH	k	Conductance
BOTTOM RAIL TO		921	901	0.0625	4.6	4.31	0.058559783
EPS HOUSING (+Y)		921	907	0.0625	4.6	4.31	0.058559783
		921	902	0.587	0.225	4.31	11.24431111
		921	903	0.587	0.225	4.31	11.24431111
		921	904	0.587	0.225	4.31	11.24431111
		921	905	0.587	0.225	4.31	11.24431111
		921	906	2.25	2.25	4.31	4.31
MIDDLE RAIL TO		922	901	0.09375	4.6	4.31	0.087839674
EPS HOUSING (+Y)		922	907	0.09375	4.6	4.31	0.087839674
		922	902	0.881	0.225	4.31	16.87604444
		922	903	0.881	0.225	4.31	16.87604444
		922	904	0.881	0.225	4.31	16.87604444
		922	905	0.881	0.225	4.31	16.87604444
TOP RAIL TO		923	901	0.04975	4.6	4.31	0.046613587
EPS HOUSING (+Y)		923	907	0.04975	4.6	4.31	0.046613587
		923	902	0.4279	0.225	4.31	8.196662222
		923	903	0.4677	0.225	4.31	8.959053333
		923	904	0.4677	0.225	4.31	8.959053333
		923	905	0.4279	0.225	4.31	8.196662222
		923	906	1.791	2.25	4.31	3.43076
BOTTOM RAIL TO		924	901	0.0625	4.6	4.31	0.058559783
EPS HOUSING (-Y)		924	907	0.0625	4.6	4.31	0.058559783
		924	908	0.5875	0.225	4.31	11.25388889
		924	909	0.5875	0.225	4.31	11.25388889
		924	910	0.587	0.225	4.31	11.24431111
		924	911	0.5875	0.225	4.31	11.25388889
		924	912	2.25	2.25	4.31	4.31
MIDDLE RAIL TO		925	901	0.09375	4.6	4.31	0.087839674
EPS HOUSING (-Y)		925	907	0.09375	4.6	4.31	0.087839674
		925	908	0.881	0.225	4.31	16.87604444
		925	909	0.881	0.225	4.31	16.87604444
		925	910	0.881	0.225	4.31	16.87604444
		925	911	0.881	0.225	4.31	16.87604444
TOP RAIL TO		926	901	0.04975	4.6	4.31	0.046613587
EPS HOUSING (-Y)		926	907	0.04975	4.6	4.31	0.046613587
		926	908	0.4279	0.225	4.31	8.196662222
		926	909	0.4677	0.225	4.31	8.959053333
		926	910	0.4677	0.225	4.31	8.959053333
		926	911	0.4279	0.225	4.31	8.196662222
		926	912	1.791	2.25	4.31	3.43076

Label	FROM	TO	A1.2	L1	L2	k-Cu/kpol	k-Al	hc'	hc	K1	K2	K0
BOTTOM PCB	1601	924	0.25	0.00067	0.125	9.65	4.31	3.78	0.945	3600.746	8.62	0.851435
	1602	924	0.39	0.00067	0.125	9.65	4.31	3.78	1.4742	5617.164	13.4472	1.328238
THRMAL	1603	924	0.281	0.00067	0.125	9.65	4.31	3.78	1.06218	4047.239	9.68888	0.957013
LAYER	1604	924	0.328	0.00067	0.125	9.65	4.31	3.78	1.23984	4724.179	11.30944	1.117082
TO	1605	924	0.125	0.00067	0.125	9.65	4.31	3.78	0.4725	1800.373	4.31	0.425717
BOTTOM	1606	924	0.625	0.00067	0.125	9.65	4.31	3.78	2.3625	9001.866	21.55	2.128587
RAIL	1617	924	0.25	0.00067	0.125	9.65	4.31	3.78	0.945	3600.746	8.62	0.851435
	1601	921	0.25	0.00067	0.125	9.65	4.31	3.78	0.945	3600.746	8.62	0.851435
	1614	921	0.39	0.00067	0.125	9.65	4.31	3.78	1.4742	5617.164	13.4472	1.328238
	1615	921	0.609	0.00067	0.125	9.65	4.31	3.78	2.30202	8771.418	20.99832	2.074095
	1616	921	0.75	0.00067	0.125	9.65	4.31	3.78	2.835	10802.24	25.86	2.554304
	1617	921	0.25	0.00067	0.125	9.65	4.31	3.78	0.945	3600.746	8.62	0.851435
BOTTOM	1101	925	0.25	0.00967	0.1875	0.2	4.31	0.242	0.0605	5.170631	5.746667	0.059184
PCB POLY	1102	925	0.39	0.00967	0.1875	0.2	4.31	0.242	0.09438	8.066184	8.9648	0.092328
LAYER	1103	925	0.281	0.00967	0.1875	0.2	4.31	0.242	0.068002	5.811789	6.459253	0.066523
TO	1104	925	0.328	0.00967	0.1875	0.2	4.31	0.242	0.079376	6.783868	7.539627	0.07765
MIDDLE	1105	925	0.125	0.00967	0.1875	0.2	4.31	0.242	0.03025	2.585315	2.873333	0.029592
	1106	925	0.625	0.00967	0.1875	0.2	4.31	0.242	0.15125	12.92658	14.36667	0.147961
RAIL	1117	925	0.25	0.00967	0.1875	0.2	4.31	0.242	0.0605	5.170631	5.746667	0.059184
	1101	922	0.25	0.00967	0.1875	0.2	4.31	0.242	0.0605	5.170631	5.746667	0.059184
	1114	922	0.39	0.00967	0.1875	0.2	4.31	0.242	0.09438	8.066184	8.9648	0.092328
	1115	922	0.609	0.00967	0.1875	0.2	4.31	0.242	0.147378	12.59566	13.99888	0.144173
	1116	922	0.75	0.00967	0.1875	0.2	4.31	0.242	0.1815	15.51189	17.24	0.177553
	1117	922	0.25	0.00967	0.1875	0.2	4.31	0.242	0.0605	5.170631	5.746667	0.059184
TOP PCB	601	925	0.3438	0.00067	0.1875	9.65	4.31	3.78	1.299564	4951.746	7.902816	1.115788
THERMAL	602	925	0.4688	0.00067	0.1875	9.65	4.31	3.78	1.772064	6752.119	10.77615	1.521469
LAYER	603	925	0.125	0.00067	0.1875	9.65	4.31	3.78	0.4725	1800.373	2.873333	0.405682
TO	604	925	0.5	0.00067	0.1875	9.65	4.31	3.78	1.89	7201.493	11.49333	1.622728
MIDDLE	605	925	0.125	0.00067	0.1875	9.65	4.31	3.78	0.4725	1800.373	2.873333	0.405682
RAIL	606	925	0.6875	0.00067	0.1875	9.65	4.31	3.78	2.59875	9902.052	15.80333	2.231251
	625	922	0.6875	0.00067	0.1875	9.65	4.31	3.78	2.59875	9902.052	15.80333	2.231251
	626	922	0.3438	0.00067	0.1875	9.65	4.31	3.78	1.299564	4951.746	7.902816	1.115788
	627	922	0.3438	0.00067	0.1875	9.65	4.31	3.78	1.299564	4951.746	7.902816	1.115788

628		922	0.3438	0.00067	0.1875	9.65	4.31	3.78	1.299564	4951.746	7.902816	1.115788
629		922	0.3438	0.00067	0.1875	9.65	4.31	3.78	1.299564	4951.746	7.902816	1.115788
630		922	0.6875	0.00067	0.1875	9.65	4.31	3.78	2.59875	9902.052	15.80333	2.231251
101	TOP PCB	926	0.3438	0.00967	0.0995	0.2	4.31	0.242	0.0832	7.110651	14.89224	0.081786
102	THERMAL	926	0.4688	0.00967	0.0995	0.2	4.31	0.242	0.11345	9.695967	20.30681	0.111522
103	LAYER	926	0.125	0.00967	0.0995	0.2	4.31	0.242	0.03025	2.585315	5.414573	0.029736
104	TO	926	0.5	0.00967	0.0995	0.2	4.31	0.242	0.121	10.34126	21.65829	0.118944
105	MIDDLE	926	0.125	0.00967	0.0995	0.2	4.31	0.242	0.03025	2.585315	5.414573	0.029736
106	RAIL	926	0.6875	0.00967	0.0995	0.2	4.31	0.242	0.166375	14.21923	29.78015	0.163548
125		923	0.6875	0.00967	0.0995	0.2	4.31	0.242	0.166375	14.21923	29.78015	0.163548
126		923	0.3438	0.00967	0.0995	0.2	4.31	0.242	0.0832	7.110651	14.89224	0.081786
127		923	0.3438	0.00967	0.0995	0.2	4.31	0.242	0.0832	7.110651	14.89224	0.081786
128		923	0.3438	0.00967	0.0995	0.2	4.31	0.242	0.0832	7.110651	14.89224	0.081786
129		923	0.3438	0.00967	0.0995	0.2	4.31	0.242	0.0832	7.110651	14.89224	0.081786
130		923	0.6875	0.00967	0.0995	0.2	4.31	0.242	0.166375	14.21923	29.78015	0.163548

APPLIES TO LAYERS	TOP PCB THERMAL LAYER NODE TO NODE				
4XX AND 2XX					
FROM	TO	AREA	LENGTH	k	Conductance
601	602	0.003183	1.625	9.65	0.018902123
601	607	0.00184	2.625	9.65	0.00676419
602	603	0.003183	1.1875	9.65	0.025866063
602	608	0.02513	2.625	9.65	0.092382667
603	604	0.003138	1.25	9.65	0.02422536
603	609	0.0007	2.625	9.65	0.002573333
604	605	0.003183	1.25	9.65	0.02457276
604	610	0.00268	2.625	9.65	0.00985219
605	606	0.003138	2	9.65	0.018634892
605	611	0.0007	2.625	9.65	0.002573333
606	612	0.00369	2.625	9.65	0.013565143
607	608	0.00385	1.625	9.65	0.022863077
607	613	0.00184	1.84375	9.65	0.009630373
608	609	0.00385	1.875	9.65	0.019814667
608	613	0.0005	1.84375	9.65	0.002616949
608	614	0.00184	1.84375	9.65	0.009630373
608	615	0.00775	1.84375	9.65	0.040562712
609	610	0.00385	1.25	9.65	0.029722
609	615	0.0007	1.84375	9.65	0.003663729
610	611	0.00385	1.25	9.65	0.029722
610	615	0.001	1.84375	9.65	0.005233898
610	616	0.00168	1.84375	9.65	0.008792949
611	612	0.00385	1.625	9.65	0.022863077
611	616	0.00168	1.84375	9.65	0.008792949
611	617	0.0005	1.84375	9.65	0.002616949
612	617	0.00134	1.84375	9.65	0.007013424
612	618	0.00235	1.84375	9.65	0.012299661
613	614	0.00116	1.5625	9.65	0.00716416
613	619	0.00235	0.9375	9.65	0.024189333
614	615	0.00116	1.375	9.65	0.008141091
614	620	0.00184	0.9375	9.65	0.018939733
615	616	0.00116	1.375	9.65	0.008141091

615	621	0.00178	0.9375	9.65	0.018322133
616	617	0.00116	1.375	9.65	0.008141091
616	622	0.00184	0.9375	9.65	0.018939733
617	618	0.00116	2	9.65	0.00716416
617	623	0.00184	0.9375	9.65	0.018939733
618	624	0.001	0.9375	9.65	0.010293333
619	620	0.00142	1.5625	9.65	0.00876992
619	625	0.00235	0.96875	9.65	0.023409032
620	621	0.00142	1.375	9.65	0.009965818
620	626	0.00184	0.96875	9.65	0.018328774
621	622	0.00142	1.375	9.65	0.009965818
621	627	0.00178	0.96875	9.65	0.017731097
622	623	0.00142	0.96875	9.65	0.014145032
622	628	0.00184	1.375	9.65	0.012913455
623	624	0.00142	1.5625	9.65	0.00876992
623	629	0.00184	0.96875	9.65	0.018328774
624	630	0.001	0.96875	9.65	0.00996129
625	626	0.00173	1.5625	9.65	0.01068448
626	627	0.00173	1.375	9.65	0.012141455
627	628	0.00173	1.375	9.65	0.012141455
628	629	0.00173	1.375	9.65	0.012141455
629	630	0.00173	1.5625	9.65	0.01068448

TOP PCB POLYIMIDE LAYER NODE TO NODE

APPLIES TO LAYERS	FROM	TO	AREA	LENGTH	k	CONDUCTANCE
3XX AND 1XX	501	502	0.04591	1.625	0.2	0.005650462
	501	507	0.02658	2.625	0.2	0.002025143
	502	503	0.04591	1.1874	0.2	0.007732862
	502	508	0.03624	2.625	0.2	0.002761143
	503	504	0.04591	1.25	0.2	0.0073456
	503	509	0.09665	2.625	0.2	0.00736381
	504	505	0.04591	1.25	0.2	0.0073456
	504	510	0.03866	2.625	0.2	0.002945524
	505	506	0.04591	1.625	0.2	0.005650462
	505	511	0.09665	2.625	0.2	0.00736381
	506	512	0.05316	2.625	0.2	0.004050286
	507	508	0.05557	1.625	0.2	0.006839385
	507	513	0.02658	1.184375	0.2	0.004488443
	508	509	0.05557	1.1875	0.2	0.009359158
	508	513	0.00725	1.184375	0.2	0.001224274
	508	514	0.02658	1.184375	0.2	0.004488443
	508	515	0.00242	1.184375	0.2	0.000408654
	509	510	0.05557	1.25	0.2	0.0088912
	509	515	0.09665	1.184375	0.2	0.016320844
	510	511	0.05557	1.25	0.2	0.0088912
	510	515	0.0145	1.184375	0.2	0.002448549
	510	516	0.024163	1.184375	0.2	0.004080296
	511	512	0.05557	2	0.2	0.006839385
	511	516	0.02416	1.184375	0.2	0.004079789
	511	517	0.007249	1.184375	0.2	0.001224106
	512	517	0.01933	1.184375	0.2	0.003264169
	512	518	0.033828	1.184375	0.2	0.00571238
	513	514	0.01576	1.562	0.2	0.002017926
	513	519	0.03383	0.9375	0.2	0.007217067
	514	515	0.015706	1.375	0.2	0.002284509
	514	520	0.02658	0.9375	0.2	0.0056704
	515	516	0.015706	1.375	0.2	0.002284509
	515	521	0.02658	0.9375	0.2	0.0056704

516	517	0.015706	1.375	0.2	0.002284509
516	522	0.02658	0.9375	0.2	0.0056704
517	518	0.015706	1.5625	0.2	0.002010368
517	523	0.02658	0.9375	0.2	0.0056704
518	524	0.03383	0.9375	0.2	0.007217067
519	520	0.02054	1.5625	0.2	0.00262912
519	525	0.03383	0.96875	0.2	0.006984258
520	521	0.02054	1.375	0.2	0.002987636
520	526	0.02658	0.96875	0.2	0.005487484
521	522	0.02054	1.375	0.2	0.002987636
521	527	0.02658	0.96875	0.2	0.005487484
522	523	0.02054	1.375	0.2	0.002987636
522	528	0.02658	0.96875	0.2	0.005487484
523	524	0.02054	1.5625	0.2	0.00262912
523	529	0.02658	0.96875	0.2	0.005487484
524	530	0.03383	0.96875	0.2	0.006984258
525	526	0.01691	1.5625	0.2	0.00216448
526	527	0.01691	1.375	0.2	0.002459636
527	528	0.01691	1.375	0.2	0.002459636
528	529	0.01691	1.375	0.2	0.002459636
529	530	0.01691	1.5625	0.2	0.00216448

APPLIES TO	FROM	TO	A1.2	L1	L2	k-Cu	k-poly	hc'	hc		K1	K2	K0
ALL TOP PCB LAYERS	601	501	3.2656	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.63124	974.806	67.54085	0.624995
	602	502	4.4531	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.860784	1329.284	92.10134	0.852267
	603	503	1.1875	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.229544	354.4776	24.5605	0.227272
	604	504	4.75	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.918175	1417.91	98.24199	0.90909
	605	505	4.75	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.918175	1417.91	98.24199	0.90909
	606	506	6.531	0.00067	0.00967	9.65	9.65	0.2	0.1933	1.262442	1949.552	135.0776	1.249951
	607	507	3.953	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.764115	1180	81.75801	0.756554
	608	508	5.391	0.00067	0.00967	9.65	9.65	0.2	0.1933	1.04208	1609.254	111.4995	1.031769
	609	509	1.4375	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.277869	429.1045	29.73113	0.275119
	610	510	5.75	0.00067	0.00967	9.65	9.65	0.2	0.1933	1.111475	1716.418	118.9245	1.100477
	611	511	5.75	0.00067	0.00967	9.65	9.65	0.2	0.1933	1.111475	1716.418	118.9245	1.100477
	612	512	7.906	0.00067	0.00967	9.65	9.65	0.2	0.1933	1.52823	2360	163.516	1.513108
	613	513	1.421	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.274679	424.1791	29.38987	0.271961
	614	514	1.117	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.215916	333.4328	23.10238	0.21378
	615	515	1.117	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.215916	333.4328	23.10238	0.21378
	616	516	1.117	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.215916	333.4328	23.10238	0.21378
	617	517	1.117	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.215916	333.4328	23.10238	0.21378
	618	518	1.421	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.274679	424.1791	29.38987	0.271961
	619	519	1.859	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.359345	554.9254	38.44881	0.355789
	620	520	1.461	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.282411	436.1194	30.21717	0.279617
	621	521	1.461	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.282411	436.1194	30.21717	0.279617
	622	522	1.461	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.282411	436.1194	30.21717	0.279617
	623	523	1.461	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.282411	436.1194	30.21717	0.279617
	624	524	1.859	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.359345	554.9254	38.44881	0.355789
	625	525	1.531	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.295942	457.0149	31.66494	0.293014
	626	526	1.203	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.23254	359.1045	24.88108	0.230239
	627	527	1.203	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.23254	359.1045	24.88108	0.230239
	628	528	1.203	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.23254	359.1045	24.88108	0.230239
	629	529	1.203	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.23254	359.1045	24.88108	0.230239
	630	530	1.531	0.00067	0.00967	9.65	9.65	0.2	0.1933	0.295942	457.0149	31.66494	0.293014

BOTTOM PCB THERMAL LAYER NODE TO NODE

APPLIES TO LAYERS					
4XX AND 2XX					
FROM	TO	AREA	LENGTH	k	CONDUCTANCE
1601	1602	0.00402	1.281	0.2	0.000627635
1601	1607	0.00201	1.281	0.2	0.000313817
1601	1614	0.00469	1.281	0.2	0.00073224
1602	1603	0.00402	1.3438	0.2	0.000598303
1602	1607	0.00294	2.25	0.2	0.000261333
1603	1604	0.00402	1.2188	0.2	0.000659665
1603	1608	0.00151	2.25	0.2	0.000134222
1604	1605	0.00402	0.906	0.2	0.000887417
1604	1609	0.00059	2.25	0.2	5.24444E-05
1604	1610	0.0005	2.25	0.2	4.44444E-05
1604	1611	0.00067	2.25	0.2	5.95556E-05
1605	1606	0.00402	1.5	0.2	0.000536
1605	1612	0.00059	2.25	0.2	5.24444E-05
1606	1617	0.00402	1.75	0.2	0.000459429
1606	1613	0.00335	2.25	0.2	0.000297778
1607	1608	0.00201	1.3438	0.2	0.000299152
1607	1614	0.002094	2.25	0.2	0.000186133
1608	1609	0.00201	1.438	0.2	0.000279555
1608	1615	0.001508	2.25	0.2	0.000134044
1609	1610	0.00201	0.406	0.2	0.000990148
1609	1615	0.00059	2.25	0.2	5.24444E-05
1610	1611	0.00201	0.438	0.2	0.000917808
1610	1615	0.0005	2.25	0.2	4.44444E-05
1611	1612	0.00201	0.5	0.2	0.000804
1611	1615	0.00067	2.25	0.2	5.95556E-05
1612	1613	0.00201	1.5	0.2	0.000268
1612	1616	0.00067	2.25	0.2	5.95556E-05
1613	1617	0.00335	1.75	0.2	0.000382857
1613	1616	0.00469	2.5	0.2	0.0003752
1614	1615	0.00469	2	0.2	0.000469
1615	1616	0.00469	2.719	0.2	0.00034498
1616	1617	0.00469	2	0.2	0.000469

BOTTOM PCB POLY LAYER NODE TO NODE

APPLIES TO LAYERS 13XX TO 11XX

FROM	TO	AREA	LENGTH	k	CONDUCTANCE
1501	1502	0.058	1.281	0.2	0.009055425
1501	1507	0.029	1.281	0.2	0.004527713
1501	1514	0.0677	1.281	0.2	0.010569867
1502	1503	0.058	1.344	0.2	0.008630952
1502	1507	0.0302	2.25	0.2	0.002684444
1503	1504	0.058	1.219	0.2	0.009515997
1503	1508	0.0217	2.25	0.2	0.001928889
1504	1505	0.058	0.906	0.2	0.012803532
1504	1509	0.00846	2.25	0.2	0.000752
1504	1510	0.00725	2.25	0.2	0.000644444
1504	1511	0.00967	2.25	0.2	0.000859556
1505	1506	0.058	1.5	0.2	0.007733333
1505	1512	0.00967	2.25	0.2	0.000859556
1506	1517	0.058	1.75	0.2	0.006628571
1506	1513	0.0483	2.25	0.2	0.004293333
1507	1508	0.029	1.344	0.2	0.004315476
1507	1514	0.0302	2.5	0.2	0.002416
1508	1509	0.029	1.438	0.2	0.00403338
1508	1515	0.029	2.5	0.2	0.00232
1509	1510	0.029	0.406	0.2	0.014285714
1509	1515	0.00864	2.5	0.2	0.0006912
1510	1511	0.029	0.438	0.2	0.013242009
1510	1515	0.00725	2.5	0.2	0.00058
1511	1512	0.029	0.5	0.2	0.0116
1511	1515	0.00967	2.5	0.2	0.0007736
1512	1513	0.029	1.5	0.2	0.003866667
1512	1516	0.00967	2.5	0.2	0.0007736
1513	1517	0.029	1.75	0.2	0.003314286
1513	1516	0.0483	2.5	0.2	0.003864
1514	1515	0.0677	2	0.2	0.00677
1515	1516	0.0677	2.719	0.2	0.004979772
1516	1517	0.0677	2	0.2	0.00677

BOTTOM PCB LAYER CONDUCTANCES

LAYERS	FROM	TO	A1.2	L-Cu	L-poly	k-Cu	k-poly	hc'	hc	K1	K2	K0
16XX TO 15XX	1601	1501	8	0.00067	0.00967	9.65	0.2	0.1933	1.5464	115223.9	165.4602	1.532061
	1602	1502	4.688	0.00067	0.00967	9.65	0.2	0.1933	0.90619	67521.19	96.95967	0.897788
APPLIES TO	1603	1503	3.375	0.00067	0.00967	9.65	0.2	0.1933	0.652388	48610.07	69.80352	0.646338
ALL LAYER	1604	1504	3.938	0.00067	0.00967	9.65	0.2	0.1933	0.761215	56718.96	81.44778	0.754157
TO LAYER	1605	1505	1.5	0.00067	0.00967	9.65	0.2	0.1933	0.28995	21604.48	31.02378	0.287261
CONDUCTANCES	1606	1506	7.5	0.00067	0.00967	9.65	0.2	0.1933	1.44975	108022.4	155.1189	1.436307
	1607	1507	2.344	0.00067	0.00967	9.65	0.2	0.1933	0.453095	33760.6	48.47983	0.448894
	1608	1508	1.688	0.00067	0.00967	9.65	0.2	0.1933	0.32629	24312.24	34.9121	0.323265
	1609	1509	0.6536	0.00067	0.00967	9.65	0.2	0.1933	0.126341	9413.791	13.5181	0.125169
	1610	1510	0.562	0.00067	0.00967	9.65	0.2	0.1933	0.108635	8094.478	11.62358	0.107627
	1611	1511	0.75	0.00067	0.00967	9.65	0.2	0.1933	0.144975	10802.24	15.51189	0.143631
	1612	1512	0.75	0.00067	0.00967	9.65	0.2	0.1933	0.144975	10802.24	15.51189	0.143631
	1613	1513	3.75	0.00067	0.00967	9.65	0.2	0.1933	0.724875	54011.19	77.55946	0.718153
	1614	1514	5.471	0.00067	0.00967	9.65	0.2	0.1933	1.057544	78798.73	113.1541	1.047738
	1615	1515	8.531	0.00067	0.00967	9.65	0.2	0.1933	1.649042	122871.9	176.4426	1.633751
	1616	1516	10.5	0.00067	0.00967	9.65	0.2	0.1933	2.02965	151231.3	217.1665	2.01083
	1617	1517	8	0.00067	0.00967	9.65	0.2	0.1933	1.5464	115223.9	165.4602	1.532061

FROM	TO	AREA	k-Ni	L1	K1	R1	K tot	k (Cu/poly)	hc'	hc	L2	K2	K0
2011	101	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2013	301	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2015	501	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2012	201	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2014	401	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2016	601	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2021	102	0.00204	1.77	0.0165	0.218836	4.569624	5.033236	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2023	302	0.00204	1.77	0.0165	0.218836	4.569624	5.033236	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2025	502	0.00204	1.77	0.0165	0.218836	4.569624	5.033236	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2022	202	0.000139	1.77	0.0165	0.014911	67.06499	0.342951	9.65	1.476	0.000205	0.25	0.005365	0.000197
2024	402	0.000139	1.77	0.0165	0.014911	67.06499	0.342951	9.65	1.476	0.000205	0.25	0.005365	0.000197
2026	602	0.000139	1.77	0.0165	0.014911	67.06499	0.342951	9.65	1.476	0.000205	0.25	0.005365	0.000197
2031	103	0.00204	1.77	0.0165	0.218836	4.569624	0.875345	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2033	303	0.00204	1.77	0.0165	0.218836	4.569624	0.875345	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2035	503	0.00204	1.77	0.0165	0.218836	4.569624	0.875345	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2032	203	0.000139	1.77	0.0165	0.014911	67.06499	0.059644	9.65	1.476	0.000205	0.25	0.005365	0.000197
2034	403	0.000139	1.77	0.0165	0.014911	67.06499	0.059644	9.65	1.476	0.000205	0.25	0.005365	0.000197
2036	603	0.000139	1.77	0.0165	0.014911	67.06499	0.059644	9.65	1.476	0.000205	0.25	0.005365	0.000197
2041	104	0.00204	1.77	0.0165	0.218836	4.569624	5.470909	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2043	304	0.00204	1.77	0.0165	0.218836	4.569624	5.470909	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2045	504	0.00204	1.77	0.0165	0.218836	4.569624	5.470909	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2042	204	0.000139	1.77	0.0165	0.014911	67.06499	0.372773	9.65	1.476	0.000205	0.25	0.005365	0.000198
2044	404	0.000139	1.77	0.0165	0.014911	67.06499	0.372773	9.65	1.476	0.000205	0.25	0.005365	0.000198
2046	604	0.000139	1.77	0.0165	0.014911	67.06499	0.372773	9.65	1.476	0.000205	0.25	0.005365	0.000198
2051	105	0.00204	1.77	0.0165	0.218836	4.569624	0.656509	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2053	305	0.00204	1.77	0.0165	0.218836	4.569624	0.656509	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2055	505	0.00204	1.77	0.0165	0.218836	4.569624	0.656509	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2052	205	0.000139	1.77	0.0165	0.014911	67.06499	0.044733	9.65	1.476	0.000205	0.25	0.005365	0.000197
2054	405	0.000139	1.77	0.0165	0.014911	67.06499	0.044733	9.65	1.476	0.000205	0.25	0.005365	0.000197
2056	605	0.000139	1.77	0.0165	0.014911	67.06499	0.044733	9.65	1.476	0.000205	0.25	0.005365	0.000197
2061	106	0.00204	1.77	0.0165	0.218836	4.569624	5.470909	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2063	306	0.00204	1.77	0.0165	0.218836	4.569624	5.470909	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2065	506	0.00204	1.77	0.0165	0.218836	4.569624	5.470909	0.2	0.1773	0.000362	0.25	0.001632	0.000296

111

2251	125	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2253	325	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2255	525	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2252	225	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2254	425	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2256	625	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2261	126	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2263	326	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2265	526	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2262	226	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2264	426	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2266	626	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2271	127	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2273	327	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2275	527	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2272	227	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2274	427	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2276	627	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2281	128	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2283	328	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2285	528	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2282	228	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2284	428	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2286	628	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2291	129	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2293	329	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2295	529	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2292	229	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2294	429	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2296	629	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2301	130	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2303	330	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2305	530	0.00204	1.77	0.0165	0.218836	4.569624	1.313018	0.2	0.1773	0.000362	0.25	0.001632	0.000296
2302	230	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2304	430	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197
2306	630	0.000139	1.77	0.0165	0.014911	67.06499	0.089465	9.65	1.476	0.000205	0.25	0.005365	0.000197

FROM	TO	AREA	k-Ni	L1	K1	R1	Ktot	k(Cu/poly)	hc'	hc	L2	K2	K0
3011	1101	0.00204	1.77	0.0165	0.218836	4.569624	14.00553	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3013	1301	0.00204	1.77	0.0165	0.218836	4.569624	14.00553	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3015	1501	0.00204	1.77	0.0165	0.218836	4.569624	14.00553	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3012	1201	0.00139	1.77	0.0165	0.149109	6.706499	9.542982	9.65	1.476	0.002052	0.025	0.53654	0.002043
3014	1401	0.00139	1.77	0.0165	0.149109	6.706499	9.542982	9.65	1.476	0.002052	0.025	0.53654	0.002043
3016	1601	0.00139	1.77	0.0165	0.149109	6.706499	9.542982	9.65	1.476	0.002052	0.025	0.53654	0.002043
3021	1102	0.00204	1.77	0.0165	0.218836	4.569624	7.440436	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3023	1302	0.00204	1.77	0.0165	0.218836	4.569624	7.440436	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3025	1502	0.00204	1.77	0.0165	0.218836	4.569624	7.440436	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3022	1202	0.00139	1.77	0.0165	0.149109	6.706499	5.069709	9.65	1.476	0.002052	0.025	0.53654	0.002043
3024	1402	0.00139	1.77	0.0165	0.149109	6.706499	5.069709	9.65	1.476	0.002052	0.025	0.53654	0.002043
3026	1602	0.00139	1.77	0.0165	0.149109	6.706499	5.069709	9.65	1.476	0.002052	0.025	0.53654	0.002043
3031	1103	0.00204	1.77	0.0165	0.218836	4.569624	7.002764	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3033	1303	0.00204	1.77	0.0165	0.218836	4.569624	7.002764	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3035	1503	0.00204	1.77	0.0165	0.218836	4.569624	7.002764	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3032	1203	0.00139	1.77	0.0165	0.149109	6.706499	4.771491	9.65	1.476	0.002052	0.025	0.53654	0.002043
3034	1403	0.00139	1.77	0.0165	0.149109	6.706499	4.771491	9.65	1.476	0.002052	0.025	0.53654	0.002043
3036	1603	0.00139	1.77	0.0165	0.149109	6.706499	4.771491	9.65	1.476	0.002052	0.025	0.53654	0.002043
3041	1104	0.00204	1.77	0.0165	0.218836	4.569624	7.002764	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3043	1304	0.00204	1.77	0.0165	0.218836	4.569624	7.002764	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3045	1504	0.00204	1.77	0.0165	0.218836	4.569624	7.002764	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3042	1204	0.00139	1.77	0.0165	0.149109	6.706499	4.771491	9.65	1.476	0.002052	0.025	0.53654	0.002043
3044	1404	0.00139	1.77	0.0165	0.149109	6.706499	4.771491	9.65	1.476	0.002052	0.025	0.53654	0.002043
3046	1604	0.00139	1.77	0.0165	0.149109	6.706499	4.771491	9.65	1.476	0.002052	0.025	0.53654	0.002043
3051	1105	0.00204	1.77	0.0165	0.218836	4.569624	6.127418	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3053	1305	0.00204	1.77	0.0165	0.218836	4.569624	6.127418	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3055	1505	0.00204	1.77	0.0165	0.218836	4.569624	6.127418	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3052	1205	0.00139	1.77	0.0165	0.149109	6.706499	4.175055	9.65	1.476	0.002052	0.025	0.53654	0.002043
3054	1405	0.00139	1.77	0.0165	0.149109	6.706499	4.175055	9.65	1.476	0.002052	0.025	0.53654	0.002043
3056	1605	0.00139	1.77	0.0165	0.149109	6.706499	4.175055	9.65	1.476	0.002052	0.025	0.53654	0.002043
3061	1106	0.00204	1.77	0.0165	0.218836	4.569624	7.002764	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3063	1306	0.00204	1.77	0.0165	0.218836	4.569624	7.002764	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3065	1506	0.00204	1.77	0.0165	0.218836	4.569624	7.002764	0.2	0.1773	0.000362	0.025	0.01632	0.000354

3154	1415	0.00139	1.77	0.0165	0.149109	6.706499	14.91091	9.65	1.476	0.002052	0.025	0.53654	0.002044
3156	1615	0.00139	1.77	0.0165	0.149109	6.706499	14.91091	9.65	1.476	0.002052	0.025	0.53654	0.002044
3161	1116	0.00204	1.77	0.0165	0.218836	4.569624	24.94735	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3163	1316	0.00204	1.77	0.0165	0.218836	4.569624	24.94735	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3165	1516	0.00204	1.77	0.0165	0.218836	4.569624	24.94735	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3162	1216	0.00139	1.77	0.0165	0.149109	6.706499	16.99844	9.65	1.476	0.002052	0.025	0.53654	0.002044
3164	1416	0.00139	1.77	0.0165	0.149109	6.706499	16.99844	9.65	1.476	0.002052	0.025	0.53654	0.002044
3166	1616	0.00139	1.77	0.0165	0.149109	6.706499	16.99844	9.65	1.476	0.002052	0.025	0.53654	0.002044
3171	1117	0.00204	1.77	0.0165	0.218836	4.569624	5.470909	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3173	1317	0.00204	1.77	0.0165	0.218836	4.569624	5.470909	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3175	1517	0.00204	1.77	0.0165	0.218836	4.569624	5.470909	0.2	0.1773	0.000362	0.025	0.01632	0.000354
3172	1217	0.00139	1.77	0.0165	0.149109	6.706499	3.727727	9.65	1.476	0.002052	0.025	0.53654	0.002043
3174	1417	0.00139	1.77	0.0165	0.149109	6.706499	3.727727	9.65	1.476	0.002052	0.025	0.53654	0.002043
3176	1617	0.00139	1.77	0.0165	0.149109	6.706499	3.727727	9.65	1.476	0.002052	0.025	0.53654	0.002043

PIN TO PIN CONDUCTANCES

FROM	TO	# OF PINS	AREA	ADJ AREA	LENGTH	k	k
2011	2012	6	0.0008553	0.0051318	0.06201	1.77	0.146481
2021	2022	23	0.0008553	0.0196719	0.237705	1.77	0.146481
2031	2032	4	0.0008553	0.0034212	0.04134	1.77	0.146481
2041	2042	25	0.0008553	0.0213825	0.258375	1.77	0.146481
2051	2052	3	0.0008553	0.0025659	0.031005	1.77	0.146481

APPENDIX M. ITAS CONDUCTANCE DATA

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1	1	1	901	1000	L	GEOMETRY TO HOUSING NODE
2	1	2	902	1000	L	GEOMETRY TO HOUSING NODE
3	1	3	903	1000	L	GEOMETRY TO HOUSING NODE
4	1	4	904	1000	L	GEOMETRY TO HOUSING NODE
5	1	5	905	1000	L	GEOMETRY TO HOUSING NODE
6	1	6	906	1000	L	GEOMETRY TO HOUSING NODE
7	1	7	907	1000	L	GEOMETRY TO HOUSING NODE
8	1	8	908	1000	L	GEOMETRY TO HOUSING NODE
9	1	9	909	1000	L	GEOMETRY TO HOUSING NODE
10	1	10	910	1000	L	GEOMETRY TO HOUSING NODE
11	1	11	911	1000	L	GEOMETRY TO HOUSING NODE
12	1	12	912	1000	L	GEOMETRY TO HOUSING NODE
13	1	13	613	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
14	1	14	614	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
15	1	15	615	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
16	1	16	616	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
17	1	17	617	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
18	1	18	618	1000	L	GEOMETRY TO PCB1 THERMAL LAYER

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
19	1	19	619	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
20	1	20	620	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
21	1	21	621	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
22	1	22	622	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
23	1	23	623	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
24	1	24	624	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
25	1	25	625	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
26	1	26	626	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
27	1	27	627	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
28	1	28	628	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
29	1	29	629	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
30	1	30	630	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
31	1	31	601	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER
32	1	32	602	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER
33	1	33	603	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER
34	1	34	604	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER
35	1	35	605	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER
36	1	36	606	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1	1	1	901	1000	L	GEOMETRY TO HOUSING NODE
2	1	2	902	1000	L	GEOMETRY TO HOUSING NODE
3	1	3	903	1000	L	GEOMETRY TO HOUSING NODE
4	1	4	904	1000	L	GEOMETRY TO HOUSING NODE
5	1	5	905	1000	L	GEOMETRY TO HOUSING NODE
6	1	6	906	1000	L	GEOMETRY TO HOUSING NODE
7	1	7	907	1000	L	GEOMETRY TO HOUSING NODE
8	1	8	908	1000	L	GEOMETRY TO HOUSING NODE
9	1	9	909	1000	L	GEOMETRY TO HOUSING NODE
10	1	10	910	1000	L	GEOMETRY TO HOUSING NODE
11	1	11	911	1000	L	GEOMETRY TO HOUSING NODE
12	1	12	912	1000	L	GEOMETRY TO HOUSING NODE
13	1	13	613	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
14	1	14	614	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
15	1	15	615	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
16	1	16	616	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
17	1	17	617	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
18	1	18	618	1000	L	GEOMETRY TO PCB1 THERMAL LAYER

```
CTRL-F1Import ITAS_NC     ALT-F3AutoMLI    UDC Allowed              PgDn PgUp Home
SHFT-F1Import Column    Shift-F3AutoCHT    Shift-F5Del/Pur                    End
      F1Save/Purge        F2Help F3AutoGen F4Purge F5Delete   F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
19	1	19	619	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
20	1	20	620	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
21	1	21	621	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
22	1	22	622	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
23	1	23	623	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
24	1	24	624	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
25	1	25	625	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
26	1	26	626	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
27	1	27	627	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
28	1	28	628	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
29	1	29	629	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
30	1	30	630	1000	L	GEOMETRY TO PCB1 THERMAL LAYER
31	1	31	601	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER
32	1	32	602	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER
33	1	33	603	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER
34	1	34	604	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER
35	1	35	605	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER
36	1	36	606	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER

```
CTRL-F1Import ITAS_NC     ALT-F3AutoMLI    UDC Allowed              PgDn PgUp Home
SHFT-F1Import Column    Shift-F3AutoCHT    Shift-F5Del/Pur                    End
      F1Save/Purge        F2Help F3AutoGen F4Purge F5Delete   F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
37	1	37	607	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER
38	1	38	608	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER
39	1	39	609	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER
40	1	40	610	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER
41	1	41	611	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER
42	1	42	612	1000	L	GEOMETRY TO TOP PCB THERMAL LAYER
43	1	43	1601	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR
44	1	44	1602	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR
45	1	45	1603	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR
46	1	46	1604	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR
47	1	47	1605	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR
48	1	48	1606	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR
49	1	49	1607	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR
50	1	50	1608	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR
51	1	51	1609	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR
52	1	52	1610	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR
53	1	53	1611	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR
54	1	54	1612	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
55	1	55	1613	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR
56	1	56	1614	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR
57	1	57	1615	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR
58	1	58	1616	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR
59	1	59	1617	1000	L	GEOMETRY TO BOTTOM PCB THERMA LYR
60	1	913	912	178.47	L	EQUIPMENT PLATE TO EPS HOUSING
61	1	901	905	.26135	L	HOUSING NODES TO HOUSING NODES
62	1	901	906	1.5333	L	HOUSING NODES TO HOUSING NODES
63	1	901	911	.27461	L	HOUSING NODES TO HOUSING NODES
64	1	901	912	1.3563	L	HOUSING NODES TO HOUSING NODES
65	1	902	903	.60110	L	HOUSING NODES TO HOUSING NODES
66	1	902	906	.42339	L	HOUSING NODES TO HOUSING NODES
67	1	902	907	.27461	L	HOUSING NODES TO HOUSING NODES
68	1	902	912	.42306	L	HOUSING NODES TO HOUSING NODES
69	1	903	904	.60110	L	HOUSING NODES TO HOUSING NODES
70	1	903	906	.42306	L	HOUSING NODES TO HOUSING NODES
71	1	903	912	.42306	L	HOUSING NODES TO HOUSING NODES
72	1	904	905	.60110	L	HOUSING NODES TO HOUSING NODES

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
73	1	904	906	.42306	L	HOUSING TO HOUSING NODES
74	1	904	912	.42306	L	HOUSING TO HOUSING NODES
75	1	905	906	.42306	L	HOUSING TO HOUSING NODES
76	1	905	912	.42306	L	HOUSING TO HOUSING NODES
77	1	907	906	13.2667	L	HOUSING TO HOUSING NODES
78	1	907	908	.27461	L	HOUSING TO HOUSING NODES
79	1	907	912	13.2667	L	HOUSING TO HOUSING NODES
80	1	908	906	.42306	L	HOUSING TO HOUSING NODES
81	1	908	910	.60110	L	HOUSING TO HOUSING NODES
82	1	908	912	.42306	L	HOUSING TO HOUSING NODES
83	1	909	906	.42306	L	HOUSING TO HOUSING NODES
84	1	909	910	.60110	L	HOUSING TO HOUSING NODES
85	1	909	912	.42306	L	HOUSING TO HOUSING NODES
86	1	910	906	.42306	L	HOUSING TO HOUSING NODES
87	1	910	911	.60110	L	HOUSING TO HOUSING NODES
88	1	910	912	.42306	L	HOUSING TO HOUSING NODES
89	1	911	906	.42306	L	HOUSING TO HOUSING NODES
90	1	911	912	.42306	L	HOUSING TO HOUSING NODES

```
CTRL-FlImport ITAS_NC     ALT-F3AutoMLI    UDC Allowed                PgDn PgUp Home
SHFT-FlImport Column    Shift-F3AutoCHT    Shift-F5Del/Pur                      End
       FlSave/Purge        F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark FlOSearch
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
91	1	921	901	.05856	L	BOTTOM RAIL TO EPS HOUSING (+Y)
92	1	921	907	.05856	L	BOTTOM RAIL TO EPS HOUSING (+Y)
93	1	921	902	11.2443	L	BOTTOM RAIL TO EPS HOUSING (+Y)
94	1	921	903	11.2443	L	BOTTOM RAIL TO EPS HOUSING (+Y)
95	1	921	904	11.2443	L	BOTTOM RAIL TO EPS HOUSING (+Y)
96	1	921	905	11.2443	L	BOTTOM RAIL TO EPS HOUSING (+Y)
97	1	921	906	4.31	L	BOTTOM RAIL TO EPS HOUSING (+Y)
98	1	922	901	.08784	L	MIDDLE RAIL TO EPS HOUSING (+Y)
99	1	922	907	.08784	L	MIDDLE RAIL TO EPS HOUSING (+Y)
100	1	922	902	16.8760	L	MIDDLE RAIL TO EPS HOUSING (+Y)
101	1	922	903	16.8760	L	MIDDLE RAIL TO EPS HOUSING (+Y)
102	1	922	904	16.8760	L	MIDDLE RAIL TO EPS HOUSING (+Y)
103	1	922	905	16.8760	L	MIDDLE RAIL TO EPS HOUSING (+Y)
104	1	923	901	.04661	L	TOP RAIL TO EPS HOUSING (+Y)
105	1	923	907	.04661	L	TOP RAIL TO EPS HOUSING (+Y)
106	1	923	902	8.19666	L	TOP RAIL TO EPS HOUSING (+Y)
107	1	923	903	8.95905	L	TOP RAIL TO EPS HOUSING (+Y)
108	1	923	904	8.95905	L	TOP RAIL TO EPS HOUSING (+Y)

```
CTRL-FlImport ITAS_NC     ALT-F3AutoMLI    UDC Allowed                PgDn PgUp Home
SHFT-FlImport Column    Shift-F3AutoCHT    Shift-F5Del/Pur                      End
       FlSave/Purge        F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark FlOSearch
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
109	1	923	905	8.19666	L	TOP RAIL TO EPS HOUSING (+Y)
110	1	923	906	3.43076	L	TOP RAIL TO EPS HOUSING (+Y)
111	1	924	901	.05856	L	BOTTOM RAIL TO EPS HOUSING (-Y)
112	1	924	907	.05856	L	BOTTOM RAIL TO EPS HOUSING (-Y)
113	1	924	908	11.2443	L	BOTTOM RAIL TO EPS HOUSING (-Y)
114	1	924	909	11.2443	L	BOTTOM RAIL TO EPS HOUSING (-Y)
115	1	924	910	11.2443	L	BOTTOM RAIL TO EPS HOUSING (-Y)
116	1	924	911	11.2443	L	BOTTOM RAIL TO EPS HOUSING (-Y)
117	1	924	912	4.31	L	BOTTOM RAIL TO EPS HOUSING (-Y)
118	1	925	901	.08784	L	MIDDLE RAIL TO EPS HOUSING (-Y)
119	1	925	907	.08784	L	MIDDLE RAIL TO EPS HOUSING (-Y)
120	1	925	908	16.8760	L	MIDDLE RAIL TO EPS HOUSING (-Y)
121	1	925	909	16.8760	L	MIDDLE RAIL TO EPS HOUSING (-Y)
122	1	925	910	16.8760	L	MIDDLE RAIL TO EPS HOUSING (-Y)
123	1	925	911	16.8760	L	MIDDLE RAIL TO EPS HOUSING (-Y)
124	1	926	901	.04661	L	TOP RAIL TO EPS HOUSING (-Y)
125	1	926	907	.04661	L	TOP RAIL TO EPS HOUSING (-Y)
126	1	926	908	8.19666	L	TOP RAIL TO EPS HOUSING (-Y)

```
CTRL-FlImport ITAS_NC    ALT-F3AutoMLI   UDC Allowed            PgDn PgUp Home
SHFT-FlImport Column    Shift-F3AutoCHT   Shift-F5Del/Pur                 End
      FlSave/Purge       F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
127	1	926	909	8.95905	L	TOP RAIL TO EPS HOUSING (-Y)
128	1	926	910	8.95905	L	TOP RAIL TO EPS HOUSING (-Y)
129	1	926	911	8.19666	L	TOP RAIL TO EPS HOUSING (-Y)
130	1	926	912	3.43076	L	TOP RAIL TO EPS HOUSING (-Y)
131	1	1601	924	.85144	L	BOTTOM PCB Cu LYR TO BTM RL (-Y)
132	1	1602	924	1.3282	L	BOTTOM PCB Cu LYR TO BTM RL (-Y)
133	1	1603	924	.95701	L	BOTTOM PCB Cu LYR TO BTM RL (-Y)
134	1	1604	924	1.1171	L	BOTTOM PCB Cu LYR TO BTM RL (-Y)
135	1	1605	924	.42572	L	BOTTOM PCB Cu LYR TO BTM RL (-Y)
136	1	1606	924	2.12859	L	BOTTOM PCB Cu LYR TO BTM RL (-Y)
137	1	1617	924	.85144	L	
138	1	1601	921	.85144	L	BOTTOM PCB Cu LYR TO BTM RL (+Y)
139	1	1614	921	1.32824	L	BOTTOM PCB Cu LYR TO BTM RL (+Y)
140	1	1615	921	2.0741	L	BOTTOM PCB Cu LYR TO BTM RL (+Y)
141	1	1616	921	2.55430	L	BOTTOM PCB Cu LYR TO BTM RL (+Y)
142	1	1617	921	.85144	L	BOTTOM PCB Cu LYR TO BTM RL (+Y)
143	1	1101	925	.05918	L	BTM PCB POLY LYR TO MID RL (-Y)
144	1	1102	925	.09233	L	BTM PCB POLY LYR TO MID RL (-Y)

```
CTRL-FlImport ITAS_NC    ALT-F3AutoMLI   UDC Allowed            PgDn PgUp Home
SHFT-FlImport Column    Shift-F3AutoCHT   Shift-F5Del/Pur                 End
      FlSave/Purge       F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
145	1	1103	925	.06652	L	BTM PCB POLY LYR TO MID RL (-Y)
146	1	1104	925	.07765	L	BTM PCB POLY LYR TO MID RL (-Y)
147	1	1105	925	.02959	L	BTM PCB POLY LYR TO MID RL (-Y)
148	1	1106	925	.14796	L	BTM PCB POLY LYR TO MID RL (-Y)
149	1	1117	925	.059184	L	BTM PCB POLY LYR TO MID RL (-Y)
150	1	1101	922	.059184	L	BTM PCB POLY LYR TO MID RL (+Y)
151	1	1114	922	.092328	L	BTM PCB POLY LYR TO MID RL (+Y)
152	1	1115	922	.144173	L	BTM PCB POLY LYR TO MID RL (+Y)
153	1	1116	922	.177553	L	BTM PCB POLY LYR TO MID RL (+Y)
154	1	1117	922	.059184	L	BTM PCB POLY LYR TO MID RL (+Y)
155	1	601	925	1.11579	L	TOP PCB Cu LYR TO MID RL (-Y)
156	1	602	925	1.52147	L	TOP PCB Cu LYR TO MID RL (-Y)
157	1	603	925	.405689	L	TOP PCB Cu LYR TO MID RL (-Y)
158	1	604	925	1.62273	L	TOP PCB Cu LYR TO MID RL (-Y)
159	1	605	925	.405689	L	TOP PCB Cu LYR TO MID RL (-Y)
160	1	606	925	2.23125	L	TOP PCB Cu LYR TO MID RL (-Y)
161	1	625	922	2.23125	L	TOP PCB Cu LYR TO MID RL (+Y)
162	1	626	922	1.11579	L	TOP PCB Cu LYR TO MID RL (+Y)

```
CTRL-FlImport ITAS_NC    ALT-F3AutoMLI   UDC Allowed              PgDn PgUp Home
SHFT-FlImport Column   Shift-F3AutoCHT   Shift-F5Del/Pur                    End
       FlSave/Purge       F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
163	1	627	922	1.11579	L	TOP PCB Cu LYR TO MID RL (+Y)
164	1	628	922	1.11579	L	TOP PCB Cu LYR TO MID RL (+Y)
165	1	629	922	1.11579	L	TOP PCB Cu LYR TO MID RL (+Y)
166	1	630	922	2.23125	L	TOP PCB Cu LYR TO MID RL (+Y)
167	1	101	926	.08179	L	TOP PCB POLY LYR TO MID RL (-Y)
168	1	102	926	.11152	L	TOP PCB POLY LYR TO MID RL (-Y)
169	1	103	926	.02974	L	TOP PCB POLY LYR TO MID RL (-Y)
170	1	104	926	.11894	L	TOP PCB POLY LYR TO MID RL (-Y)
171	1	105	926	.02974	L	TOP PCB POLY LYR TO MID RL (-Y)
172	1	106	926	.16355	L	TOP PCB POLY LYR TO MID RL (-Y)
173	1	125	923	.16355	L	TOP PCB POLY LYR TO TOP RL (+Y)
174	1	126	923	.08179	L	TOP PCB POLY LYR TO TOP RL (+Y)
175	1	127	923	.08179	L	TOP PCB POLY LYR TO TOP RL (+Y)
176	1	128	923	.08179	L	TOP PCB POLY LYR TO TOP RL (+Y)
177	1	129	923	.08179	L	TOP PCB POLY LYR TO TOP RL (+Y)
178	1	130	923	.16355	L	TOP PCB POLY LYR TO TOP RL (+Y)
179	1	601	602	.018635	L	TOP PCB THERMAL LAYER NODE-NODE
180	1	601	607	.006764	L	

```
CTRL-FlImport ITAS_NC    ALT-F3AutoMLI   UDC Allowed              PgDn PgUp Home
SHFT-FlImport Column   Shift-F3AutoCHT   Shift-F5Del/Pur                    End
       FlSave/Purge       F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
181	1	602	603	.025866	L	TOP PCB THERMAL LYR NODE-NODE
182	1	602	608	.092383	L	
183	1	603	604	.02423	L	
184	1	603	609	.002573	L	
185	1	604	605	.02457	L	
186	1	604	610	.009852	L	
187	1	605	606	.018635	L	
188	1	605	611	.00257	L	
189	1	606	612	.013565	L	
190	1	607	608	.02286	L	
191	1	607	613	.009630	L	
192	1	608	609	.019815	L	
193	1	608	613	.002617	L	
194	1	608	614	.009630	L	
195	1	608	615	.04057	L	
196	1	609	610	.02972	L	
197	1	609	615	.003664	L	
198	1	610	611	.02972	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
199	1	610	615	.005234	L	TOP PCB THRML LYR NODE-NODE
200	1	610	616	.008793	L	
201	1	611	612	.022863	L	
202	1	611	616	.008793	L	
203	1	611	617	.002617	L	
204	1	612	617	.007013	L	
205	1	612	618	.01230	L	
206	1	613	614	.007164	L	
207	1	613	619	.024189	L	
208	1	614	615	.008141	L	
209	1	614	620	.018940	L	
210	1	615	616	.008141	L	
211	1	615	621	.01832	L	
212	1	616	617	.008141	L	
213	1	616	622	.018940	L	
214	1	617	618	.007164	L	
215	1	617	623	.018940	L	
216	1	618	624	.010293	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
217	1	619	620	.008770	L	TOP PCB THERMAL LYR NODE-NODE
218	1	619	625	.023410	L	
219	1	620	621	.009967	L	
220	1	620	625	.018329	L	
221	1	621	622	.009967	L	
222	1	621	627	.017731	L	
223	1	622	623	.014145	L	
224	1	622	628	.012913	L	
225	1	623	624	.008770	L	
226	1	623	629	.018324	L	
227	1	624	630	.009961	L	
228	1	625	626	.010684	L	
229	1	626	627	.012141	L	
230	1	627	628	.012141	L	
231	1	628	629	.012141	L	
232	1	629	630	.010684	L	
233	1	501	502	.005651	L	TOP PCB LOWEST POLY LYR NODE-NODE
234	1	501	507	.002025	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
235	1	502	503	.005650	L	TOP PCB BTM POLY LYR NODE-NODE
236	1	502	508	.002025	L	
237	1	503	504	.007733	L	
238	1	503	509	.002761	L	
239	1	504	505	.007346	L	
240	1	504	510	.007364	L	
241	1	505	506	.007346	L	
242	1	505	511	.002946	L	
243	1	506	512	.005650	L	
244	1	507	508	.007364	L	
245	1	507	513	.004050	L	
246	1	508	509	.006839	L	
247	1	508	513	.004488	L	
248	1	508	514	.009359	L	
249	1	508	515	.001224	L	
250	1	509	510	.004488	L	
251	1	509	515	.0004087	L	
252	1	510	511	.008891	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
253	1	510	515	.002449	L	TOP PCB BTM POLY LYR NODE-NODE
254	1	510	516	.004080	L	
255	1	511	512	.006839	L	
256	1	511	516	.004080	L	
257	1	511	517	.001224	L	
258	1	512	517	.003264	L	
259	1	512	518	.005712	L	
260	1	513	514	.002018	L	
261	1	513	519	.007217	L	
262	1	514	515	.002285	L	
263	1	514	520	.005670	L	
264	1	515	516	.002284	L	
265	1	515	521	.005670	L	
266	1	516	517	.002285	L	
267	1	516	522	.005670	L	
268	1	517	518	.002010	L	
269	1	517	523	.005670	L	
270	1	518	524	.007217	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
271	1	519	520	.002629	L	TOP PCB BTM POLY LYR NODE-NODE
272	1	519	525	.006984	L	
273	1	520	521	.002988	L	
274	1	520	526	.005487	L	
275	1	521	522	.002988	L	
276	1	521	527	.005487	L	
277	1	522	523	.002988	L	
278	1	522	528	.005487	L	
279	1	523	524	.002629	L	
280	1	523	529	.005487	L	
281	1	525	526	.002164	L	
282	1	526	527	.002460	L	
283	1	527	528	.002460	L	
284	1	528	529	.002460	L	
285	1	529	530	.002164	L	
286	1	401	402	.018902	L	TOP PCB GRND LYR NODE-NODE
287	1	401	407	.006764	L	
288	1	402	403	.025866	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
289	1	402	408	.09238	L	TOP PCB GRND LYR NODE-NODE
290	1	403	404	.02422	L	
291	1	403	409	.00257	L	
292	1	404	405	.02457	L	
293	1	404	410	.009852	L	
294	1	405	406	.01863	L	
295	1	405	411	.002573	L	
296	1	406	412	.013565	L	
297	1	407	408	.02286	L	
298	1	407	413	.009630	L	
299	1	408	409	.01981	L	
300	1	408	413	.002617	L	
301	1	408	414	.009630	L	
302	1	408	415	.04056	L	
303	1	409	410	.02972	L	
304	1	409	415	.003664	L	
305	1	410	411	.029722	L	
306	1	410	415	.005234	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
307	1	410	416	.008793	L	TOP PCB GRND LYR NODE-NODE
308	1	411	412	.022863	L	
309	1	411	416	.008793	L	
310	1	411	417	.002617	L	
311	1	412	417	.007013	L	
312	1	412	418	.01230	L	
313	1	413	414	.007164	L	
314	1	413	419	.024189	L	
315	1	414	415	.008141	L	
316	1	414	420	.018940	L	
317	1	415	416	.008141	L	
318	1	415	421	.018322	L	
319	1	416	417	.008141	L	
320	1	416	422	.018940	L	
321	1	417	418	.007164	L	
322	1	417	423	.018940	L	
323	1	418	424	.010293	L	
324	1	419	420	.008770	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
325	1	419	425	.02341	L	TOP PCB GRND LYR NODE-NODE
326	1	420	421	.009966	L	
327	1	420	426	.018329	L	
328	1	421	422	.009966	L	
329	1	421	427	.017731	L	
330	1	422	423	.014145	L	
331	1	422	428	.012913	L	
332	1	423	424	.008770	L	
333	1	423	429	.018329	L	
334	1	424	430	.009961	L	
335	1	425	426	.01068	L	
336	1	426	427	.01214	L	
337	1	427	428	.01214	L	
338	1	428	429	.01214	L	
339	1	429	430	.01068	L	
340	1	301	302	.005650	L	TOP PCB MID POLY LYR NODE-NODE
341	1	301	307	.002025	L	
342	1	302	303	.007733	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
343	1	302	308	.002761	L	TOP PCB MID POLY LYR NODE-NODE
344	1	303	304	.007346	L	
345	1	303	309	.007364	L	
346	1	304	305	.007346	L	
347	1	304	310	.002946	L	
348	1	305	306	.005650	L	
349	1	305	311	.007364	L	
350	1	306	312	.004050	L	
351	1	307	308	.006840	L	
352	1	307	313	.004488	L	
353	1	308	309	.009359	L	
354	1	308	313	.001224	L	
355	1	308	314	.004488	L	
356	1	308	315	.000408	L	
357	1	309	310	.008991	L	
358	1	309	315	.016321	L	
359	1	310	311	.00889	L	
360	1	310	315	.002449	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
361	1	310	316	.004080	L	TOP PCB MID POLY LAYER NODE-NODE
362	1	311	312	.006840	L	
363	1	311	316	.004080	L	
364	1	311	317	.001224	L	
365	1	312	317	.003264	L	
366	1	312	318	.005712	L	
367	1	313	314	.002018	L	
368	1	313	319	.007217	L	
369	1	314	315	.002285	L	
370	1	314	320	.005670	L	
371	1	315	316	.002285	L	
372	1	315	321	.005670	L	
373	1	316	317	.002285	L	
374	1	316	322	.005670	L	
375	1	317	318	.002010	L	
376	1	317	323	.005670	L	
377	1	318	324	.0007217	L	
378	1	319	320	.002629	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
379	1	319	325	.006984	L	TOP PCB MID POLY LYR NODE-NODE
380	1	320	321	.002988	L	
381	1	320	326	.005487	L	
382	1	321	322	.002988	L	
383	1	321	327	.005487	L	
384	1	322	323	.002988	L	
385	1	322	328	.005487	L	
386	1	323	324	.002629	L	
387	1	323	329	.005487	L	
388	1	324	330	.06984	L	
389	1	325	326	.002164	L	
390	1	326	327	.002460	L	
391	1	327	328	.002460	L	
392	1	328	329	.002460	L	
393	1	329	330	.002164	L	
394	1	201	202	.018902	L	TOP PCB TOP Cu LYR NODE-NODE
395	1	201	207	.006764	L	
396	1	202	203	.025866	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
397	1	202	208	.09238	L	TOP PCB TOP Cu LYR NODE-NODE
398	1	203	2045	.02423	L	
399	1	203	209	.002573	L	
400	1	204	205	.02457	L	
401	1	204	210	.00985	L	
402	1	205	206	.01863	L	
403	1	205	211	.002573	L	
404	1	206	212	.013565	L	
405	1	207	208	.022863	L	
406	1	207	213	.009630	L	
407	1	208	209	.01981	L	
408	1	208	213	.002670	L	
409	1	208	214	.009630	L	
410	1	208	215	.04056	L	
411	1	209	210	.02972	L	
412	1	209	215	.003663	L	
413	1	210	211	.02972	L	
414	1	210	215	.005234	L	

CTRL-FlImport ITAS_NC   ALT-F3AutoMLI   UDC Allowed   PgDn PgUp Home
SHFT-FlImport Column   Shift-F3AutoCHT   Shift-F5Del/Pur   End
        FlSave/Purge   F2Help F3AutoGen F4Purge F5Delete   F7Mark/UnMark F10Search

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
415	1	210	216	.008793	L	TOP PCB TOP Cu LYR NODE-NODE
416	1	211	212	.02286	L	
417	1	211	216	.008793	L	
418	1	211	217	.0026170	L	
419	1	212	217	.0070134	L	
420	1	212	218	.001230	L	
421	1	213	214	.0071641	L	
422	1	213	219	.024190	L	
423	1	214	215	.008141	L	
424	1	214	220	.018940	L	
425	1	215	216	.0081410	L	
426	1	215	221	.018322	L	
427	1	216	217	.0189397	L	
428	1	216	222	.018940	L	
429	1	217	218	.007164	L	
430	1	217	223	.0018940	L	
431	1	218	224	.010293	L	
432	1	219	220	.008770	L	

CTRL-FlImport ITAS_NC   ALT-F3AutoMLI   UDC Allowed   PgDn PgUp Home
SHFT-FlImport Column   Shift-F3AutoCHT   Shift-F5Del/Pur   End
        FlSave/Purge   F2Help F3AutoGen F4Purge F5Delete   F7Mark/UnMark F10Search

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
433	1	219	225	.02341	L	TOP PCB TOP Cu LYR NODE-NODE
434	1	220	221	.009966	L	
435	1	220	226	.018329	L	
436	1	221	222	.009966	L	
437	1	221	227	.017731	L	
438	1	222	223	.014145	L	
439	1	222	228	.01291	L	
440	1	223	224	.008770	L	
441	1	223	229	.018329	L	
442	1	224	230	.009961	L	
443	1	225	226	.010684	L	
444	1	226	227	.012141	L	
445	1	227	228	.012141	L	
446	1	228	229	.012141	L	
447	1	229	230	.010684	L	
448	1	101	102	.005650	L	TOP PCB TOP POLY LYR NODE-NODE
449	1	101	107	.002025	L	
450	1	102	103	.007733	L	

```
CTRL-F1Import ITAS_NC    ALT-F3AutoMLI    UDC Allowed              PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT   Shift-F5Del/Pur                     End
      F1Save/Purge      F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
451	1	102	108	.002761	L	TOP PCB TOP POLY LYR NODE-NODE
452	1	103	104	.0073456	L	
453	1	103	109	.0073638	L	
454	1	104	105	.007346	L	
455	1	104	110	.0029455	L	
456	1	105	106	.005650	L	
457	1	105	111	.0073638	L	
458	1	106	112	.004050	L	
459	1	107	108	.006839	L	
460	1	107	113	.004488	L	
461	1	108	109	.009359	L	
462	1	108	113	.001224	L	
463	1	108	114	.004488	L	
464	1	108	115	.0004087	L	
465	1	109	110	.0088991	L	
466	1	109	115	.01632	L	
467	1	110	111	.008891	L	
468	1	110	115	.002449	L	

```
CTRL-F1Import ITAS_NC    ALT-F3AutoMLI    UDC Allowed              PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT   Shift-F5Del/Pur                     End
      F1Save/Purge      F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
469 1		110	116	.004080	L	TOP PCB TOP POLY LYR NODE-NODE
470 1		111	112	.006839	L	
471 1		111	116	.004080	L	
472 1		111	117	.001224	L	
473 1		112	117	.032642	L	
474 1		112	118	.005712	L	
475 1		113	114	.002018	L	
476 1		113	119	.007217	L	
477 1		114	115	.002285	L	
478 1		114	120	.005670	L	
479 1		115	116	.002285	L	
480 1		115	621	.005670	L	
481 1		116	117	.002845	L	
482 1		116	122	.005670	L	
483 1		117	118	.002010	L	
484 1		117	123	.005670	L	
485 1		118	124	.007217	L	
486 1		119	120	.002629	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
487 1		119	125	.006984	L	TOP PCB TOP POLY LYR NODE-NODE
488 1		120	121	.002988	L	
489 1		120	126	.005487	L	
490 1		121	122	.002988	L	
491 1		121	127	.005487	L	
492 1		122	123	.002988	L	
493 1		122	128	.005487	L	
494 1		123	124	.002629	L	
495 1		123	129	.005487	L	
496 1		124	130	.006984	L	
497 1		125	126	.002164	L	
498 1		126	127	.002460	L	
499 1		127	128	.002460	L	
500 1		128	129	.002460	L	
501 1		129	130	.000164	L	
502 1		601	501	.625	L	TOP PCB LAYER 6XX TO 5XX
503 1		602	502	.85227	L	TOP PCB LAYER 6XX TO 5XX
504 1		603	503	.22727	L	TOP PCB LAYER 6XX TO 5XX

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
505	1	604	504	.90909	L	TOP PCB LAYER 6XX TO 5XX
506	1	605	505	.90909	L	TOP PCB LAYER 6XX TO 5XX
507	1	606	506	1.2450	L	TOP PCB LAYER 6XX TO 5XX
508	1	607	507	.75655	L	TOP PCB LAYER 6XX TO 5XX
509	1	608	508	1.03177	L	TOP PCB LAYER 6XX TO 5XX
510	1	609	509	.27512	L	TOP PCB LAYER 6XX TO 5XX
511	1	610	510	1.10048	L	TOP PCB LAYER 6XX TO 5XX
512	1	611	511	1.10048	L	TOP PCB LAYER 6XX TO 5XX
513	1	612	512	1.51311	L	TOP PCB LAYER 6XX TO 5XX
514	1	613	513	.02720	L	TOP PCB LAYER 6XX TO 5XX
515	1	614	514	.21378	L	TOP PCB LAYER 6XX TO 5XX
516	1	615	515	.21378	L	TOP PCB LAYER 6XX TO 5XX
517	1	616	516	.21378	L	TOP PCB LAYER 6XX TO 5XX
518	1	617	517	.21378	L	TOP PCB LAYER 6XX TO 5XX
519	1	618	518	.27197	L	TOP PCB LAYER 6XX TO 5XX
520	1	619	519	.35579	L	TOP PCB LAYER 6XX TO 5XX
521	1	620	520	.27962	L	TOP PCB LAYER 6XX TO 5XX
522	1	621	521	.27962	L	TOP PCB LAYER 6XX TO 5XX

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
523	1	622	522	.27962	L	TOP PCB LAYER 6XX TO 5XX
524	1	623	523	.27962	L	TOP PCB LAYER 6XX TO 5XX
525	1	624	524	.35579	L	TOP PCB LAYER 6XX TO 5XX
526	1	625	525	.29301	L	TOP PCB LAYER 6XX TO 5XX
527	1	626	526	.23024	L	TOP PCB LAYER 6XX TO 5XX
528	1	627	527	.23024	L	TOP PCB LAYER 6XX TO 5XX
529	1	628	528	.23024	L	TOP PCB LAYER 6XX TO 5XX
530	1	629	529	.23024	L	TOP PCB LAYER 6XX TO 5XX
531	1	630	530	.29301	L	TOP PCB LAYER 6XX TO 5XX
532	1	501	401	.62509	L	TOP PCB LAYER 5XX TO 4XX
533	1	502	402	.85227	L	TOP PCB LAYER 5XX TO 4XX
534	1	503	403	.22727	L	TOP PCB LAYER 5XX TO 4XX
535	1	504	404	.90909	L	TOP PCB LAYER 5XX TO 4XX
536	1	505	405	.90909	L	TOP PCB LAYER 5XX TO 4XX
537	1	506	406	1.25	L	TOP PCB LAYER 5XX TO 4XX
538	1	507	407	.75655	L	TOP PCB LAYER 5XX TO 4XX
539	1	508	408	1.03177	L	TOP PCB LAYER 5XX TO 4XX
540	1	509	409	.27512	L	TOP PCB LAYER 5XX TO 4XX

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
541	1	510	410	1.10047	L	TOP PCB LAYER 5XX TO 4XX
542	1	511	411	1.10047	L	TOP PCB LAYER 5XX TO 4XX
543	1	512	412	1.51311	L	TOP PCB LAYER 5XX TO 4XX
544	1	513	413	.27196	L	TOP PCB LAYER 5XX TO 4XX
545	1	514	414	.21378	L	TOP PCB LAYER 5XX TO 4XX
546	1	515	415	.21378	L	TOP PCB LAYER 5XX TO 4XX
547	1	516	416	.21378	L	TOP PCB LAYER 5XX TO 4XX
548	1	517	417	.21378	L	TOP PCB LAYER 5XX TO 4XX
549	1	518	418	.27196	L	TOP PCB LAYER 5XX TO 4XX
550	1	519	419	.35579	L	TOP PCB LAYER 5XX TO 4XX
551	1	520	420	.27962	L	TOP PCB LAYER 5XX TO 4XX
552	1	521	421	.27962	L	TOP PCB LAYER 5XX TO 4XX
553	1	522	422	.27962	L	TOP PCB LAYER 5XX TO 4XX
554	1	523	423	.27962	L	TOP PCB LAYER 5XX TO 4XX
555	1	524	424	.35579	L	TOP PCB LAYER 5XX TO 4XX
556	1	525	425	.29301	L	TOP PCB LAYER 5XX TO 4XX
557	1	526	426	.23024	L	TOP PCB LAYER 5XX TO 4XX
558	1	527	427	.23024	L	TOP PCB LAYER 5XX TO 4XX

```
CTRL-FlImport ITAS_NC    ALT-F3AutoMLI   UDC Allowed              PgDn PgUp Home
SHFT-FlImport Column   Shift-F3AutoCHT   Shift-F5Del/Pur                    End
     FlSave/Purge      F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark Fl0Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
559	1	528	428	.23024	L	TOP PCB LAYER 5XX TO 4XX
560	1	529	429	.23024	L	TOP PCB LAYER 5XX TO 4XX
561	1	530	430	.29301	L	TOP PCB LAYER 5XX TO 4XX
562	1	401	301	.625	L	TOP PCB LAYER 4XX TO 3XX
563	1	402	302	.85227	L	TOP PCB LAYER 4XX TO 3XX
564	1	403	303	.22727	L	TOP PCB LAYER 4XX TO 3XX
565	1	404	304	.90909	L	TOP PCB LAYER 4XX TO 3XX
566	1	405	305	.90909	L	TOP PCB LAYER 4XX TO 3XX
567	1	406	306	1.25	L	TOP PCB LAYER 4XX TO 3XX
568	1	407	307	.75655	L	TOP PCB LAYER 4XX TO 3XX
569	1	408	308	1.03177	L	TOP PCB LAYER 4XX TO 3XX
570	1	409	309	.27512	L	TOP PCB LAYER 4XX TO 3XX
571	1	410	310	1.10048	L	TOP PCB LAYER 4XX TO 3XX
572	1	411	311	1.10048	L	TOP PCB LAYER 4XX TO 3XX
573	1	412	312	1.51311	L	TOP PCB LAYER 4XX TO 3XX
574	1	413	313	.27196	L	TOP PCB LAYER 4XX TO 3XX
575	1	414	314	.21378	L	TOP PCB LAYER 4XX TO 3XX
576	1	415	315	.21378	L	TOP PCB LAYER 4XX TO 3XX

```
CTRL-FlImport ITAS_NC    ALT-F3AutoMLI   UDC Allowed              PgDn PgUp Home
SHFT-FlImport Column   Shift-F3AutoCHT   Shift-F5Del/Pur                    End
     FlSave/Purge      F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark Fl0Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
577	1	416	316	.21378	L	TOP PCB LAYER 4XX TO 3XX
578	1	417	317	.21378	L	TOP PCB LAYER 4XX TO 3XX
579	1	418	318	.27196	L	TOP PCB LAYER 4XX TO 3XX
580	1	419	319	.27196	L	TOP PCB LAYER 4XX TO 3XX
581	1	420	320	.35579	L	TOP PCB LAYER 4XX TO 3XX
582	1	421	321	.27196	L	TOP PCB LAYER 4XX TO 3XX
583	1	422	322	.27196	L	TOP PCB LAYER 4XX TO 3XX
584	1	423	323	.27196	L	TOP PCB LAYER 4XX TO 3XX
585	1	424	324	.90909	L	TOP PCB LAYER 4XX TO 3XX
586	1	425	325	.35579	L	TOP PCB LAYER 4XX TO 3XX
587	1	426	326	.29301	L	TOP PCB LAYER 4XX TO 3XX
588	1	427	327	.23024	L	TOP PCB LAYER 4XX TO 3XX
589	1	428	328	.23024	L	TOP PCB LAYER 4XX TO 3XX
590	1	429	329	.23024	L	TOP PCB LAYER 4XX TO 3XX
591	1	430	330	.29301	L	TOP PCB LAYER 4XX TO 3XX
592	1	301	201	.625	L	TOP PCB LAYER 3XX TO 2XX
593	1	302	202	.85227	L	TOP PCB LAYER 3XX TO 2XX
594	1	303	203	.22727	L	TOP PCB LAYER 3XX TO 2XX

```
CTRL-FlImport ITAS_NC     ALT-F3AutoMLI    UDC Allowed                PgDn PgUp Home
SHFT-FlImport Column   Shift-F3AutoCHT    Shift-F5Del/Pur                       End
        FlSave/Purge       F2Help F3AutoGen F4Purge F5Delete   F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
595	1	304	204	.90909	L	TOP PCB LAYER 3XX TO 2XX
596	1	305	205	.90909	L	TOP PCB LAYER 3XX TO 2XX
597	1	306	206	1.25	L	TOP PCB LAYER 3XX TO 2XX
598	1	307	207	.75655	L	TOP PCB LAYER 3XX TO 2XX
599	1	308	208	1.03177	L	TOP PCB LAYER 3XX TO 2XX
600	1	309	209	.27512	L	TOP PCB LAYER 3XX TO 2XX
601	1	310	210	1.10048	L	TOP PCB LAYER 3XX TO 2XX
602	1	311	211	1.10048	L	TOP PCB LAYER 3XX TO 2XX
603	1	312	212	1.51311	L	TOP PCB LAYER 3XX TO 2XX
604	1	313	213	.27196	L	TOP PCB LAYER 3XX TO 2XX
605	1	314	214	.21378	L	TOP PCB LAYER 3XX TO 2XX
606	1	315	215	.21378	L	TOP PCB LAYER 3XX TO 2XX
607	1	316	216	.21378	L	TOP PCB LAYER 3XX TO 2XX
608	1	317	217	.21378	L	TOP PCB LAYER 3XX TO 2XX
609	1	318	218	.27196	L	TOP PCB LAYER 3XX TO 2XX
610	1	319	219	.35559	L	TOP PCB LAYER 3XX TO 2XX
611	1	320	220	.27196	L	TOP PCB LAYER 3XX TO 2XX
612	1	321	221	.27196	L	TOP PCB LAYER 3XX TO 2XX

```
CTRL-FlImport ITAS_NC     ALT-F3AutoMLI    UDC Allowed                PgDn PgUp Home
SHFT-FlImport Column   Shift-F3AutoCHT    Shift-F5Del/Pur                       End
        FlSave/Purge       F2Help F3AutoGen F4Purge F5Delete   F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
613	1	322	222	.27196	L	TOP PCB LAYER 3XX TO 2XX
614	1	323	223	.27196	L	TOP PCB LAYER 3XX TO 2XX
615	1	324	224	.35579	L	TOP PCB LAYER 3XX TO 2XX
616	1	325	225	.29301	L	TOP PCB LAYER 3XX TO 2XX
617	1	326	226	.23024	L	TOP PCB LAYER 3XX TO 2XX
618	1	327	227	.23024	L	TOP PCB LAYER 3XX TO 2XX
619	1	328	228	.23024	L	TOP PCB LAYER 3XX TO 2XX
620	1	329	229	.23024	L	TOP PCB LAYER 3XX TO 2XX
621	1	330	230	.29301	L	TOP PCB LAYER 3XX TO 2XX
622	1	201	101	.625	L	TOP PCB LAYER 2XX TO1XX
623	1	202	102	.85227	L	TOP PCB LAYER 2XX TO1XX
624	1	203	103	.22727	L	TOP PCB LAYER 2XX TO1XX
625	1	204	104	.90909	L	TOP PCB LAYER 2XX TO1XX
626	1	205	105	.90909	L	TOP PCB LAYER 2XX TO1XX
627	1	206	106	1.25	L	TOP PCB LAYER 2XX TO1XX
628	1	207	107	.75655	L	TOP PCB LAYER 2XX TO1XX
629	1	208	108	1.03177	L	TOP PCB LAYER 2XX TO1XX
630	1	209	109	.27512	L	TOP PCB LAYER 2XX TO1XX

```
CTRL-FlImport ITAS_NC     ALT-F3AutoMLI    UDC Allowed                PgDn PgUp Home
SHFT-FlImport Column    Shift-F3AutoCHT    Shift-F5Del/Pur                     End
       FlSave/Purge        F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark Fl0Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
631	1	210	110	1.10048	L	TOP PCB LAYER 2XX TO1XX
632	1	211	111	1.10048	L	TOP PCB LAYER 2XX TO1XX
633	1	212	112	1.51311	L	TOP PCB LAYER 2XX TO1XX
634	1	213	113	.27196	L	TOP PCB LAYER 2XX TO1XX
635	1	214	114	.21378	L	TOP PCB LAYER 2XX TO1XX
636	1	215	115	.21378	L	TOP PCB LAYER 2XX TO1XX
637	1	216	116	.21378	L	TOP PCB LAYER 2XX TO1XX
638	1	217	117	.21378	L	TOP PCB LAYER 2XX TO1XX
639	1	218	118	.27196	L	TOP PCB LAYER 2XX TO1XX
640	1	219	119	.35579	L	TOP PCB LAYER 2XX TO1XX
641	1	220	120	.27196	L	TOP PCB LAYER 2XX TO1XX
642	1	221	121	.27196	L	TOP PCB LAYER 2XX TO1XX
643	1	222	122	.27196	L	TOP PCB LAYER 2XX TO1XX
644	1	223	123	.27196	L	TOP PCB LAYER 2XX TO1XX
645	1	224	124	.35579	L	TOP PCB LAYER 2XX TO1XX
646	1	225	125	.29301	L	TOP PCB LAYER 2XX TO1XX
647	1	226	126	.23024	L	TOP PCB LAYER 2XX TO1XX
648	1	227	127	.23024	L	TOP PCB LAYER 2XX TO1XX

```
CTRL-FlImport ITAS_NC     ALT-F3AutoMLI    UDC Allowed                PgDn PgUp Home
SHFT-FlImport Column    Shift-F3AutoCHT    Shift-F5Del/Pur                     End
       FlSave/Purge        F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark Fl0Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
649	1	228	128	.23024	L	TOP PCB LAYER 2XX TO1XX
650	1	229	129	.23024	L	TOP PCB LAYER 2XX TO1XX
651	1	230	130	.29301	L	TOP PCB LAYER 2XX TO1XX
652	1	1601	1602	.0006276	L	BOTTOM PCB THERMAL LYR NODE-NODE
653	1	1601	1607	.0003138	L	
654	1	1601	1614	.0007322	L	
655	1	1602	1603	.0005983	L	
656	1	1602	1607	.0002613	L	
657	1	1603	1604	.0006597	L	
658	1	1603	1608	.0001342	L	
659	1	1604	1605	.0008874	L	
660	1	1604	1609	.0000524	L	
661	1	1604	1610	.0000444	L	
662	1	1604	1611	.0000560	L	
663	1	1605	1606	.000536	L	
664	1	1605	1612	.0000524	L	
665	1	1606	1617	.0004594	L	
666	1	1606	1613	.0002978	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
667	1	1607	1608	.0002992	L	BOTTOM PCB THERMAL LYR NODE-NODE
668	1	1607	1614	.0001861	L	
669	1	1608	1609	.0002780	L	
670	1	1608	1615	.0001340	L	
671	1	1609	1610	.0009901	L	
672	1	1609	1615	.0000524	L	
673	1	1610	1611	.0009178	L	
674	1	1610	1615	.0000444	L	
675	1	1611	1612	.000804	L	
676	1	1611	1615	.0000560	L	
677	1	1612	1613	.000268	L	
678	1	1612	1616	.0000596	L	
679	1	1613	1617	.0003829	L	
680	1	1613	1616	.0003752	L	
681	1	1614	1615	.000469	L	
682	1	1615	1616	.0003450	L	
683	1	1616	1617	.000469	L	
684	1	1501	1502	.009055	L	BOTTOM PCB BTM POLY LYR NODE-NODE

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
685	1	1501	1507	.004528	L	BOTTOM PCB BTM POLY LYR NODE-NODE
686	1	1501	1514	.010570	L	
687	1	1502	1503	.008631	L	
688	1	1502	1507	.002684	L	
689	1	1503	1504	.009516	L	
690	1	1503	1508	.001929	L	
691	1	1504	1505	.01280	L	
692	1	1504	1509	.000752	L	
693	1	1504	1510	.000644	L	
694	1	1504	1511	.000860	L	
695	1	1505	1506	.007733	L	
696	1	1505	1512	.000860	L	
697	1	1506	1517	.006629	L	
698	1	1506	1513	.004293	L	
699	1	1507	1508	.004315	L	
700	1	1507	1514	.002416	L	
701	1	1508	1509	.004033	L	
702	1	1508	1515	.00232	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
703	1	1509	1510	.01429	L	BOTTOM PCB BTM POLY LYR NODE-NODE
704	1	1509	1515	.000691	L	
705	1	1510	1511	.01324	L	
706	1	1510	1515	.00058	L	
707	1	1511	1512	.0116	L	
708	1	1511	1515	.000774	L	
709	1	1512	1513	.003867	L	
710	1	1512	1516	.000774	L	
711	1	1513	1517	.003314	L	
712	1	1513	1516	.003864	L	
713	1	1514	1515	.00677	L	
714	1	1515	1516	.004980	L	
715	1	1516	1517	.00677	L	
716	1	1401	1402	.000628	L	BOTTOM PCB GRND LYR NODE-NODE
717	1	1401	1407	.000314	L	
718	1	1401	1414	.000732	L	
719	1	1402	1403	.000598	L	
720	1	1402	1407	.000261	L	

135

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
721	1	1403	1404	.0006597	L	BOTTOM PCB GRND LYR NODE-NODE
722	1	1403	1408	.0001342	L	
723	1	1404	1405	.0008874	L	
724	1	1404	1409	.0000524	L	
725	1	1404	1410	.0000444	L	
726	1	1404	1411	.0000596	L	
727	1	1405	1406	.0005366	L	
728	1	1405	1412	.0000524	L	
729	1	1406	1417	.0004594	L	
730	1	1406	1413	.0002978	L	
731	1	1407	1408	.0002991	L	
732	1	1407	1414	.0001861	L	
733	1	1408	1409	.0002796	L	
734	1	1408	1415	.0001340	L	
735	1	1409	1410	.0009901	L	
736	1	1409	1415	.0000524	L	
737	1	1410	1411	.0009178	L	
738	1	1410	1415	.0000444	L	

CTRL-F1Import ITAS_NC   ALT-F3AutoMLI   UDC Allowed   PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT   Shift-F5Del/Pur   End
     F1Save/Purge   F2Help F3AutoGen F4Purge F5Delete F7Mark/UnMark F10Search

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
739	1	1411	1412	.000804	L	BOTTOM PCB GRND LYR NODE-NODE
740	1	1411	1415	.0000596	L	
741	1	1412	1413	.000268	L	
742	1	1412	1416	.0000596	L	
743	1	1413	1417	.0003829	L	
744	1	1413	1416	.0003752	L	
745	1	1414	1415	.000469	L	
746	1	1415	1416	.0003450	L	
747	1	1416	1417	.000469	L	
748	1	1301	1302	.009055	L	
749	1	1301	1307	.004528	L	BOTTOM PCB MID POLY LYR NODE-NODE
750	1	1301	1314	.01060	L	
751	1	1302	1303	.00863	L	
752	1	1302	1307	.002684	L	
753	1	1303	1304	.009516	L	
754	1	1303	1308	.001929	L	
755	1	1304	1305	.01280	L	
756	1	1304	1309	.000752	L	

CTRL-F1Import ITAS_NC   ALT-F3AutoMLI   UDC Allowed   PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT   Shift-F5Del/Pur   End
     F1Save/Purge   F2Help F3AutoGen F4Purge F5Delete F7Mark/UnMark F10Search

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
757	1	1304	1310	.000644	L	BOTTOM PCB MID POLY LYR NODE-NODE
758	1	1304	1311	.000860	L	
759	1	1305	1306	.007733	L	
760	1	1305	1312	.000860	L	
761	1	1306	1317	.006629	L	
762	1	1306	1313	.004293	L	
763	1	1307	1308	.004315	L	
764	1	1307	1314	.002416	L	
765	1	1308	1309	.004033	L	
766	1	1308	1315	.00232	L	
767	1	1309	1310	.01439	L	
768	1	1309	1315	.000691	L	
769	1	1310	1311	.01324	L	
770	1	1310	1315	.00058	L	
771	1	1311	1312	.0116	L	
772	1	1311	1315	.000774	L	
773	1	1312	1313	.003867	L	
774	1	1312	1316	.000774	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
775	1	1313	1317	.003314	L	BOTTOM PCB MID POLY LYR NODE-NODE
776	1	1313	1316	.003864	L	
777	1	1314	1315	.00677	L	
778	1	1315	1316	.004980	L	
779	1	1316	1317	.00677	L	
780	1	1201	1202	.0006276	L	BOTTOM PCB TOP Cu LYR NODE-NODE
781	1	1201	1207	.0003138	L	
782	1	1201	1214	.0007322	L	
783	1	1202	1203	.0005983	L	
784	1	1202	1207	.0002613	L	
785	1	1203	1204	.0006597	L	
786	1	1203	1208	.0001342	L	
787	1	1204	1205	.0008874	L	
788	1	1204	1209	.0000524	L	
789	1	1204	1210	.0000444	L	
790	1	1204	1211	.0000596	L	
791	1	1205	1206	.000536	L	
792	1	1205	1212	.0000524	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
793	1	1206	1217	.0004594	L	BOTTOM PCB TOP Cu LYR NODE-NODE
794	1	1206	1213	.0002978	L	
795	1	1207	1208	.0002992	L	
796	1	1207	1214	.0001861	L	
797	1	1208	1209	.0002796	L	
798	1	1208	1215	.0001340	L	
799	1	1209	1210	.0009901	L	
800	1	1209	1215	.0000524	L	
801	1	1210	1211	.0009178	L	
802	1	1210	1215	.0000444	L	
803	1	1211	1212	.000804	L	
804	1	1211	1215	.0000596	L	
805	1	1212	1213	.000268	L	
806	1	1212	1216	.0000596	L	
807	1	1213	1217	.0003829	L	
808	1	1213	1216	.0003752	L	
809	1	1214	1215	.000469	L	
810	1	1215	1216	.0003450	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
811	1	1216	1217	.000469	L	BOTTOM PCB TOP Cu LYR NODE-NODE
812	1	1101	1102	.009055	L	BOTTOM PCB TOP POLY LYR NODE-NODE
813	1	1101	1107	.004528	L	
814	1	1101	1114	.010570	L	
815	1	1102	1103	.008631	L	
816	1	1102	1107	.002684	L	
817	1	1103	1104	.009516	L	
818	1	1103	1108	.001929	L	
819	1	1104	1105	.012804	L	
820	1	1104	1109	.000752	L	
821	1	1104	1110	.000644	L	
822	1	1104	1111	.0008596	L	
823	1	1105	1106	.007733	L	
824	1	1105	1112	.0008596	L	
825	1	1106	1117	.006629	L	
826	1	1106	1113	.004293	L	
827	1	1107	1108	.004315	L	
828	1	1107	1114	.002416	L	

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
829	1	1108	1109	.004033	L	BOTTOM PCB TOP POLY LYR NODE-NODE
830	1	1108	1115	.00232	L	
831	1	1109	1110	.01429	L	
832	1	1109	1115	.000691	L	
833	1	1110	1111	.013242	L	
834	1	1110	1115	.00058	L	
835	1	1111	1112	.0116	L	
836	1	1111	1115	.000774	L	
837	1	1112	1113	.003867	L	
838	1	1112	1116	.000774	L	
839	1	1113	1117	.003314	L	
840	1	1113	1116	.003864	L	
841	1	1114	1115	.00677	L	
842	1	1115	1116	.004980	L	
843	1	1116	1117	.00677	L	
844	1	1601	1501	1.53206	L	BOTTOM PCB LAYER 16XX TO 15XX
845	1	1602	1502	.89779	L	BOTTOM PCB LAYER 16XX TO 15XX
846	1	1603	1503	.64634	L	BOTTOM PCB LAYER 16XX TO 15XX

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
847	1	1604	1504	.75416	L	BOTTOM PCB LAYER 16XX TO 15XX
848	1	1605	1505	.28726	L	BOTTOM PCB LAYER 16XX TO 15XX
849	1	1606	1506	1.43631	L	BOTTOM PCB LAYER 16XX TO 15XX
850	1	1607	1507	.44889	L	BOTTOM PCB LAYER 16XX TO 15XX
851	1	1608	1508	.323276	L	BOTTOM PCB LAYER 16XX TO 15XX
852	1	1609	1509	.12517	L	BOTTOM PCB LAYER 16XX TO 15XX
853	1	1610	1510	.10763	L	BOTTOM PCB LAYER 16XX TO 15XX
854	1	1611	1511	.14363	L	BOTTOM PCB LAYER 16XX TO 15XX
855	1	1612	1512	.14363	L	BOTTOM PCB LAYER 16XX TO 15XX
856	1	1613	1513	.71815	L	BOTTOM PCB LAYER 16XX TO 15XX
857	1	1614	1514	1.04774	L	BOTTOM PCB LAYER 16XX TO 15XX
858	1	1615	1515	1.63375	L	BOTTOM PCB LAYER 16XX TO 15XX
859	1	1616	1516	2.0108	L	BOTTOM PCB LAYER 16XX TO 15XX
860	1	1617	1517	1.53206	L	BOTTOM PCB LAYER 16XX TO 15XX
861	1	1501	1401	1.53206	L	BOTTOM PCB LAYER 15XX TO 14XX
862	1	1502	1402	.89779	L	BOTTOM PCB LAYER 15XX TO 14XX
863	1	1503	1403	.64634	L	BOTTOM PCB LAYER 15XX TO 14XX
864	1	1504	1404	.75416	L	BOTTOM PCB LAYER 15XX TO 14XX

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
865	1	1505	1405	.28726	L	BOTTOM PCB LAYER 15XX TO 14XX
866	1	1506	1406	1.43631	L	BOTTOM PCB LAYER 15XX TO 14XX
867	1	1507	1407	.44889	L	BOTTOM PCB LAYER 15XX TO 14XX
868	1	1508	1408	.32327	L	BOTTOM PCB LAYER 15XX TO 14XX
869	1	1509	1409	.12517	L	BOTTOM PCB LAYER 15XX TO 14XX
870	1	1510	1410	.10763	L	BOTTOM PCB LAYER 15XX TO 14XX
871	1	1511	1411	.14363	L	BOTTOM PCB LAYER 15XX TO 14XX
872	1	1512	1412	.14363	L	BOTTOM PCB LAYER 15XX TO 14XX
873	1	1513	1413	.71815	L	BOTTOM PCB LAYER 15XX TO 14XX
874	1	1514	1414	1.04774	L	BOTTOM PCB LAYER 15XX TO 14XX
875	1	1515	1415	1.63375	L	BOTTOM PCB LAYER 15XX TO 14XX
876	1	1516	1416	2.01083	L	BOTTOM PCB LAYER 15XX TO 14XX
877	1	1517	1417	1.53206	L	BOTTOM PCB LAYER 15XX TO 14XX
878	1	1401	1301	1.53206	L	BOTTOM PCB LAYER 14XX TO13XX
879	1	1402	1302	.89779	L	BOTTOM PCB LAYER 14XX TO13XX
880	1	1403	1303	.64634	L	BOTTOM PCB LAYER 14XX TO13XX
881	1	1404	1304	.75416	L	BOTTOM PCB LAYER 14XX TO13XX
882	1	1405	1305	.28726	L	BOTTOM PCB LAYER 14XX TO13XX

```
CTRL-F1Import ITAS_NC    ALT-F3AutoMLI    UDC Allowed                PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT    Shift-F5Del/Pur                      End
        F1Save/Purge        F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
883	1	1406	1306	1.43631	L	BOTTOM PCB LAYER 14XX TO13XX
884	1	1407	1307	.44889	L	BOTTOM PCB LAYER 14XX TO13XX
885	1	1408	1308	.32327	L	BOTTOM PCB LAYER 14XX TO13XX
886	1	1409	1309	.12517	L	BOTTOM PCB LAYER 14XX TO13XX
887	1	1410	1310	.10763	L	BOTTOM PCB LAYER 14XX TO13XX
888	1	1411	1311	.14363	L	BOTTOM PCB LAYER 14XX TO13XX
889	1	1412	1312	.14363	L	BOTTOM PCB LAYER 14XX TO13XX
890	1	1413	1313	.71815	L	BOTTOM PCB LAYER 14XX TO13XX
891	1	1414	1314	1.04774	L	BOTTOM PCB LAYER 14XX TO13XX
892	1	1415	1315	1.63375	L	BOTTOM PCB LAYER 14XX TO13XX
893	1	1416	1316	2.01083	L	BOTTOM PCB LAYER 14XX TO13XX
894	1	1417	1317	1.53206	L	BOTTOM PCB LAYER 14XX TO13XX
895	1	1301	1201	1.53206	L	BOTTOM PCB LAYER 13XX TO 12XX
896	1	1302	1202	.89779	L	BOTTOM PCB LAYER 13XX TO 12XX
897	1	1303	1203	.64634	L	BOTTOM PCB LAYER 13XX TO 12XX
898	1	1304	1204	.75416	L	BOTTOM PCB LAYER 13XX TO 12XX
899	1	1305	1205	.28726	L	BOTTOM PCB LAYER 13XX TO 12XX
900	1	1306	1206	1.43631	L	BOTTOM PCB LAYER 13XX TO 12XX

```
CTRL-F1Import ITAS_NC    ALT-F3AutoMLI    UDC Allowed                PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT    Shift-F5Del/Pur                      End
        F1Save/Purge        F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
901	1	1307	1207	.44889	L	BOTTOM PCB LAYER 13XX TO 12XX
902	1	1308	1208	.32327	L	BOTTOM PCB LAYER 13XX TO 12XX
903	1	1309	1209	.12517	L	BOTTOM PCB LAYER 13XX TO 12XX
904	1	1310	1210	.10763	L	BOTTOM PCB LAYER 13XX TO 12XX
905	1	1311	1211	.14363	L	BOTTOM PCB LAYER 13XX TO 12XX
906	1	1312	1212	.14363	L	BOTTOM PCB LAYER 13XX TO 12XX
907	1	1313	1213	.71815	L	BOTTOM PCB LAYER 13XX TO 12XX
908	1	1314	1214	1.04774	L	BOTTOM PCB LAYER 13XX TO 12XX
909	1	1315	1215	1.63375	L	BOTTOM PCB LAYER 13XX TO 12XX
910	1	1316	1216	2.01083	L	BOTTOM PCB LAYER 13XX TO 12XX
911	1	1317	1217	1.53206	L	BOTTOM PCB LAYER 13XX TO 12XX
912	1	1201	1101	1.53206	L	BOTTOM PCB LAYER 12XX TO11XX
913	1	1202	1102	.89779	L	BOTTOM PCB LAYER 12XX TO11XX
914	1	1203	1103	.64634	L	BOTTOM PCB LAYER 12XX TO11XX
915	1	1204	1104	.75416	L	BOTTOM PCB LAYER 12XX TO11XX
916	1	1205	1105	.28726	L	BOTTOM PCB LAYER 12XX TO11XX
917	1	1206	1106	1.43631	L	BOTTOM PCB LAYER 12XX TO11XX
918	1	1207	1107	.44889	L	BOTTOM PCB LAYER 12XX TO11XX

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
919	1	1208	1108	.32327	L	BOTTOM PCB LAYER 12XX TO11XX
920	1	1209	1109	.12517	L	BOTTOM PCB LAYER 12XX TO11XX
921	1	1210	1110	.10763	L	BOTTOM PCB LAYER 12XX TO11XX
922	1	1211	1111	.14363	L	BOTTOM PCB LAYER 12XX TO11XX
923	1	1212	1112	.14363	L	BOTTOM PCB LAYER 12XX TO11XX
924	1	1213	1113	.71815	L	BOTTOM PCB LAYER 12XX TO11XX
925	1	1214	1114	1.04774	L	BOTTOM PCB LAYER 12XX TO11XX
926	1	1215	1115	1.63375	L	BOTTOM PCB LAYER 12XX TO11XX
927	1	1216	1116	2.01083	L	BOTTOM PCB LAYER 12XX TO11XX
928	1	1217	1117	1.53206	L	BOTTOM PCB LAYER 12XX TO11XX
929	1	2011	101	.000296	L	EQUIV PIN CONDUCTANCE 3.01
930	1	2012	201	.000197	L	EQUIV PIN CONDUCTANCE 3.01
931	1	2013	301	.000296	L	EQUIV PIN CONDUCTANCE 3.01
932	1	2014	401	.000176	L	EQUIV PIN CONDUCTANCE 3.01
933	1	2015	501	.000296	L	EQUIV PIN CONDUCTANCE 3.01
934	1	2016	601	.000197	L	EQUIV PIN CONDUCTANCE 3.01
935	1	2021	102	.000296	L	EQUIV CONDUCTANCE FOR 3.02
936	1	2022	202	.000197	L	EQUIV CONDUCTANCE FOR 3.02

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
937	1	2023	302	.000296	L	EQUIV CONDUCTANCE FOR 3.02
938	1	2024	402	.000197	L	EQUIV CONDUCTANCE FOR 3.02
939	1	2025	502	.000296	L	EQUIV CONDUCTANCE FOR 3.02
940	1	2026	602	.000197	L	EQUIV CONDUCTANCE FOR 3.02
941	1	2031	103	.000296	L	EQUIV COND FOR 3.03
942	1	2032	203	.000197	L	EQUIV COND FOR 3.03
943	1	2033	303	.000296	L	EQUIV COND FOR 3.03
944	1	2034	403	.000197	L	EQUIV COND FOR 3.03
945	1	2035	503	.000296	L	EQUIV COND FOR 3.03
946	1	2036	603	.000197	L	EQUIV COND FOR 3.03
947	1	2041	104	.000296	L	EQUIV PIN COND FOR 3.04
948	1	2042	204	.000198	L	EQUIV PIN COND FOR 3.04
949	1	2043	304	.000296	L	EQUIV PIN COND FOR 3.04
950	1	2044	404	.000198	L	EQUIV PIN COND FOR 3.04
951	1	2045	504	.000296	L	EQUIV PIN COND FOR 3.04
952	1	2046	604	.000198	L	EQUIV PIN COND FOR 3.04
953	1	2051	105	.000296	L	EQUIV PIN COND FOR 3.05
954	1	2052	205	.000197	L	EQUIV PIN COND FOR 3.05

```
CTRL-FlImport ITAS_NC    ALT-F3AutoMLI   UDC Allowed              PgDn PgUp Home
SHFT-FlImport Column   Shift-F3AutoCHT   Shift-F5Del/Pur                    End
        FlSave/Purge      F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
955	1	2053	305	.000296	L	EQUIV PIN COND FOR 3.05
956	1	2054	405	.000197	L	EQUIV PIN COND FOR 3.05
957	1	2055	505	.000296	L	EQUIV PIN COND FOR 3.05
958	1	2056	605	.000197	L	EQUIV PIN COND FOR 3.05
959	1	2061	106	.000296	L	EQUIV PIN COND FOR 3.06
960	1	2062	206	.000198	L	EQUIV PIN COND FOR 3.06
961	1	2063	306	.000296	L	EQUIV PIN COND FOR 3.06
962	1	2064	406	.000198	L	EQUIV PIN COND FOR 3.06
963	1	2065	506	.000296	L	EQUIV PIN COND FOR 3.06
964	1	2066	606	.000198	L	EQUIV PIN COND FOR 3.06
965	1	2071	107	.000296	L	EQUIV PIN COND FOR 3.07
966	1	2072	207	.000197	L	EQUIV PIN COND FOR 3.07
967	1	2073	307	.000296	L	EQUIV PIN COND FOR 3.07
968	1	2074	407	.000197	L	EQUIV PIN COND FOR 3.07
969	1	2075	507	.000296	L	EQUIV PIN COND FOR 3.07
970	1	2076	607	.000197	L	EQUIV PIN COND FOR 3.07
971	1	2081	108	.000296	L	EQUIV PIN COND FOR 3.08
972	1	2082	208	.000197	L	EQUIV PIN COND FOR 3.08

```
CTRL-FlImport ITAS_NC    ALT-F3AutoMLI   UDC Allowed              PgDn PgUp Home
SHFT-FlImport Column   Shift-F3AutoCHT   Shift-F5Del/Pur                    End
        FlSave/Purge      F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
973	1	2083	308	.000296	L	EQUIV PIN COND FOR 3.08
974	1	2084	408	.000197	L	EQUIV PIN COND FOR 3.08
975	1	2085	508	.000296	L	EQUIV PIN COND FOR 3.08
976	1	2086	608	.000197	L	EQUIV PIN COND FOR 3.08
977	1	2091	109	.000296	L	EQUIV PIN COND FOR 3.09
978	1	2092	110	.000197	L	EQUIV PIN COND FOR 3.09
979	1	2093	111	.000296	L	EQUIV PIN COND FOR 3.09
980	1	2094	112	.000197	L	EQUIV PIN COND FOR 3.09
981	1	2095	113	.000296	L	EQUIV PIN COND FOR 3.09
982	1	2096	114	.000197	L	EQUIV PIN COND FOR 3.09
983	1	2101	110	.000296	L	EQUIV PIN COND FOR 3.10
984	1	2102	210	.000197	L	EQUIV PIN COND FOR 3.10
985	1	2103	310	.000296	L	EQUIV PIN COND FOR 3.10
986	1	2104	410	.000197	L	EQUIV PIN COND FOR 3.10
987	1	2105	510	.000296	L	EQUIV PIN COND FOR 3.10
988	1	2106	610	.000197	L	EQUIV PIN COND FOR 3.10
989	1	2111	111	.000296	L	EQUIV PIN COND FOR 3.11
990	1	2112	211	.000197	L	EQUIV PIN COND FOR 3.11

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
991	1	2113	311	.000296	L	EQUIV PIN COND FOR 3.11
992	1	2114	411	.000197	L	EQUIV PIN COND FOR 3.11
993	1	2115	511	.000296	L	EQUIV PIN COND FOR 3.11
994	1	2116	611	.000197	L	EQUIV PIN COND FOR 3.11
995	1	2121	112	.000296	L	EQUIV PIN COND FOR 3.12
996	1	2122	212	.000197	L	EQUIV PIN COND FOR 3.12
997	1	2123	312	.000296	L	EQUIV PIN COND FOR 3.12
998	1	2124	412	.000197	L	EQUIV PIN COND FOR 3.12
999	1	2125	512	.000296	L	EQUIV PIN COND FOR 3.12
1000	1	2126	612	.000197	L	EQUIV PIN COND FOR 3.12
1001	1	2131	113	.000296	L	EQUIV PIN COND FOR 2.01
1002	1	2132	213	.000197	L	EQUIV PIN COND FOR 2.01
1003	1	2133	313	.000296	L	EQUIV PIN COND FOR 2.01
1004	1	2134	413	.000197	L	EQUIV PIN COND FOR 2.01
1005	1	2135	513	.000296	L	EQUIV PIN COND FOR 2.01
1006	1	2136	613	.000197	L	EQUIV PIN COND FOR 2.01
1007	1	2141	114	.000296	L	EQUIV PIN COND FOR 2.02
1008	1	2142	214	.000197	L	EQUIV PIN COND FOR 2.02

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1009	1	2143	314	.000296	L	EQUIV PIN COND FOR 2.02
1010	1	2144	414	.000197	L	EQUIV PIN COND FOR 2.02
1011	1	2145	514	.000296	L	EQUIV PIN COND FOR 2.02
1012	1	2146	614	.000197	L	EQUIV PIN COND FOR 2.02
1013	1	2151	115	.000296	L	EQUIV PIN COND FOR 2.03
1014	1	2152	215	.000197	L	EQUIV PIN COND FOR 2.03
1015	1	2153	315	.000296	L	EQUIV PIN COND FOR 2.03
1016	1	2154	415	.000197	L	EQUIV PIN COND FOR 2.03
1017	1	2155	515	.000296	L	EQUIV PIN COND FOR 2.03
1018	1	2156	615	.000197	L	EQUIV PIN COND FOR 2.03
1019	1	2161	116	.000296	L	EQUIV PIN COND FOR 2.04
1020	1	2162	216	.000197	L	EQUIV PIN COND FOR 2.04
1021	1	2163	316	.000296	L	EQUIV PIN COND FOR 2.04
1022	1	2164	416	.000197	L	EQUIV PIN COND FOR 2.04
1023	1	2165	516	.000296	L	EQUIV PIN COND FOR 2.04
1024	1	2166	616	.000197	L	EQUIV PIN COND FOR 2.04
1025	1	2171	117	.000296	L	EQUIV PIN COND FOR 2.05
1026	1	2172	217	.000197	L	EQUIV PIN COND FOR 2.05

CTRL-F1Import ITAS_NC   ALT-F3AutoMLI   UDC Allowed   PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT   Shift-F5Del/Pur   End
        F1Save/Purge   F2Help F3AutoGen F4Purge F5Delete   F7Mark/UnMark F10Search

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1027	1	2173	317	.000296	L	EQUIV PIN COND FOR 2.05
1028	1	2174	417	.000197	L	EQUIV PIN COND FOR 2.05
1029	1	2175	517	.000296	L	EQUIV PIN COND FOR 2.05
1030	1	2176	617	.000197	L	EQUIV PIN COND FOR 2.05
1031	1	2181	118	.000296	L	EQUIV PIN COND FOR 2.06
1032	1	2182	218	.000197	L	EQUIV PIN COND FOR 2.06
1033	1	2183	318	.000296	L	EQUIV PIN COND FOR 2.06
1034	1	2184	418	.000197	L	EQUIV PIN COND FOR 2.06
1035	1	2185	518	.000296	L	EQUIV PIN COND FOR 2.06
1036	1	2186	618	.000197	L	EQUIV PIN COND FOR 2.06
1037	1	2191	119	.000296	L	EQUIV PIN COND FOR 2.07
1038	1	2192	219	.000197	L	EQUIV PIN COND FOR 2.07
1039	1	2193	319	.000296	L	EQUIV PIN COND FOR 2.07
1040	1	2194	419	.000197	L	EQUIV PIN COND FOR 2.07
1041	1	2195	519	.000296	L	EQUIV PIN COND FOR 2.07
1042	1	2196	619	.000197	L	EQUIV PIN COND FOR 2.07
1043	1	2201	120	.000296	L	EQUIV PIN COND FOR 2.08
1044	1	2202	220	.000197	L	EQUIV PIN COND FOR 2.08

CTRL-F1Import ITAS_NC   ALT-F3AutoMLI   UDC Allowed   PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT   Shift-F5Del/Pur   End
        F1Save/Purge   F2Help F3AutoGen F4Purge F5Delete   F7Mark/UnMark F10Search

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1045	1	2203	320	.000296	L	EQUIV PIN COND FOR 2.08
1046	1	2204	420	.000197	L	EQUIV PIN COND FOR 2.08
1047	1	2205	520	.000296	L	EQUIV PIN COND FOR 2.08
1048	1	2206	620	.000197	L	EQUIV PIN COND FOR 2.08
1049	1	2211	121	.000296	L	EQUIV PIN COND FOR 2.09
1050	1	2212	221	.000197	L	EQUIV PIN COND FOR 2.09
1051	1	2213	321	.000296	L	EQUIV PIN COND FOR 2.09
1052	1	2214	421	.000197	L	EQUIV PIN COND FOR 2.09
1053	1	2215	521	.000296	L	EQUIV PIN COND FOR 2.09
1054	1	2216	621	.000197	L	EQUIV PIN COND FOR 2.09
1055	1	2221	122	.000296	L	EQUIV PIN COND FOR 2.10
1056	1	2222	222	.000197	L	EQUIV PIN COND FOR 2.10
1057	1	2223	322	.000296	L	EQUIV PIN COND FOR 2.10
1058	1	2224	422	.000197	L	EQUIV PIN COND FOR 2.10
1059	1	2225	522	.000296	L	EQUIV PIN COND FOR 2.10
1060	1	2226	622	.000197	L	EQUIV PIN COND FOR 2.10
1061	1	2231	123	.000296	L	EQUIV PIN COND FOR 2.11
1062	1	2232	223	.000197	L	EQUIV PIN COND FOR 2.11

CTRL-F1Import ITAS_NC   ALT-F3AutoMLI   UDC Allowed   PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT   Shift-F5Del/Pur   End
        F1Save/Purge   F2Help F3AutoGen F4Purge F5Delete   F7Mark/UnMark F10Search

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1063	1	2233	323	.000296	L	EQUIV PIN COND FOR 2.11
1064	1	2234	423	.000197	L	EQUIV PIN COND FOR 2.11
1065	1	2235	523	.000296	L	EQUIV PIN COND FOR 2.11
1066	1	2236	623	.000197	L	EQUIV PIN COND FOR 2.11
1067	1	2241	124	.000296	L	EQUIV PIN COND FOR 2.12
1068	1	2242	224	.000197	L	EQUIV PIN COND FOR 2.12
1069	1	2243	324	.000296	L	EQUIV PIN COND FOR 2.12
1070	1	2244	424	.000197	L	EQUIV PIN COND FOR 2.12
1071	1	2245	524	.000296	L	EQUIV PIN COND FOR 2.12
1072	1	2246	624	.000197	L	EQUIV PIN COND FOR 2.12
1073	1	2251	125	.000296	L	EQUIV PIN COND FOR 2.13
1074	1	2252	225	.000197	L	EQUIV PIN COND FOR 2.13
1075	1	2253	325	.000296	L	EQUIV PIN COND FOR 2.13
1076	1	2254	425	.000197	L	EQUIV PIN COND FOR 2.13
1077	1	2255	525	.000296	L	EQUIV PIN COND FOR 2.13
1078	1	2256	625	.000197	L	EQUIV PIN COND FOR 2.13
1079	1	2261	126	.000296	L	EQUIV PIN COND FOR 2.14
1080	1	2262	226	.000197	L	EQUIV PIN COND FOR 2.14

CTRL-F1Import ITAS_NC   ALT-F3AutoMLI   UDC Allowed   PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT   Shift-F5Del/Pur   End
        F1Save/Purge   F2Help F3AutoGen F4Purge F5Delete   F7Mark/UnMark F10Search

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1081	1	2263	326	.000296	L	EQUIV PIN COND FOR 2.14
1082	1	2264	426	.000197	L	EQUIV PIN COND FOR 2.14
1083	1	2265	526	.000296	L	EQUIV PIN COND FOR 2.14
1084	1	2266	626	.000197	L	EQUIV PIN COND FOR 2.14
1085	1	2271	127	.000296	L	EQUIV PIN COND FOR 2.15
1086	1	2272	227	.000197	L	EQUIV PIN COND FOR 2.15
1087	1	2273	327	.000296	L	EQUIV PIN COND FOR 2.15
1088	1	2274	427	.000197	L	EQUIV PIN COND FOR 2.15
1089	1	2275	527	.000296	L	EQUIV PIN COND FOR 2.15
1090	1	2276	627	.000197	L	EQUIV PIN COND FOR 2.15
1091	1	2281	128	.000296	L	EQUIV PIN COND FOR 2.16
1092	1	2282	228	.000197	L	EQUIV PIN COND FOR 2.16
1093	1	2283	328	.000296	L	EQUIV PIN COND FOR 2.16
1094	1	2284	428	.000197	L	EQUIV PIN COND FOR 2.16
1095	1	2285	528	.000296	L	EQUIV PIN COND FOR 2.16
1096	1	2286	628	.000197	L	EQUIV PIN COND FOR 2.16
1097	1	2291	129	.000296	L	EQUIV PIN COND FOR 2.17
1098	1	2292	229	.000197	L	EQUIV PIN COND FOR 2.17

CTRL-F1Import ITAS_NC   ALT-F3AutoMLI   UDC Allowed   PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT   Shift-F5Del/Pur   End
       F1Save/Purge   F2Help F3AutoGen F4Purge F5Delete F7Mark/UnMark F10Search

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1099	1	2293	329	.000296	L	EQUIV PIN COND FOR 2.17
1100	1	2294	429	.000197	L	EQUIV PIN COND FOR 2.17
1101	1	2295	529	.000296	L	EQUIV PIN COND FOR 2.17
1102	1	2296	629	.000197	L	EQUIV PIN COND FOR 2.17
1103	1	2301	130	.000296	L	EQUIV PIN COND FOR 2.18
1104	1	2302	230	.000197	L	EQUIV PIN COND FOR 2.18
1105	1	2303	330	.000296	L	EQUIV PIN COND FOR 2.18
1106	1	2304	430	.000197	L	EQUIV PIN COND FOR 2.18
1107	1	2305	530	.000296	L	EQUIV PIN COND FOR 2.18
1108	1	2306	630	.000197	L	EQUIV PIN COND FOR 2.18
1109	1	3011	1101	.000296	L	EQUIV PIN COND FOR 4.00
1110	1	3012	1201	.000197	L	EQUIV PIN COND FOR 4.00
1111	1	3013	1301	.000296	L	EQUIV PIN COND FOR 4.00
1112	1	3014	1401	.000197	L	EQUIV PIN COND FOR 4.00
1113	1	3015	1501	.000296	L	EQUIV PIN COND FOR 4.00
1114	1	3016	1601	.000197	L	EQUIV PIN COND FOR 4.00
1115	1	3021	1102	.000296	L	EQUIV PIN COND FOR 5.01
1116	1	3022	1202	.000197	L	EQUIV PIN COND FOR 5.01

CTRL-F1Import ITAS_NC   ALT-F3AutoMLI   UDC Allowed   PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT   Shift-F5Del/Pur   End
       F1Save/Purge   F2Help F3AutoGen F4Purge F5Delete F7Mark/UnMark F10Search

SqNo	FACTOR	From	To	Cond. value	L/R	Description
1117	1	3023	1302	.000296	L	EQUIV PIN COND FOR 5.01
1118	1	3024	1402	.000197	L	EQUIV PIN COND FOR 5.01
1119	1	3025	1502	.000296	L	EQUIV PIN COND FOR 5.01
1120	1	3026	1602	.000197	L	EQUIV PIN COND FOR 5.01
1121	1	3031	1103	.000296	L	EQUIV PIN COND FOR 5.02
1122	1	3032	1203	.000197	L	EQUIV PIN COND FOR 5.02
1123	1	3033	1303	.000296	L	EQUIV PIN COND FOR 5.02
1124	1	3034	1403	.000197	L	EQUIV PIN COND FOR 5.02
1125	1	3035	1503	.000296	L	EQUIV PIN COND FOR 5.02
1126	1	3036	1603	.000197	L	EQUIV PIN COND FOR 5.02
1127	1	3041	1104	.000296	L	EQUIV PIN COND FOR 5.03
1128	1	3042	1204	.000197	L	EQUIV PIN COND FOR 5.03
1129	1	3043	1304	.000296	L	EQUIV PIN COND FOR 5.03
1130	1	3044	1404	.000197	L	EQUIV PIN COND FOR 5.03
1131	1	3045	1504	.000296	L	EQUIV PIN COND FOR 5.03
1132	1	3046	1604	.000197	L	EQUIV PIN COND FOR 5.03
1133	1	3051	1105	.000296	L	EQUIV PIN COND FOR 5.04
1134	1	3052	1205	.000197	L	EQUIV PIN COND FOR 5.04

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1135	1	3053	1305	.000296	L	EQUIV PIN COND FOR 5.04
1136	1	3054	1405	.000197	L	EQUIV PIN COND FOR 5.04
1137	1	3055	1505	.000296	L	EQUIV PIN COND FOR 5.04
1138	1	3056	1605	.000197	L	EQUIV PIN COND FOR 5.04
1139	1	3061	1106	.000296	L	EQUIV PIN COND FOR 5.05
1140	1	3062	1206	.000197	L	EQUIV PIN COND FOR 5.05
1141	1	3063	1306	.000296	L	EQUIV PIN COND FOR 5.05
1142	1	3064	1406	.000197	L	EQUIV PIN COND FOR 5.05
1143	1	3065	1506	.000296	L	EQUIV PIN COND FOR 5.05
1144	1	3066	1606	.000197	L	EQUIV PIN COND FOR 5.05
1145	1	3091	1109	.000296	L	EQUIV PIN COND FOR 6.03
1146	1	3092	1209	.000197	L	EQUIV PIN COND FOR 6.03
1147	1	3093	1309	.000296	L	EQUIV PIN COND FOR 6.03
1148	1	3094	1409	.000197	L	EQUIV PIN COND FOR 6.03
1149	1	3095	1509	.000296	L	EQUIV PIN COND FOR 6.03
1150	1	3096	1609	.000197	L	EQUIV PIN COND FOR 6.03
1151	1	3101	1110	.000296	L	EQUIV PIN COND FOR 6.04
1152	1	3102	1210	.000197	L	EQUIV PIN COND FOR 6.04

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1153	1	3103	1310	.000296	L	EQUIV PIN COND FOR 6.04
1154	1	3104	1410	.000197	L	EQUIV PIN COND FOR 6.04
1155	1	3105	1510	.000296	L	EQUIV PIN COND FOR 6.04
1156	1	3106	1610	.000197	L	EQUIV PIN COND FOR 6.04
1157	1	3111	1111	.000296	L	EQUIV PIN COND FOR 6.05
1158	1	3112	1211	.000197	L	EQUIV PIN COND FOR 6.05
1159	1	3113	1311	.000296	L	EQUIV PIN COND FOR 6.05
1160	1	3114	1411	.000197	L	EQUIV PIN COND FOR 6.05
1161	1	3115	1511	.000296	L	EQUIV PIN COND FOR 6.05
1162	1	3116	1611	.000197	L	EQUIV PIN COND FOR 6.05
1163	1	3121	1112	.000296	L	EQUIV PIN COND FOR 6.06
1164	1	3122	1212	.000197	L	EQUIV PIN COND FOR 6.06
1165	1	3123	1312	.000296	L	EQUIV PIN COND FOR 6.06
1166	1	3124	1412	.000197	L	EQUIV PIN COND FOR 6.06
1167	1	3125	1512	.000296	L	EQUIV PIN COND FOR 6.06
1168	1	3126	1612	.000197	L	EQUIV PIN COND FOR 6.06
1169	1	3141	1114	.000296	L	EQUIV PIN COND FOR 7.01
1170	1	3142	1214	.000197	L	EQUIV PIN COND FOR 7.01

```
CTRL-F1Import ITAS_NC    ALT-F3AutoMLI    UDC Allowed              PgDn PgUp Home
SHFT-F1Import Column  Shift-F3AutoCHT    Shift-F5Del/Pur                    End
    F1Save/Purge      F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1171	1	3143	1314	.000197	L	EQUIV PIN COND FOR 7.01
1172	1	3144	1414	.000296	L	EQUIV PIN COND FOR 7.01
1173	1	3145	1514	.000197	L	EQUIV PIN COND FOR 7.01
1174	1	3146	1614	.000296	L	EQUIV PIN COND FOR 7.01
1175	1	3151	1115	.000197	L	EQUIV PIN COND FOR 7.02
1176	1	3152	1215	.000296	L	EQUIV PIN COND FOR 7.02
1177	1	3153	1315	.000197	L	EQUIV PIN COND FOR 7.02
1178	1	3154	1415	.000296	L	EQUIV PIN COND FOR 7.02
1179	1	3155	1515	.000197	L	EQUIV PIN COND FOR 7.02
1180	1	3156	1615	.000296	L	EQUIV PIN COND FOR 7.02
1181	1	3161	1116	.000197	L	EQUIV PIN COND FOR 7.03
1182	1	3162	1216	.000296	L	EQUIV PIN COND FOR 7.03
1183	1	3163	1316	.000197	L	EQUIV PIN COND FOR 7.03
1184	1	3164	1416	.000296	L	EQUIV PIN COND FOR 7.03
1185	1	3165	1516	.000197	L	EQUIV PIN COND FOR 7.03
1186	1	3166	1616	.000296	L	EQUIV PIN COND FOR 7.03
1187	1	3171	1117	.000197	L	EQUIV PIN COND FOR 8.00
1188	1	3172	1217	.000296	L	EQUIV PIN COND FOR 8.00

```
CTRL-F1Import ITAS_NC    ALT-F3AutoMLI    UDC Allowed              PgDn PgUp Home
SHFT-F1Import Column  Shift-F3AutoCHT    Shift-F5Del/Pur                    End
    F1Save/Purge      F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1189	1	3173	1317	.000296	L	EQUIV PIN COND FOR 8.00
1190	1	3174	1417	.000197	L	EQUIV PIN COND FOR 8.00
1191	1	3175	1517	.000296	L	EQUIV PIN COND FOR 8.00
1192	1	3176	1617	.000197	L	EQUIV PIN COND FOR 8.00
1193	1	2011	2012	.1465	L	PIN COND
1194	1	2012	2013	.1465	L	PIN COND
1195	1	2013	2014	.1465	L	PIN COND
1196	1	2014	2015	.1465	L	PIN COND
1197	1	2015	2016	.1465	L	PIN COND
1198	1	2021	2022	.1465	L	PIN COND
1199	1	2022	2023	.1465	L	PIN COND
1200	1	2023	2024	.1465	L	PIN COND
1201	1	2024	2025	.1465	L	PIN COND
1202	1	2025	2026	.1465	L	PIN COND
1203	1	2031	2032	.1465	L	PIN COND
1204	1	2032	2033	.1465	L	PIN COND
1205	1	2033	2034	.1465	L	PIN COND
1206	1	2034	2035	.1465	L	PIN COND

```
CTRL-F1Import ITAS_NC    ALT-F3AutoMLI    UDC Allowed              PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT    Shift-F5Del/Pur                   End
       F1Save/Purge        F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1207	1	2035	2036	.1465	L	PIN COND
1208	1	2041	2042	.1465	L	PIN COND
1209	1	2042	2043	.1465	L	PIN COND
1210	1	2043	2044	.1465	L	PIN COND
1211	1	2044	2045	.1465	L	PIN COND
1212	1	2045	2046	.1465	L	PIN COND
1213	1	2051	2052	.1465	L	PIN COND
1214	1	2052	2053	.1465	L	PIN COND
1215	1	2053	2054	.1465	L	PIN COND
1216	1	2054	2055	.1465	L	PIN COND
1217	1	2055	2056	.1465	L	PIN COND
1218	1	2061	2062	.1465	L	PIN COND
1219	1	2062	2063	.1465	L	PIN COND
1220	1	2063	2064	.1465	L	PIN COND
1221	1	2064	2065	.1465	L	PIN COND
1222	1	2065	2066	.1465	L	PIN COND
1223	1	2071	2072	.1465	L	PIN COND
1224	1	2072	2073	.1465	L	PIN COND

```
CTRL-F1Import ITAS_NC    ALT-F3AutoMLI    UDC Allowed              PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT    Shift-F5Del/Pur                   End
       F1Save/Purge        F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1225	1	2073	2074	.1465	L	PIN COND
1226	1	2074	2075	.1465	L	PIN COND
1227	1	2075	2076	.1465	L	PIN COND
1228	1	2081	2082	.1465	L	PIN COND
1229	1	2082	2083	.1465	L	PIN COND
1230	1	2083	2084	.1465	L	PIN COND
1231	1	2084	2085	.1465	L	PIN COND
1232	1	2085	2086	.1465	L	PIN COND
1233	1	2091	2092	.1465	L	PIN COND
1234	1	2092	2093	.1465	L	PIN COND
1235	1	2093	2094	.1465	L	PIN COND
1236	1	2094	2095	.1465	L	PIN COND
1237	1	2095	2096	.1465	L	PIN COND
1238	1	2101	2102	.1465	L	PIN COND
1239	1	2102	2103	.1465	L	PIN COND
1240	1	2103	2104	.1465	L	PIN COND
1241	1	2104	2105	.1465	L	PIN COND
1242	1	2105	2106	.1465	L	PIN COND

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1243	1	2111	2112	.1465	L	PIN COND
1244	1	2112	2113	.1465	L	PIN COND
1245	1	2113	2114	.1465	L	PIN COND
1246	1	2114	2115	.1465	L	PIN COND
1247	1	2115	2116	.1465	L	PIN COND
1248	1	2121	2122	.1465	L	PIN COND
1249	1	2122	2123	.1465	L	PIN COND
1250	1	2123	2124	.1465	L	PIN COND
1251	1	2124	2125	.1465	L	PIN COND
1252	1	2125	2126	.1465	L	PIN COND
1253	1	2131	2132	.1465	L	PIN COND
1254	1	2132	2133	.1465	L	PIN COND
1255	1	2133	2134	.1465	L	PIN COND
1256	1	2134	2135	.1465	L	PIN COND
1257	1	2135	2136	.1465	L	PIN COND
1258	1	2141	2142	.1465	L	PIN COND
1259	1	2142	2143	.1465	L	PIN COND
1260	1	2143	2144	.1465	L	PIN COND

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1261	1	2144	2145	.1465	L	PIN COND
1262	1	2145	2146	.1465	L	PIN COND
1263	1	2151	2152	.1465	L	PIN COND
1264	1	2152	2153	.1465	L	PIN COND
1265	1	2153	2154	.1465	L	PIN COND
1266	1	2154	2155	.1465	L	PIN COND
1267	1	2155	2156	.1465	L	PIN COND
1268	1	2161	2162	.1465	L	PIN COND
1269	1	2162	2163	.1465	L	PIN COND
1270	1	2163	2164	.1465	L	PIN COND
1271	1	2164	2165	.1465	L	PIN COND
1272	1	2165	2166	.1465	L	PIN COND
1273	1	2171	2172	.1465	L	PIN COND
1274	1	2172	2173	.1465	L	PIN COND
1275	1	2173	2174	.1465	L	PIN COND
1276	1	2174	2175	.1465	L	PIN COND
1277	1	2175	2176	.1465	L	PIN COND
1278	1	2181	2182	.1465	L	PIN COND

CTRL-F1Import ITAS_NC   ALT-F3AutoMLI   UDC Allowed   PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT   Shift-F5Del/Pur   End
       F1Save/Purge   F2Help F3AutoGen F4Purge F5Delete F7Mark/UnMark F10Search

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1279	1	2182	2183	.1465	L	PIN COND
1280	1	2183	2184	.1465	L	PIN COND
1281	1	2184	2185	.1465	L	PIN COND
1282	1	2185	2186	.1465	L	PIN COND
1283	1	2191	2192	.1465	L	PIN COND
1284	1	2192	2193	.1465	L	PIN COND
1285	1	2193	2194	.1465	L	PIN COND
1286	1	2194	2195	.1465	L	PIN COND
1287	1	2195	2196	.1465	L	PIN COND
1288	1	2201	2202	.1465	L	PIN COND
1289	1	2202	2203	.1465	L	PIN COND
1290	1	2203	2204	.1465	L	PIN COND
1291	1	2204	2205	.1465	L	PIN COND
1292	1	2205	2206	.1465	L	PIN COND
1293	1	2211	2212	.1465	L	PIN COND
1294	1	2212	2213	.1465	L	PIN COND
1295	1	2213	2214	.1465	L	PIN COND
1296	1	2214	2215	.1465	L	PIN COND

CTRL-F1Import ITAS_NC   ALT-F3AutoMLI   UDC Allowed   PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT   Shift-F5Del/Pur   End
       F1Save/Purge   F2Help F3AutoGen F4Purge F5Delete F7Mark/UnMark F10Search

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1297	1	2215	2216	.1465	L	PIN COND
1298	1	2221	2222	.1465	L	PIN COND
1299	1	2222	2223	.1465	L	PIN COND
1300	1	2223	2224	.1465	L	PIN COND
1301	1	2224	2225	.1465	L	PIN COND
1302	1	2225	2226	.1465	L	PIN COND
1303	1	2231	2232	.1465	L	PIN COND
1304	1	2232	2233	.1465	L	PIN COND
1305	1	2233	2234	.1465	L	PIN COND
1306	1	2234	2235	.1465	L	PIN COND
1307	1	2235	2236	.1465	L	PIN COND
1308	1	2241	2242	.1465	L	PIN COND
1309	1	2242	2243	.1465	L	PIN COND
1310	1	2243	2244	.1465	L	PIN COND
1311	1	2244	2245	.1465	L	PIN COND
1312	1	2245	2246	.1465	L	PIN COND
1313	1	2251	2252	.1465	L	PIN COND
1314	1	2252	2253	.1465	L	PIN COND

```
CTRL-F1Import ITAS_NC     ALT-F3AutoMLI    UDC Allowed            PgDn PgUp Home
SHFT-F1Import Column    Shift-F3AutoCHT    Shift-F5Del/Pur                   End
       F1Save/Purge       F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1315	1	2253	2254	.1465	L	PIN COND
1316	1	2254	2255	.1465	L	PIN COND
1317	1	2255	2256	.1465	L	PIN COND
1318	1	2261	2262	.1465	L	PIN COND
1319	1	2262	2263	.1465	L	PIN COND
1320	1	2263	2264	.1465	L	PIN COND
1321	1	2264	2265	.1465	L	PIN COND
1322	1	2265	2266	.1465	L	PIN COND
1323	1	2271	2272	.1465	L	PIN COND
1324	1	2272	2273	.1465	L	PIN COND
1325	1	2273	2274	.1465	L	PIN COND
1326	1	2274	2275	.1465	L	PIN COND
1327	1	2275	2276	.1465	L	PIN COND
1328	1	2281	2282	.1465	L	PIN COND
1329	1	2282	2283	.1465	L	PIN COND
1330	1	2283	2284	.1465	L	PIN COND
1331	1	2284	2285	.1465	L	PIN COND
1332	1	2285	2286	.1465	L	PIN COND

```
CTRL-F1Import ITAS_NC     ALT-F3AutoMLI    UDC Allowed            PgDn PgUp Home
SHFT-F1Import Column    Shift-F3AutoCHT    Shift-F5Del/Pur                   End
       F1Save/Purge       F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1333	1	2291	2292	.1465	L	PIN COND
1334	1	2292	2293	.1465	L	PIN COND
1335	1	2293	2294	.1465	L	PIN COND
1336	1	2294	2295	.1465	L	PIN COND
1337	1	2295	2296	.1465	L	PIN COND
1338	1	2301	2302	.1465	L	PIN COND
1339	1	2302	2303	.1465	L	PIN COND
1340	1	2303	2304	.1465	L	PIN COND
1341	1	2304	2305	.1465	L	PIN COND
1342	1	2305	2306	.1465	L	PIN COND
1343	1	3011	3012	.1465	L	PIN COND
1344	1	3012	3013	.1465	L	PIN COND
1345	1	3013	3014	.1465	L	PIN COND
1346	1	3014	3015	.1465	L	PIN COND
1347	1	3015	3016	.1465	L	PIN COND
1348	1	3021	3022	.1465	L	PIN COND
1349	1	3022	3023	.1465	L	PIN COND
1350	1	3023	3024	.1465	L	PIN COND

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1351	1	3024	3025	.1465	L	PIN COND
1352	1	3025	3026	.1465	L	PIN COND
1353	1	3031	3032	.1465	L	PIN COND
1354	1	3032	3033	.1465	L	PIN COND
1355	1	3033	3034	.1465	L	PIN COND
1356	1	3034	3035	.1465	L	PIN COND
1357	1	3035	3036	.1465	L	PIN COND
1358	1	3041	3042	.1465	L	PIN COND
1359	1	3042	3043	.1465	L	PIN COND
1360	1	3043	3044	.1465	L	PIN COND
1361	1	3044	3045	.1465	L	PIN COND
1362	1	3045	3046	.1465	L	PIN COND
1363	1	3051	3052	.1465	L	PIN COND
1364	1	3052	3053	.1465	L	PIN COND
1365	1	3053	3054	.1465	L	PIN COND
1366	1	3054	3055	.1465	L	PIN COND
1367	1	3055	3056	.1465	L	PIN COND
1368	1	3061	3062	.1465	L	PIN COND

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1369	1	3062	3063	.1465	L	PIN COND
1370	1	3063	3064	.1465	L	PIN COND
1371	1	3064	3065	.1465	L	PIN COND
1372	1	3065	3066	.1465	L	PIN COND
1373	1	3091	3092	.1465	L	PIN COND
1374	1	3092	3093	.1465	L	PIN COND
1375	1	3093	3094	.1465	L	PIN COND
1376	1	3094	3095	.1465	L	PIN COND
1377	1	3095	3096	.1465	L	PIN COND
1378	1	3101	3102	.1465	L	PIN COND
1379	1	3102	3103	.1465	L	PIN COND
1380	1	3103	3104	.1465	L	PIN COND
1381	1	3104	3105	.1465	L	PIN COND
1382	1	3105	3106	.1465	L	PIN COND
1383	1	3111	3112	.1465	L	PIN COND
1384	1	3112	3113	.1465	L	PIN COND
1385	1	3113	3114	.1465	L	PIN COND
1386	1	3114	3115	.1465	L	PIN COND

```
CTRL-F1Import ITAS_NC    ALT-F3AutoMLI   UDC Allowed           PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT   Shift-F5Del/Pur                   End
        F1Save/Purge      F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1387	1	3115	3116	.1465	L	PIN COND
1388	1	3121	3122	.1465	L	PIN COND
1389	1	3122	3123	.1465	L	PIN COND
1390	1	3123	3124	.1465	L	PIN COND
1391	1	3124	3125	.1465	L	PIN COND
1392	1	3125	3126	.1465	L	PIN COND
1393	1	3141	3142	.1465	L	PIN COND
1394	1	3142	3143	.1465	L	PIN COND
1395	1	3143	3144	.1465	L	PIN COND
1396	1	3144	3145	.1465	L	PIN COND
1397	1	3145	3146	.1465	L	PIN COND
1398	1	3151	3152	.1465	L	PIN COND
1399	1	3152	3153	.1465	L	PIN COND
1400	1	3153	3154	.1465	L	PIN COND
1401	1	3154	3155	.1465	L	PIN COND
1402	1	3155	3156	.1465	L	PIN COND
1403	1	3161	3162	.1465	L	PIN COND
1404	1	3162	3163	.1465	L	PIN COND

```
CTRL-F1Import ITAS_NC    ALT-F3AutoMLI   UDC Allowed           PgDn PgUp Home
SHFT-F1Import Column   Shift-F3AutoCHT   Shift-F5Del/Pur                   End
        F1Save/Purge      F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1405	1	3163	3164	.1465	L	PIN COND
1406	1	3164	3165	.1465	L	PIN COND
1407	1	3165	3166	.1465	L	PIN COND
1408	1	3171	3172	.1465	L	PIN COND
1409	1	3172	3173	.1465	L	PIN COND
1410	1	3173	3174	.1465	L	PIN COND
1411	1	3174	3175	.1465	L	PIN COND
1412	1	3175	3176	.1465	L	PIN COND

APPENDIX N. ITAS BATTERY GEOMETRY MODEL

PC-ITAS   *   LOWER EQUIP PLATE, BATTERY A+B, DC8   * 10·12·88 08/15/84

PC-ITAS   *   PANSAT SIDEWALL STRUCTURE   * 10·18·22 08/15/84

157

UPPER EQUIPMENT PLATE WITH EPS

APPENDIX O.   BATTERY B SURFACE AND NODE NUMBERS

BATTERY B NODE NUMBERS

BATTERY B SURFACE NUMBERS

APPENDIX P.   BATTERY OPTICAL PROPERTIES

ëëë Ctrl : Copy (See F2)ëë ITAS Property Data Entry ëëëëëëëëëëëëëëëëëëëëëëëëëëëëë

Seq	Surface No	NodeNo	Alpha	Emiss	T/Mass	Dissip	MID	Comments
1	1.00	1	0.400	0.790	1.	0.	144	LOWER EQUIPMENT PL
2	5.00	2	0.400	0.790	1.	0.	144	LOWER EQUIPMENT PL
3	10.00	3	0.400	0.790	1.	0.	144	LOWER EQUIPMENT PL
4	15.00	4	0.400	0.790	1.	0.	144	LOWER EQUIPMENT PL
5	20.00	5	0.400	0.790	1.	0.	144	UPPER EQUIPMENT PL
6	25.00	6	0.400	0.790	1.	0.	144	LOWER EQUIPMENT PL
7	30.00	7	0.400	0.790	1.	0.	144	LOWER EQUIPMENT PL
8	35.01	8	0.400	0.790	1.	0.	144	BATTERY A
9	35.02	9	0.400	0.790	1.	0.	144	BATTERY A
10	35.03	10	0.400	0.790	1.	0.	144	BATTERY A
11	35.04	11	0.400	0.790	1.	0.	144	BATTERY A
12	35.05	12	0.400	0.790	1.	0.	144	BATTERY A
13	35.06	13	0.400	0.790	1.	0.	144	BATTERY A
14	40.01	14	0.400	0.790	1.	0.	144	DCS
15	40.02	15	0.400	0.790	1.	0.	144	DCS
16	40.03	16	0.400	0.790	1.	0.	144	DCS
17	40.04	17	0.400	0.790	1.	0.	144	DCS
18	40.05	18	0.400	0.790	1.	0.	144	DCS

äëëë

S-F1Load/Save All   S-F4Auto TM   UDC Allowed   ESCQuit
   F1Load/Save Page F3PropLib F4AutoGen F5ImportPropFmt F6NewPropFile F10Search

ëëë Ctrl : Copy (See F2)ëë ITAS Property Data Entry ëëëëëëëëëëëëëëëëëëëëëëëëëëëëë

Seq	Surface No	NodeNo	Alpha	Emiss	T/Mass	Dissip	MID	Comments
19	40.06	19	0.400	0.790	1.	0.	144	DCS
20	45.01	20	0.400	0.790	1.	0.	144	BATTERY B
21	45.02	21	0.400	0.790	1.	0.	144	BATTERY B
22	45.03	22	0.400	0.790	1.	0.	144	BATTERY B
23	45.04	23	0.400	0.790	1.	0.	144	BATTERY B
24	45.05	24	0.400	0.790	1.	0.	144	BATTERY B
25	45.06	25	0.400	0.790	1.	0.	144	BATTERY B
26	51.00	26	0.400	0.790	1.	0.	144	UPPER EQUIPMENT PL
27	55.00	27	0.400	0.790	1.	0.	144	UPPER EQUIPMENT PL
28	60.00	28	0.400	0.790	1.	0.	144	UPPER EQUIPMENT PL
29	65.00	29	0.400	0.790	1.	0.	144	UPPER EQUIPMENT PL
30	70.00	30	0.400	0.790	1.	0.	144	UPPER EQUIPMENT PL
31	75.00	31	0.400	0.790	1.	0.	144	UPPER EQUIPMENT PL
32	80.00	32	0.400	0.790	1.	0.	144	UPPER EQUIPMENT PL
33	82.00	33	0.400	0.790	1.	0.	144	STRUCTURE FRONT MI
34	84.00	34	0.400	0.790	1.	0.	144	STRUCTURE BACK MID
35	86.00	35	0.400	0.790	1.	0.	144	STRUCTURE RIGHT
36	88.00	36	0.400	0.790	1.	0.	144	STRUCTURE LEFT

äëëë

S-F1Load/Save All   S-F4Auto TM   UDC Allowed   ESCQuit
   F1Load/Save Page F3PropLib F4AutoGen F5ImportPropFmt F6NewPropFile F10Search

ëëë Ctrl : Copy (See F2)ëë ITAS Property Data Entry ëëëëëëëëëëëëëëëëëëëëëëëëëëëëë£

Seq	Surface No	NodeNo	Alpha	Emiss	T/Mass	Dissip	MID	Comments
29	65.00	29	0.400	0.790	1.	0.	144	UPPER EQUIPMENT PL
30	70.00	30	0.400	0.790	1.	0.	144	UPPER EQUIPMENT PL
31	75.00	31	0.400	0.790	1.	0.	144	UPPER EQUIPMENT PL
32	80.00	32	0.400	0.790	1.	0.	144	UPPER EQUIPMENT PL
33	82.00	33	0.400	0.790	1.	0.	144	STRUCTURE FRONT MI
34	84.00	34	0.400	0.790	1.	0.	144	STRUCTURE BACK MID
35	86.00	35	0.400	0.790	1.	0.	144	STRUCTURE RIGHT
36	88.00	36	0.400	0.790	1.	0.	144	STRUCTURE LEFT
37	92.00	37	0.400	0.790	1.	0.	144	RIGHT FRONT SLANT ;
38	94.00	38	0.400	0.790	1.	0.	144	RIGHT FRONT SLANT
39	96.00	39	0.400	0.790	1.	0.	144	BACK RIGHT SLANT
40	98.00	40	0.400	0.790	1.	0.	144	RIGHT BACK SLANT
41	99.01	41	0.400	0.790	1.	0.	144	EPS
42	99.02	42	0.400	0.790	1.	0.	144	EPS
43	99.03	43	0.400	0.790	1.	0.	144	EPS
44	99.04	44	0.400	0.790	1.	0.	144	EPS
45	99.05	45	0.400	0.790	1.	0.	144	EPS
46	99.06	46	0.400	0.790	1.	0.	144	EPS

àëë¥

APPENDIX Q.   PANSAT TRANSIENT STRUCTURAL ANALYSIS

PANSAT - TRANSIENT - SUNLIGHT ZONE - INTERNAL HEAT DISSIPATION - PASS
emperatures, degC

1	32.40	2	33.67	3	35.07	4	32.09	5	33.59	6
7	32.47	8	33.54	9	34.69	10	39.58	11	40.61	12
3	39.76	14	41.05	15	41.37	16	37.92	17	38.77	18
9	39.37	20	38.62	21	37.18	22	40.80	23	39.98	24
5	39.06	26	38.54	27	37.08	28	32.28	29	30.99	30
1	32.08	32	30.41	33	30.00	34	31.71	35	30.53	36
7	30.37	38	30.57	39	31.03	40	30.01	41	30.40	42
3	30.86	44	31.25	45	31.81	46	32.11	47	32.55	48
9	33.21	50	33.87	51	34.13	52	33.26	53	33.70	54
5	33.03	56	32.75	57	31.78	58	34.11	59	33.68	60
1	34.11	62	33.80	63	32.85	64	28.40	65	27.87	66
7	28.78	68	27.91	69	28.55	70	29.55	71	28.89	72
3	27.73	74	29.43	75	33.79	76	29.45	77	32.27	78
9	31.11	80	33.04	81	35.23	82	40.46	83	40.30	84
5	41.20	86	40.80	87	41.71	88	37.21	89	35.10	90
1	38.88	92	37.05	93	35.60	94	38.35	95	36.90	96
7	30.16	98	29.48	99	30.39	100	29.48	101	31.61	102
3	26.29	104	24.59	105	24.93	106	26.60	107	25.48	108
9	28.50	110	27.98	111	28.44	112	26.73	113	26.73	114
5	28.95	116	29.86	117	30.52	118	26.24	119	25.88	120
1	27.85	122	27.19	123	26.76	124	29.65	125	29.14	126
7	25.70	128	25.89	129	25.45	130	25.64	131	26.63	132
3	29.72	134	30.52	135	32.04	136	28.14	137	28.85	138
9	28.05	140	28.30	141	32.10	142	35.42	143	36.06	144
5	37.12	146	41.06	147	41.32	148	34.91	149	33.95	150
1	34.88	152	32.97	153	31.51	154	34.69	155	31.77	156
7	29.53	158	28.94	159	29.44	160	28.94	161	30.75	162
3	30.26	164	30.91	165	31.62	166	29.16	167	29.75	168
9	29.46	170	29.18	171	31.59	172	32.18	173	32.52	174
5	33.63	176	36.91	177	37.05	178	33.01	179	32.11	180
1	33.09	182	31.86	183	30.65	184	33.02	185	31.00	186
7	28.43	188	28.02	189	28.73	190	28.23	191	30.26	192
3	25.04	194	25.51	195	28.20	196	25.32	197	26.39	198
9	25.99	200	27.55	201	31.35	202	29.36	203	27.91	204
5	28.22	206	27.24	207	28.56	208	27.73	209	27.67	210
1	33.97	212	34.66	213	34.63	214	33.51	215	32.24	216
7	31.45	218	31.15	219	33.70	220	34.39	221	34.43	222
3	33.33	224	33.48	225	33.44	226	33.39	227	32.78	228
9	30.58	230	30.52	231	28.77	232	28.61		
1	-272.80									

PANSAT - TRANSIENT - SHADOW ZONE - INTERNAL HEAT DISSIPATION - PA

Temperatures, degC

```
  1   29.93    2   30.88    3   31.83    4   29.32    5   30.44
  7   30.08    8   30.85    9   31.66   10   33.00   11   33.64
 13   33.67   14   34.77   15   35.60   16   32.55   17   33.56
 19   33.64   20   33.04   21   31.97   22   34.48   23   33.54
 25   33.96   26   33.09   27   31.99   28   29.65   29   28.59
 31   29.66   32   28.44   33   28.27   34   29.57   35   28.79
 37   30.28   38   30.75   39   31.22   40   29.99   41   30.63
 43   30.77   44   31.38   45   31.91   46   32.44   47   32.83
 49   33.37   50   34.00   51   34.25   52   33.25   53   33.66
 55   33.23   56   32.94   57   31.97   58   34.26   59   33.84
 61   34.21   62   33.93   63   32.98   64   28.56   65   27.97
 67   28.95   68   28.07   69   28.38   70   29.67   71   28.99
 73   24.95   74   26.06   75   28.75   76   26.75   77   29.08
 79   28.75   80   30.26   81   31.09   82   29.42   83   29.52
 85   30.26   86   30.81   87   31.24   88   30.37   89   29.63
 91   31.86   92   31.57   93   30.88   94   32.42   95   32.12
 97   25.67   98   25.50   99   25.41  100   25.33  101   26.88  1
103   25.04  104   24.21  105   24.73  106   25.75  107   25.58  1
109   27.92  110   28.13  111   28.74  112   26.58  113   26.76  1
115   29.25  116   30.62  117   30.90  118   25.99  119   25.53  1
121   27.98  122   27.30  123   26.85  124   29.88  125   29.35  1
127   24.68  128   24.63  129   25.13  130   25.13  131   26.53  1
133   28.85  134   29.98  135   30.14  136   27.17  137   27.61  1
139   27.11  140   26.83  141   27.67  142   30.15  143   30.95  14
145   29.18  146   27.85  147   27.92  148   31.26  149   30.80  1
151   29.86  152   29.29  153   28.08  154   28.63  155   28.18  1
157   27.54  158   27.46  159   26.82  160   26.90  161   26.93  16
163   30.13  164   31.00  165   31.55  166   28.82  167   29.84  16
169   28.68  170   29.32  171   31.50  172   31.67  173   32.01  17
175   32.24  176   36.36  177   36.47  178   32.95  179   32.13  18
181   32.83  182   31.96  183   30.78  184   32.92  185   31.11  18
187   28.45  188   27.85  189   28.67  190   27.96  191   30.00  19
193   23.23  194   22.92  195   24.73  196   22.97  197   23.03  19
199   23.42  200   23.94  201   26.55  202   29.35  203   27.73  20
205   28.20  206   26.93  207   27.28  208   27.49  209   27.03  21
211   32.31  212   32.69  213   32.56  214   32.18  215   31.74  21
217   31.56  218   31.32  219   32.66  220   33.00  221   32.89  22
223   32.82  224   33.13  225   33.10  226   32.81  227   32.29  22
229   30.60  230   30.64  231   28.51  232   28.55
301 -272.80
```

APPENDIX R.   ITAS BATTERY THERMAL MASSES

```
ëëCtrl:Copyëëëëëëë ITAS Node Data Entry For Thermal Analysis ëëëëëëëëëESC:Quitëf
□                                                                             □
□ SEQN   NodeNo   Temp-C   ThrMass   Dissip   Comment                         □
□    1   -101     33.74    19.438    0        LOWER EQUIPMENT PLATE           □
□    2   -102     33.74    5.692     0        LOWER EQUIPMENT PLATE           □
□    3   -103     33.74    5.692     0        LOWER EQUIPMENT PLATE           □
□    4   -104     33.74    2.014     0        LOWER EQUIPMENT PLATE           □
□    5   -105     33.74    2.014     0        LOWER EQUIPMENT PLATE           □
□    6   -106     33.74    2.014     0        LOWER EQUIPMENT PLATE           □
□    7   -107     33.74    2.014     0        LOWER EQUIPMENT PLATE           □
□    8    201     30       2.169     0        BATTERY A                       □
□    9    202     30       5.327     0        BATTERY A                       □
□   10    203     30       3.3       0        BATTERY A                       □
□   11    204     30       2.169     0        BATTERY A                       □
□   12    205     30       5.327     0        BATTERY A                       □
□   13    206     30       3.3       0        BATTERY A                       □
□   14    301     30       3.805     0        DCS                             □
□   15    302     30       6.342     0        DCS                             □
□   16    303     30       7.610     0        DCS                             □
□   17    304     30       3.805     0        DCS                             □
□   18    305     30       6.342     0        DCS                             □
àëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëÿ
CTRL-FlImport ITAS_NC   UDC Allowed                    PgDn PgUp Home End
SHFT-FlImport Column                     Shift-F5Del/Pur
     FlSave/Purge      F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark FlOSearch

ëëCtrl:Copyëëëëëëë ITAS Node Data Entry For Thermal Analysis ëëëëëëëëëESC:Quitëf
□                                                                             □
□ SEQN   NodeNo   Temp-C   ThrMass   Dissip   Comment                         □
□   19    306     30       7.610     0        DCS                             □
□   20    401     30       2.169     0        BATTERY B                       □
□   21    402     30       5.327     0        BATTERY B                       □
□   22    403     30       3.3       0        BATTERY B                       □
□   23    404     30       2.169     0        BATTERY B                       □
□   24    405     30       5.327     0        BATTERY B                       □
□   25    406     30       3.3       0        BATTERY B                       □
□   26   -501     33.08    9.719     0        UPPER EQUIPMENT PLATE           □
□   27   -502     33.08    2.846     0        UPPER EQUIPMENT PLATE           □
□   28   -503     33.08    2.846     0        UPPER EQUIPMENT PLATE           □
□   29   -504     33.08    1.068     0        UPPER EQUIPMENT PLATE           □
□   30   -505     33.08    1.068     0        UPPER EQUIPMENT PLATE           □
□   31   -506     33.08    1.068     0        UPPER EQUIPMENT PLATE           □
□   32   -507     33.08    1.068     0        UPPER EQUIPMENT PLATE           □
□   33   -601     33.44    2.014     0        PANSAT STRUCTURE                □
□   34   -602     39.87    2.014     0        PANSAT STRUCTURE                □
□   35   -603     38.83    2.014     0        PANSAT STRUCTURE                □
□   36   -604     31.14    2.014     0        PANSAT STRUCTURE                □
àëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëëÿ
CTRL-FlImport ITAS_NC   UDC Allowed                    PgDn PgUp Home End
SHFT-FlImport Column                     Shift-F5Del/Pur
     FlSave/Purge      F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark FlOSearch
```

SEQN	NodeNo	Temp-C	ThrMass	Dissip	Comment
37	-605	30.79	2.014	0	PANSAT STRUCTURE
38	-606	33.26	2.014	0	PANSAT STRUCTURE
39	-607	33.26	2.014	0	PANSAT STRUCTURE
40	-608	28.56	2.014	0	PANSAT STRUCTURE
41	701	30	1.598	0	EPS
42	702	30	1.788	0	EPS
43	703	30	9.132	0	EPS
44	704	30	1.598	0	EPS
45	705	30	1.788	0	EPS
46	706	30	9.132	0	EPS
47	1500	30	0	1	HEAT DISSIPATION IN BATTERY A
48	1600	30	0	6.25	HEAT DISSIPATION IN DCS
49	1700	30	0	.5	HEAT DISSIPATION IN BATTERY B
50	1800	30	0	.5	HEAT DISSIPATION IN EPS

APPENDIX S.   BATTERY THERMAL MASS CALCULATIONS

			BATTERY THERMAL CAPACITANCES					
NODE	area	thickness	volume	ro-Al	c-Al	conv fact	in-m	thr mass
101	122.6	0.25	30.65	2787	0.199	69.78	61024	19.43797
102	35.9	0.25	8.975	2787	0.199	69.78	61024	5.691868
103	35.9	0.25	8.975	2787	0.199	69.78	61024	5.691868
104	12.7	0.25	3.175	2787	0.199	69.78	61024	2.013558
105	12.7	0.25	3.175	2787	0.199	69.78	61024	2.013558
106	12.7	0.25	3.175	2787	0.199	69.78	61024	2.013558
107	12.7	0.25	3.175	2787	0.199	69.78	61024	2.013558
201	17.1	0.2	3.42	2787	0.199	69.78	61024	2.168935
202	42	0.2	8.4	2787	0.199	69.78	61024	5.327208
203	26	0.2	5.2	2787	0.199	69.78	61024	3.297795
204	17.1	0.2	3.42	2787	0.199	69.78	61024	2.168935
205	42	0.2	8.4	2787	0.199	69.78	61024	5.327208
206	26	0.2	5.2	2787	0.199	69.78	61024	3.297795
301	30	0.2	6	2787	0.199	69.78	61024	3.805148
302	50	0.2	10	2787	0.199	69.78	61024	6.341914
303	60	0.2	12	2787	0.199	69.78	61024	7.610297
304	30	0.2	6	2787	0.199	69.78	61024	3.805148
305	50	0.2	10	2787	0.199	69.78	61024	6.341914
306	60	0.2	12	2787	0.199	69.78	61024	7.610297
401	17.1	0.2	3.42	2787	0.199	69.78	61024	2.168935
402	42	0.2	8.4	2787	0.199	69.78	61024	5.327208
403	26	0.2	5.2	2787	0.199	69.78	61024	3.297795
404	17.1	0.2	3.42	2787	0.199	69.78	61024	2.168935
405	42	0.2	8.4	2787	0.199	69.78	61024	5.327208
406	26	0.2	5.2	2787	0.199	69.78	61024	3.297795
501	122.6	0.125	15.325	2787	0.199	69.78	61024	9.718983
502	35.9	0.125	4.4875	2787	0.199	69.78	61024	2.845934
503	35.9	0.125	4.4875	2787	0.199	69.78	61024	2.845934
504	12.7	0.125	1.5875	2787	0.199	69.78	61024	1.006779
505	12.7	0.125	1.5875	2787	0.199	69.78	61024	1.006779
506	12.7	0.125	1.5875	2787	0.199	69.78	61024	1.006779
507	12.7	0.125	1.5875	2787	0.199	69.78	61024	1.006779
601	50.8	0.0625	3.175	2787	0.199	69.78	61024	2.013558
602	50.8	0.0625	3.175	2787	0.199	69.78	61024	2.013558

603	50.8	0.0625	3.175	2787	0.199	69.78	61024	2.013558
604	50.8	0.0625	3.175	2787	0.199	69.78	61024	2.013558
605	50.8	0.0625	3.175	2787	0.199	69.78	61024	2.013558
606	50.8	0.0625	3.175	2787	0.199	69.78	61024	2.013558
607	50.8	0.0625	3.175	2787	0.199	69.78	61024	2.013558
608	50.8	0.0625	3.175	2787	0.199	69.78	61024	2.013558
701	12.6	0.2	2.52	2787	0.199	69.78	61024	1.598162
702	14.1	0.2	2.82	2787	0.199	69.78	61024	1.78842
703	72	0.2	14.4	2787	0.199	69.78	61024	9.132356
704	12.6	0.2	2.52	2787	0.199	69.78	61024	1.598162
705	14.1	0.2	2.82	2787	0.199	69.78	61024	1.78842
706	72	0.2	14.4	2787	0.199	69.78	61024	9.132356

APPENDIX T. BATTERY CONDUCTANCE CALCULATIONS

				BATTERY CONDUCTANCES			
From	To	width	th	area	length	k (Al)	conductance
201	202	5.25	0.2	1.05	5.625	4.31	0.804533333
201	205	5.25	0.2	1.05	5.625	4.31	0.804533333
201	203	3.25	0.2	0.65	6.625	4.31	0.422867925
201	206	3.25	0.2	0.65	6.625	4.31	0.422867925
202	204	3.25	0.2	0.65	6.625	4.31	0.422867925
202	203	8	0.2	1.6	4.25	4.31	1.622588235
202	206	8	0.2	1.6	4.25	4.31	1.622588235
203	205	8	0.2	1.6	4.25	4.31	1.622588235
203	204	3.25	0.2	0.65	6.625	4.31	0.422867925
204	206	3.25	0.2	0.65	6.625	4.31	0.422867925
204	205	3.25	0.2	0.65	5.625	4.31	0.498044444
205	206	8	0.2	1.6	4.25	4.31	1.622588235
301	302	5	0.2	1	8	4.31	0.53875
301	305	5	0.2	1	8	4.31	0.53875
301	303	6	0.2	1.2	7.5	4.31	0.6896
301	306	6	0.2	1.2	7.5	4.31	0.6896
302	304	5	0.2	1	8	4.31	0.53875
302	303	10	0.2	2	5.5	4.31	1.567272727
302	306	10	0.2	2	5.5	4.31	1.567272727
303	305	10	0.2	2	5.5	4.31	1.567272727
303	304	6	0.2	1.2	7.5	4.31	0.6896
304	306	6	0.2	1.2	7.5	4.31	0.6896
304	305	5	0.2	1	8	4.31	0.53875
305	306	10	0.2	2	5.5	4.31	1.567272727
401	402	5.25	0.2	1.05	5.625	4.31	0.804533333
401	405	5.25	0.2	1.05	5.625	4.31	0.804533333
401	403	3.25	0.2	0.65	6.625	4.31	0.422867925
401	406	3.25	0.2	0.65	6.625	4.31	0.422867925
402	404	3.25	0.2	0.65	6.625	4.31	0.422867925
402	403	8	0.2	1.6	4.25	4.31	1.622588235
402	406	8	0.2	1.6	4.25	4.31	1.622588235
403	405	8	0.2	1.6	4.25	4.31	1.622588235

403	404	3.25	0.2	0.65	6.625	4.31	0.422867925
404	406	3.25	0.2	0.65	6.625	4.31	0.422867925
404	405	5.25	0.2	1.05	5.625	4.31	0.804533333
405	406	8	0.2	1.6	4.25	4.31	1.622588235
1500	201			17.1	0.2	4.31	368.505
1500	202			42	0.2	4.31	905.1
1500	203			26	0.2	4.31	560.3
1500	204			17.1	0.2	4.31	368.505
1500	205			42	0.2	4.31	905.1
1500	206			26	0.2	4.31	560.3
1600	301			30	0.2	4.31	646.5
1600	302			50	0.2	4.31	1077.5
1600	303			60	0.2	4.31	1293
1600	304			30	0.2	4.31	646.5
1600	305			50	0.2	4.31	1077.5
1600	306			60	0.2	4.31	1293
1700	401			17.1	0.2	4.31	368.505
1700	402			42	0.2	4.31	905.1
1700	403			26	0.2	4.31	560.3
1700	404			17.1	0.2	4.31	368.505
1700	405			42	0.2	4.31	905.1
1700	406			26	0.2	4.31	560.3
206	102	3.25	7.13	23.1725	0.225	4.31	443.8821111
206	104	3.25	0.435	1.41375	0.225	4.31	27.08116667
206	105	3.25	0.435	1.41375	0.225	4.31	27.08116667
306	101	6	10	60	0.225	4.31	1149.333333
406	103	3.25	7.13	23.1725	0.225	4.31	443.8821111
406	106	3.25	0.435	1.41375	0.225	4.31	27.08116667
406	107	3.25	0.435	1.41375	0.225	4.31	27.08116667
703	501	7.13	7.13	50.8369	0.225	4.31	973.8090622
703	502	0.435	7.13	3.10155	0.225	4.31	59.41191333
703	503	0.435	7.13	3.10155	0.225	4.31	59.41191333
703	504	0.435	0.935	0.406725	0.225	4.31	7.791043333
703	505	0.435	0.935	0.406725	0.225	4.31	7.791043333
703	506	0.435	0.935	0.406725	0.225	4.31	7.791043333
703	507	0.435	0.935	0.406725	0.225	4.31	7.791043333

APPENDIX U. BATTERY MODEL CONDUCTOR DATA ENTRY

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
1	1	1	101	1000	L	GEOMETRY TO LOWER PLATE NODE
2	1	2	102	1000	L	GEOMETRY TO LOWER PLATE NODE
3	1	3	103	1000	L	GEOMETRY TO LOWER PLATE NODE
4	1	4	104	1000	L	GEOMETRY TO LOWER PLATE NODE
5	1	5	105	1000	L	GEOMETRY TO LOWER PLATE NODE
6	1	6	106	1000	L	GEOMETRY TO LOWER PLATE NODE
7	1	7	107	1000	L	GEOMETRY TO LOWER PLATE NODE
8	1	8	201	1000	L	GEOMETRY TO BATTERY A NODE
9	1	9	202	1000	L	GEOMETRY TO BATTERY A NODE
10	1	10	203	1000	L	GEOMETRY TO BATTERY A NODE
11	1	11	204	1000	L	GEOMETRY TO BATTERY A NODE
12	1	12	205	1000	L	GEOMETRY TO BATTERY A NODE
13	1	13	206	1000	L	GEOMETRY TO BATTERY A NODE
14	1	14	301	1000	L	GEOMETRY TO DCS NODE
15	1	15	302	1000	L	GEOMETRY TO DCS NODE
16	1	16	303	1000	L	GEOMETRY TO DCS NODE
17	1	17	304	1000	L	GEOMETRY TO DCS NODE
18	1	18	305	1000	L	GEOMETRY TO DCS NODE

```
CTRL-F1Import ITAS_NC      ALT-F3AutoMLI    UDC Allowed              PgDn PgUp Home
SHFT-F1Import Column    Shift-F3AutoCHT    Shift-F5Del/Pur                  End
       F1Save/Purge       F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
19	1	19	306	1000	L	GEOMETRY TO DCS NODE
20	1	20	401	1000	L	GEOMETRY TO BATTERY B NODE
21	1	21	402	1000	L	GEOMETRY TO BATTERY B NODE
22	1	22	403	1000	L	GEOMETRY TO BATTERY B NODE
23	1	23	404	1000	L	GEOMETRY TO BATTERY B NODE
24	1	24	405	1000	L	GEOMETRY TO BATTERY B NODE
25	1	25	406	1000	L	GEOMETRY TO BATTERY B NODE
26	1	26	501	1000	L	GEOMETRY TO UPPER PLATE
27	1	27	502	1000	L	GEOMETRY TO UPPER PLATE
28	1	28	503	1000	L	GEOMETRY TO UPPER PLATE
29	1	29	504	1000	L	GEOMETRY TO UPPER PLATE
30	1	30	505	1000	L	GEOMETRY TO UPPER PLATE
31	1	31	506	1000	L	GEOMETRY TO UPPER PLATE
32	1	32	506	1000	L	GEOMETRY TO UPPER PLATE
33	1	33	601	1000	L	GEOMETRY TO STRUCTURE NODE
34	1	34	602	1000	L	GEOMETRY TO STRUCTURE NODE
35	1	35	603	1000	L	GEOMETRY TO STRUCTURE NODE
36	1	36	604	1000	L	GEOMETRY TO STRUCTURE NODE

```
CTRL-F1Import ITAS_NC      ALT-F3AutoMLI    UDC Allowed              PgDn PgUp Home
SHFT-F1Import Column    Shift-F3AutoCHT    Shift-F5Del/Pur                  End
       F1Save/Purge       F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
37	1	37	605	1000	L	GEOMETRY TO STRUCTURE NODE
38	1	38	606	1000	L	GEOMETRY TO STRUCTURE NODE
39	1	39	607	1000	L	GEOMETRY TO STRUCTURE NODE
40	1	40	608	1000	L	GEOMETRY TO STRUCTURE NODE
41	1	41	701	1000	L	GEOMETRY TO EPS NODE
42	1	42	702	1000	L	GEOMETRY TO EPS NODE
43	1	43	703	1000	L	GEOMETRY TO EPS NODE
44	1	44	704	1000	L	GEOMETRY TO EPS NODE
45	1	45	705	1000	L	GEOMETRY TO EPS NODE
46	1	46	706	1000	L	GEOMETRY TO EPS NODE
47	1	201	202	.80453	L	BATTERY A NODE TO NODE
48	1	201	205	.80453	L	BATTERY A NODE TO NODE
49	1	201	203	.42287	L	BATTERY A NODE TO NODE
50	1	201	206	.42287	L	BATTERY A NODE TO NODE
51	1	202	204	.42287	L	BATTERY A NODE TO NODE
52	1	202	203	1.62259	L	BATTERY A NODE TO NODE
53	1	202	206	1.62259	L	BATTERY A NODE TO NODE
54	1	203	205	1.62259	L	BATTERY A NODE TO NODE

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
55	1	203	204	.42287	L	BATTERY A NODE TO NODE
56	1	204	206	.42287	L	BATTERY A NODE TO NODE
57	1	204	205	.49804	L	BATTERY A NODE TO NODE
58	1	205	206	1.62259	L	BATTERY A NODE TO NODE
59	1	301	302	.53875	L	DCS NODE TO NODE
60	1	301	305	.53875	L	DCS NODE TO NODE
61	1	301	303	.6896	L	DCS NODE TO NODE
62	1	301	306	.6896	L	DCS NODE TO NODE
63	1	302	304	.53875	L	DCS NODE TO NODE
64	1	302	303	1.56727	L	DCS NODE TO NODE
65	1	302	306	1.56727	L	DCS NODE TO NODE
66	1	303	305	1.56727	L	DCS NODE TO NODE
67	1	303	304	.6896	L	DCS NODE TO NODE
68	1	304	306	.6896	L	DCS NODE TO NODE
69	1	304	305	.53875	L	DCS NODE TO NODE
70	1	305	306	1.56727	L	DCS NODE TO NODE
71	1	401	402	.80453	L	BATTERY B NODE TO NODE
72	1	401	405	.80453	L	BATTERY B NODE TO NODE

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
73	1	401	403	.42287	L	BATTERY B NODE TO NODE
74	1	401	406	.42287	L	BATTERY B NODE TO NODE
75	1	402	404	.42287	L	BATTERY B NODE TO NODE
76	1	402	403	1.62259	L	BATTERY B NODE TO NODE
77	1	402	406	1.62259	L	BATTERY B NODE TO NODE
78	1	403	405	1.62259	L	BATTERY B NODE TO NODE
79	1	403	404	.42287	L	BATTERY B NODE TO NODE
80	1	404	406	.42287	L	BATTERY B NODE TO NODE
81	1	404	405	.80453	L	BATTERY B NODE TO NODE
82	1	405	406	1.62259	L	BATTERY B NODE TO NODE
83	1	1500	201	368.5	L	HEAT NODE TO BATTERY A
84	1	1500	202	950.1	L	HEAT NODE TO BATTERY A
85	1	1500	203	560.3	L	HEAT NODE TO BATTERY A
86	1	1500	204	368.5	L	HEAT NODE TO BATTERY A
87	1	1500	205	950.1	L	HEAT NODE TO BATTERY A
88	1	1500	206	560.3	L	HEAT NODE TO BATTERY A
89	1	1600	301	646.5	L	HEAT NODE TO DCS
90	1	1600	302	1077.5	L	HEAT NODE TO DCS

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
91	1	1600	303	1293	L	HEAT NODE TO DCS
92	1	1600	304	646.5	L	HEAT NODE TO DCS
93	1	1600	305	1077.5	L	HEAT NODE TO DCS
94	1	1600	306	1293	L	HEAT NODE TO DCS
95	1	1700	401	368.51	L	HEAT NODE TO BATTERY B
96	1	1700	402	905.1	L	HEAT NODE TO BATTERY B
97	1	1700	403	560.3	L	HEAT NODE TO BATTERY B
98	1	1700	404	368.51	L	HEAT NODE TO BATTERY B
99	1	1700	405	905.1	L	HEAT NODE TO BATTERY B
100	1	1700	406	560.3	L	HEAT NODE TO BATTERY B
101	1	206	102	443.88	L	BATTERY A TO LOWER PLATE
102	1	206	104	27.08	L	BATTERY A TO LOWER PLATE
103	1	206	105	27.08	L	BATTERY A TO LOWER PLATE
104	1	306	101	1149.3	L	DCS TO LOWER PLATE
105	1	406	103	443.88	L	BATTERY B TO LOWER PLATE
106	1	406	106	27.08	L	BATTERY B TO LOWER PLATE
107	1	406	107	27.08	L	BATTERY B TO LOWER PLATE
108	1	703	501	973.81	L	EPS TO UPPER PLATE

SqNo	FACTOR	From	To	Cond. Value	L/R	Description
109	1	703	502	27.08	L	EPS TO UPPER PLATE
110	1	703	503	27.08	L	EPS TO UPPER PLATE
111	1	703	504	7.791	L	EPS TO UPPER PLATE
112	1	703	505	7.791	L	EPS TO UPPER PLATE
113	1	703	506	7.791	L	EPS TO UPPER PLATE
114	1	703	507	7.791	L	EPS TO UPPER PLATE

```
CTRL-FlImport ITAS_NC    ALT-F3AutoMLI    UDC Allowed              PgDn PgUp Home
SHFT-FlImport Column    Shift-F3AutoCHT    Shift-F5Del/Pur                   End
     FlSave/Purge        F2Help F3AutoGen F4Purge F5Delete  F7Mark/UnMark F10Search
```

APPENDIX V.   BATTERY THERMAL ANALYSIS RESULTS

```
Öááááááááááááááááááááááááááááááááá PC-ITAS áááááááááááááááááááááááááááááááááác
•LINE NO.      1 to      18     RESULTS REVIEW                              °
áááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááái
*****************************************************************************
Date: 09/15/94                                          Time: 17:08:37.10
*****************************************************************************
==========================================================================
                      Thermal Analysis Parameters
==========================================================================
  1.  Solution Method:1.Steady-State 2.Transient 3. (1&2).......        1
  2.  Solution Time Step ........(minutes).....................        0.10
  3.  Final Time (minutes);if <0 then no of orbs...............       -1.00
  4.  Starting Temperature ......(Kelvin )....................      300.00
  5.  Temperature Print Interval (minutes)....................        20
  6.  No. of Iterations For Convergence (NLOOP)...............      9999
  7.  Temperature Unit 1:K, 2:C, 3:F, 4:R....................         2
  8.  Solution Accuracy Parameter (not used)..................       130
  9.  Solution Convergence Parameter (not used)...............       1.30
 10.  Solution Tolerance (ARLXCA, DRLXCA)......................     0.00100
 11.  Transient Solution Stability Factor (not used)...........     0.850
 12.  Include User-Defined Network.......(Y/N)..................        Y

     Use PgDn PgUp Home End         F1Save   F10Search For   ESCQuit/Main Menu


Öááááááááááááááááááááááááááááááááá PC-ITAS áááááááááááááááááááááááááááááááááác
•LINE NO.     19 to      36     RESULTS REVIEW                              °
áááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááááái
 13.  Print RADK, POWER..................(Y/N)..................        N
 14.  Print Transient Time/Temperature...(Y/N)..................       N
 15.  Starting Temperatures Forced (No.4)(Y/N)..................       N
 16.  Thermal Analyses Without Orbital Loads (Y/N)..............       N
 17.  Stand-Alone Thermal Analyzer (ITAS-Format Models).........       N
 18.  No. of Isolated Cavities (RADK files)....................        0

==========================================================================


/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\
                       *ITAS THERMAL ANALYSIS*
/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\/\
*****************************************************************************
 ITAS ABSORBED HEAT RATES FROM ORBITAL INCIDENT & IR AND UV MARICES
*****************************************************************************
*****************************************************************************
Date: 09/15/94                                          Time: 17:08:37.10

     Use PgDn PgUp Home End         F1Save   F10Search For   ESCQuit/Main Menu
```

****
Date: 09/16/94   Time: 10:17:03.10
****

==
                    Thermal Analysis Parameters
==
   1. Solution Method:1.Steady-State 2.Transient 3. (1&2)........   1
   2. Solution Time Step ....(minutes).....................   0.10
   3. Final Time (minutes);if <0 then no of orbs...............   -1.00
   4. Starting Temperature ......(Kelvin).....................   300.00
   5. Temperature Print Interval (minutes)....................   20
   6. No. of Iterations For Convergence (NLOOP)...............   9999
   7. Temperature Unit 1:K, 2:C, 3:F, 4:R.....................   2
   8. Solution Accuracy Parameter (not used)..................   130
   9. Solution Convergence Parameter (not used)...............   1.30
  10. Solution Tolerance (ARLXCA, DRLXCA)......................   0.00100
  11. Transient Solution Stability Factor (not used)..........   0.850
  12. Include User-Defined Network.......(Y/N).................   Y

      Use PgDn PgUp Home End   F1Save   F10Search For   ESCQuit/Main Menu

  13. Print RADK, POWER..................(Y/N).................   N
  14. Print Transient Time/Temperature...(Y/N).................   N
  15. Starting Temperatures Forced (No.4)(Y/N).................   N
  16. Thermal Analyses Without Orbital Loads (Y/N).............   N
  17. Stand-Alone Thermal Analyzer (ITAS-Format Models)........   N
  18. No. of Isolated Cavities (RADK files)....................   0

==

/\
                        ITAS THERMAL ANALYSIS
/\
****
  ITAS ABSORBED HEAT RATES FROM ORBITAL INCIDENT & IR AND UV MARICES
****
****
Date: 09/16/94   Time: 10:17:04.10

      Use PgDn PgUp Home End   F1Save   F10Search For   ESCQuit/Main Menu

CHECKOUT PHASE OF PC-ITAS THERMAL ANALYSIS

  TOTAL CARDS ENCOUNTERED: 2092
  TOTAL THERMAL MASSES USED (W-Min/C)=   7102.07
  TOTAL THERMAL MASSES USED (BTU/F)=   224.440
==
  NO. OF THERMAL NODES=   96

  ITAS STEADY-STATE SOLUTION ALGORITHM (SUCCESSIVE POINT ITERATION) PARAMETERS:
  ARLXCA=0.10000E-02, DRLXCA=0.10000E-02 NLOOP= 9999
  ****
  ITAS STEADY-STATE SOLUTION (SUCCESSIVE POINT ITERATION)
  NO. OF ITERATIONS=   68 TOTAL INPUT ENERGY (W)= 9.6800
  SYSTEM ENERGY BALANCE (W)= 5.1598   (53.303   %)
  ****
  T   1=   33.71 T   2=   33.73 T   3=   33.73 T   4=   33.74
  T   5=   33.74 T   6=   33.74 T   7=   33.74 T   8=   33.69
  T   9=   33.68 T   10=   33.69 T   11=   33.69 T   12=   33.69

     Use PgDn PgUp Home End   F1Save   F10Search For   ESCQuit/Main Menu

  T   13=   33.69 T   14=   33.72 T   15=   33.72 T   16=   33.72
  T   17=   33.72 T   18=   33.72 T   19=   33.69 T   20=   33.70
  T   21=   33.70 T   22=   33.70 T   23=   33.70 T   24=   33.69
  T   25=   33.69 T   26=   33.08 T   27=   33.08 T   28=   33.08
  T   29=   33.08 T   30=   33.08 T   31=   33.08 T   32=   33.08
  T   33=   33.44 T   34=   39.87 T   35=   38.83 T   36=   31.14
  T   37=   30.79 T   38=   33.26 T   39=   33.26 T   40=   28.56
  T   41=   33.00 T   42=   33.00 T   43=   33.97 T   44=   33.00
  T   45=   33.00 T   46=   33.97 T   47= -273.16 T   101=   33.74
  T 102=   33.74 T   103=   33.74 T   104=   33.74 T   105=   33.74
  T 106=   33.74 T   107=   33.74 T   201=   33.69 T   202=   33.69
  T 203=   33.69 T   204=   33.69 T   205=   33.69 T   206=   33.70
  T 301=   33.72 T   302=   33.72 T   303=   33.72 T   304=   33.72
  T 305=   33.72 T   306=   33.72 T   401=   33.70 T   402=   33.70
  T 403=   33.70 T   404=   33.70 T   405=   33.69 T   406=   33.71
  T 501=   33.08 T   502=   33.08 T   503=   33.08 T   504=   33.08
  T 505=   33.08 T   506=   33.08 T   507=   33.08 T   601=   33.44
  T 602=   39.87 T   603=   38.83 T   604=   31.14 T   605=   30.79

     Use PgDn PgUp Home End   F1Save   F10Search For   ESCQuit/Main Menu

```
T    606=     33.26 T   607=     33.26 T   608=     28.56 T   701=     33.00
T    702=     33.00 T   703=     34.00 T   704=     33.00 T   705=     33.00
T    706=     34.00 T  1500=     33.69 T  1600=     33.72 T  1700=     33.70
```

                    ASCENDING NODE NUMBER : TEMPERATURE
****
ITAS STEADY-STATE SOLUTION (SUCCESSIVE POINT ITERATION)
NO. OF ITERATIONS=   68 TOTAL INPUT ENERGY (W)= 9.6800
SYSTEM ENERGY BALANCE (W)=   5.1598   (53.303   %)
****
```
T      1=     33.710 T     2=     33.730 T     3=     33.730 T     4=     33.739
T      5=     33.739 T     6=     33.739 T     7=     33.739 T     8=     33.688
T      9=     33.684 T    10=     33.688 T    11=     33.688 T    12=     33.687
T     13=     33.689 T    14=     33.721 T    15=     33.716 T    16=     33.722
T     17=     33.722 T    18=     33.716 T    19=     33.691 T    20=     33.695
T     21=     33.697 T    22=     33.696 T    23=     33.696 T    24=     33.692
T     25=     33.693 T    26=     33.080 T    27=     33.080 T    28=     33.080
T     29=     33.080 T    30=     33.080 T    31=     33.080 T    32=     33.080
```

       Use PgDn PgUp Home End   F1Save   F10Search For   ESCQuit/Main Menu

```
T     33=     33.439 T    34=     39.867 T    35=     38.828 T    36=     31.140
T     37=     30.790 T    38=     33.259 T    39=     33.260 T    40=     28.561
T     41=     32.996 T    42=     32.996 T    43=     33.972 T    44=     32.996
T     45=     32.996 T    46=     33.966 T    47=   -273.159 T   101=     33.740
T    102=     33.740 T   103=     33.740 T   104=     33.740 T   105=     33.740
T    106=     33.740 T   107=     33.740 T   201=     33.689 T   202=     33.687
T    203=     33.689 T   204=     33.688 T   205=     33.688 T   206=     33.702
T    301=     33.722 T   302=     33.719 T   303=     33.722 T   304=     33.722
T    305=     33.719 T   306=     33.719 T   401=     33.696 T   402=     33.697
T    403=     33.697 T   404=     33.697 T   405=     33.695 T   406=     33.706
T    501=     33.080 T   502=     33.080 T   503=     33.080 T   504=     33.080
T    505=     33.080 T   506=     33.080 T   507=     33.080 T   601=     33.440
T    602=     39.870 T   603=     38.830 T   604=     31.140 T   605=     30.790
T    606=     33.260 T   607=     33.260 T   608=     28.560 T   701=     33.000
T    702=     33.000 T   703=     34.000 T   704=     33.000 T   705=     33.000
T    706=     34.000 T  1500=     33.691 T  1600=     33.722 T  1700=     33.698
```
                    ASCENDING NODE NUMBER : IMPRESSED Q
```
Q      1=      0.000 Q     2=      0.000 Q     3=      0.000 Q     4=      0.000
```

       Use PgDn PgUp Home End   F1Save   F10Search For   ESCQuit/Main Menu

Time	Node 103	104	105	106	107	201	202
63.95	33.74	33.74	33.74	33.74	33.74	33.71	33.71
65.95	33.74	33.74	33.74	33.74	33.74	33.71	33.71
67.95	33.74	33.74	33.74	33.74	33.74	33.71	33.71
69.95	33.74	33.74	33.74	33.74	33.74	33.71	33.71
71.95	33.74	33.74	33.74	33.74	33.74	33.72	33.71
73.95	33.74	33.74	33.74	33.74	33.74	33.72	33.71
75.95	33.74	33.74	33.74	33.74	33.74	33.72	33.71
77.95	33.74	33.74	33.74	33.74	33.74	33.71	33.71
79.95	33.74	33.74	33.74	33.74	33.74	33.71	33.71
81.95	33.74	33.74	33.74	33.74	33.74	33.71	33.71
83.95	33.74	33.74	33.74	33.74	33.74	33.71	33.71
85.95	33.74	33.74	33.74	33.74	33.74	33.71	33.71
87.95	33.74	33.74	33.74	33.74	33.74	33.71	33.71
89.95	33.74	33.74	33.74	33.74	33.74	33.71	33.71
91.95	33.74	33.74	33.74	33.74	33.74	33.71	33.71
92.33	33.74	33.74	33.74	33.74	33.74	33.71	33.71
92.33	33.74	33.74	33.74	33.74	33.74	33.71	33.71

Tempáááá¢ ÖááNode   Öáááááá4Plot Flags (X or Y)

S-F3Save ASCII
F1Plot F2Help F3Save Binary F4SelPlot F8PageLeft F9PageRight ESCQuit

Time	Node 203	204	205	206	301	302	303
63.95	33.71	33.71	33.71	33.71	33.72	33.72	33.72
65.95	33.71	33.71	33.71	33.72	33.72	33.72	33.72
67.95	33.71	33.71	33.71	33.72	33.73	33.72	33.73
69.95	33.72	33.71	33.71	33.72	33.73	33.73	33.73
71.95	33.72	33.72	33.72	33.72	33.73	33.73	33.73
73.95	33.72	33.72	33.72	33.72	33.73	33.73	33.73
75.95	33.72	33.72	33.71	33.72	33.73	33.72	33.73
77.95	33.71	33.71	33.71	33.71	33.72	33.72	33.73
79.95	33.71	33.71	33.71	33.71	33.72	33.72	33.72
81.95	33.71	33.71	33.71	33.71	33.72	33.72	33.72
83.95	33.71	33.71	33.71	33.71	33.72	33.72	33.72
85.95	33.71	33.71	33.71	33.71	33.72	33.72	33.72
87.95	33.71	33.71	33.71	33.71	33.72	33.72	33.72
89.95	33.71	33.71	33.71	33.71	33.72	33.72	33.72
91.95	33.71	33.71	33.71	33.71	33.72	33.72	33.72
92.33	33.71	33.71	33.71	33.71	33.72	33.72	33.72
92.33	33.71	33.71	33.71	33.71	33.72	33.72	33.72

Tempáááá¢ ÖááNode   Öáááááá4Plot Flags (X or Y)

S-F3Save ASCII
F1Plot F2Help F3Save Binary F4SelPlot F8PageLeft F9PageRight ESCQuit

ëëf
□ Tempáááá¢ ÖááNode   Öáááááá Plot Flags (X or Y) □
□   • •   □

□ Time •	304	305	306	401	402	403	404□
□ 63.95 â	33.72	33.72	33.72	33.71	33.71	33.71	33.71□
□ 65.95	33.72	33.72	33.72	33.71	33.71	33.71	33.71□
□ 67.95	33.73	33.72	33.72	33.71	33.72	33.71	33.71□
□ 69.95	33.73	33.73	33.73	33.72	33.72	33.72	33.72□
□ 71.95	33.73	33.73	33.73	33.72	33.72	33.72	33.72□
□ 73.95	33.73	33.73	33.73	33.72	33.72	33.72	33.72□
□ 75.95	33.73	33.72	33.72	33.72	33.72	33.72	33.72□
□ 77.95	33.73	33.72	33.72	33.71	33.72	33.72	33.72□
□ 79.95	33.72	33.72	33.72	33.71	33.71	33.71	33.71□
□ 81.95	33.72	33.72	33.72	33.71	33.71	33.71	33.71□
□ 83.95	33.72	33.72	33.72	33.71	33.71	33.71	33.71□
□ 85.95	33.72	33.72	33.72	33.71	33.71	33.71	33.71□
□ 87.95	33.72	33.72	33.72	33.71	33.71	33.71	33.71□
□ 89.95	33.72	33.72	33.72	33.71	33.71	33.71	33.71□
□ 91.95	33.72	33.72	33.72	33.71	33.71	33.71	33.71□
□ 92.33	33.72	33.72	33.72	33.71	33.71	33.71	33.71□
□ 92.33	33.72	33.72	33.72	33.71	33.71	33.71	33.71□

àëëV
                    S-F3Save ASCII
      F1Plot   F2Help F3Save Binary F4SelPlot F8PageLeft F9PageRight ESCQuit

ëëf
□ Tempáááá¢ ÖááNode   Öáááááá Plot Flags (X or Y) □
□   • •   □

□ Time •	405	406	501	502	503	504	505□
□ 63.95 â	33.71	33.71	33.08	33.08	33.08	33.08	33.08□
□ 65.95	33.71	33.72	33.08	33.08	33.08	33.08	33.08□
□ 67.95	33.71	33.72	33.08	33.08	33.08	33.08	33.08□
□ 69.95	33.71	33.72	33.08	33.08	33.08	33.08	33.08□
□ 71.95	33.72	33.72	33.08	33.08	33.08	33.08	33.08□
□ 73.95	33.72	33.72	33.08	33.08	33.08	33.08	33.08□
□ 75.95	33.72	33.72	33.08	33.08	33.08	33.08	33.08□
□ 77.95	33.71	33.72	33.08	33.08	33.08	33.08	33.08□
□ 79.95	33.71	33.71	33.08	33.08	33.08	33.08	33.08□
□ 81.95	33.71	33.71	33.08	33.08	33.08	33.08	33.08□
□ 83.95	33.71	33.71	33.08	33.08	33.08	33.08	33.08□
□ 85.95	33.71	33.71	33.08	33.08	33.08	33.08	33.08□
□ 87.95	33.71	33.71	33.08	33.08	33.08	33.08	33.08□
□ 89.95	33.71	33.71	33.08	33.08	33.08	33.08	33.08□
□ 91.95	33.71	33.71	33.08	33.08	33.08	33.08	33.08□
□ 92.33	33.71	33.71	33.08	33.08	33.08	33.08	33.08□
□ 92.33	33.71	33.71	33.08	33.08	33.08	33.08	33.08□

àëëV
                    S-F3Save ASCII
      F1Plot   F2Help F3Save Binary F4SelPlot F8PageLeft F9PageRight ESCQuit

 TOTAL SURFACES IN THIS MODEL=   46
****
                    PC-ITAS Summary of Input Parameters
           These parameters reflect the latest values assigned to them
                         prior to any computation
****
Date: 09/17/94   Time: 18:30:45.10
****

==
                         Thermal Analysis Parameters
==

    1. Solution Method:1.Steady-State 2.Transient 3. (1&2).......   2
    2. Solution Time Step ....(minutes).....................   0.10
    3. Final Time (minutes);if <0 then no of orbs................   -1.00
    4. Starting Temperature ......(Kelvin)......................   300.00
    5. Temperature Print Interval (minutes).....................   20
    6. No. of Iterations For Convergence (NLOOP)................   9999
    7. Temperature Unit 1:K, 2:C, 3:F, 4:R......................   2

    Use PgDn PgUp Home End   F1Save   F10Search For   ESCQuit/Main Menu

    8. Solution Accuracy Parameter (not used)...................   1.0
    9. Solution Convergence Parameter (not used)................   1.30
    10. Solution Tolerance (ARLXCA, DRLXCA).......................   0.00100
    11. Transient Solution Stability Factor (not used)...........   0.850
    12. Include User-Defined Network.......(Y/N).................   Y
    13. Print RADK, POWER.................(Y/N)...................   N
    14. Print Transient Time/Temperature...(Y/N).................   N
    15. Starting Temperatures Forced (No.4)(Y/N).................   N
    16. Thermal Analyses Without Orbital Loads (Y/N).............   N
    17. Stand-Alone Thermal Analyzer (ITAS-Format Models)........   N
    18. No. of Isolated Cavities (RADK files)....................   0

==

/\
                          ITAS THERMAL ANALYSIS
/\

    Use PgDn PgUp Home End   F1Save   F10Search For   ESCQuit/Main Menu

Tempáááá¢ ÖááNode   Öáááááá áPlot Flags (X or Y)

Time	8	9	10	11	12	13	14
0.00	26.84	26.84	26.84	26.84	26.84	26.84	26.84
1.95	26.93	26.93	26.94	26.93	26.94	27.10	26.99
3.95	27.06	27.06	27.06	27.06	27.07	27.23	27.19
5.95	27.18	27.18	27.19	27.18	27.19	27.35	27.37
7.95	27.30	27.31	27.31	27.30	27.31	27.47	27.56
9.95	27.42	27.42	27.43	27.42	27.43	27.58	27.73
11.95	27.54	27.54	27.54	27.54	27.54	27.69	27.91
13.95	27.65	27.65	27.65	27.65	27.66	27.80	28.07
15.95	27.76	27.76	27.77	27.76	27.77	27.91	28.23
17.95	27.87	27.87	27.88	27.87	27.88	28.02	28.39
19.95	27.98	27.98	27.98	27.98	27.98	28.12	28.54
21.95	28.08	28.08	28.09	28.08	28.09	28.22	28.68
23.95	28.19	28.19	28.19	28.19	28.19	28.32	28.82
25.95	28.29	28.29	28.29	28.29	28.29	28.42	28.96
27.95	28.38	28.39	28.39	28.38	28.39	28.51	29.09
29.95	28.48	28.48	28.48	28.48	28.49	28.61	29.22
31.95	28.57	28.58	28.58	28.57	28.58	28.70	29.34

S-F3Save ASCII

F1Plot F2Help F3Save Binary F4SelPlot F8PageLeft F9PageRight ESCQuit

PgDn PgUp Home End   ITAS Time ( ) / Temperature ( ) Results   ^^

Tempáááá¢ ÖááNode   Öááááá áPlot Flags (X or Y) ¤

Time	15	16	17	18	19	20	21
0.00	26.84	26.84	26.84	26.84	26.84	26.84	26.84
1.95	26.99	27.00	26.99	26.99	27.15	26.93	26.94
3.95	27.18	27.19	27.19	27.18	27.34	27.06	27.07
5.95	27.37	27.38	27.38	27.37	27.52	27.18	27.19
7.95	27.55	27.56	27.56	27.55	27.70	27.30	27.31
9.95	27.73	27.74	27.73	27.73	27.87	27.42	27.43
11.95	27.90	27.91	27.91	27.90	28.04	27.54	27.55
13.95	28.07	28.08	28.07	28.07	28.20	27.65	27.66
15.95	28.23	28.24	28.23	28.23	28.35	27.77	27.77
17.95	28.38	28.39	28.39	28.38	28.50	27.88	27.88
19.95	28.53	28.54	28.54	28.53	28.65	27.98	27.99
21.95	28.68	28.69	28.68	28.68	28.79	28.09	28.10
23.95	28.82	28.83	28.82	28.82	28.93	28.19	28.20
25.95	28.96	28.96	28.96	28.96	29.06	28.29	28.30
27.95	29.09	29.10	29.09	29.09	29.19	28.39	28.40
29.95	29.22	29.22	29.22	29.22	29.31	28.49	28.49
31.95	29.34	29.35	29.34	29.34	29.43	28.58	28.59

S-F3Save ASCII

F1Plot F2Help F3Save Binary F4SelPlot F8PageLeft F9PageRight ESCQuit

Tempáááá¢ ÖááNode   ÖáááááPlot Flags (X or Y)

Time	22	23	24	25	26	27	28
0.00	26.84	26.84	26.84	26.84	26.84	26.84	26.84
1.95	26.94	26.93	26.93	27.10	33.08	33.08	33.08
3.95	27.06	27.06	27.06	27.23	33.08	33.08	33.08
5.95	27.19	27.18	27.18	27.35	33.08	33.08	33.08
7.95	27.31	27.31	27.31	27.47	33.08	33.08	33.08
9.95	27.43	27.42	27.43	27.58	33.08	33.08	33.08
11.95	27.54	27.54	27.54	27.70	33.08	33.08	33.08
13.95	27.66	27.66	27.66	27.81	33.08	33.08	33.08
15.95	27.77	27.77	27.77	27.91	33.08	33.08	33.08
17.95	27.88	27.88	27.88	28.02	33.08	33.08	33.08
19.95	27.99	27.98	27.98	28.12	33.08	33.08	33.08
21.95	28.09	28.09	28.09	28.23	33.08	33.08	33.08
23.95	28.19	28.19	28.19	28.33	33.08	33.08	33.08
25.95	28.29	28.29	28.29	28.42	33.08	33.08	33.08
27.95	28.39	28.39	28.39	28.52	33.08	33.08	33.08
29.95	28.49	28.49	28.49	28.61	33.08	33.08	33.08
31.95	28.58	28.58	28.58	28.70	33.08	33.08	33.08

S-F3Save ASCII

F1Plot F2Help F3Save Binary F4SelPlot F8PageLeft F9PageRight ESCQuit

Tempááá¢ ÖááNode   Öáááááplot Flags (X or Y) ¤

Time	8	9	10	11	12	13	14
0.00	30.67	30.67	30.67	30.67	30.67	30.73	31.73
1.95	30.68	30.67	30.68	30.67	30.68	30.73	31.74
3.95	30.68	30.66	30.68	30.68	30.68	30.73	31.74
5.95	30.68	30.66	30.69	30.68	30.68	30.72	31.75
7.95	30.69	30.66	30.69	30.68	30.68	30.72	31.75
9.95	30.69	30.66	30.70	30.69	30.68	30.72	31.75
11.95	30.70	30.66	30.70	30.69	30.69	30.72	31.76
13.95	30.70	30.66	30.70	30.69	30.69	30.72	31.76
15.95	30.70	30.66	30.71	30.69	30.69	30.72	31.76
17.95	30.70	30.66	30.71	30.70	30.69	30.72	31.76
19.95	30.71	30.66	30.71	30.70	30.69	30.72	31.76
21.95	30.71	30.66	30.71	30.70	30.70	30.72	31.76
23.95	30.71	30.66	30.72	30.70	30.70	30.72	31.76
25.95	30.71	30.66	30.72	30.70	30.70	30.72	31.76
27.95	30.71	30.66	30.72	30.70	30.70	30.72	31.76
29.95	30.72	30.66	30.72	30.71	30.70	30.72	31.76
31.95	30.72	30.66	30.72	30.71	30.70	30.73	31.76

S-F3Save ASCII

F1Plot F2Help F3Save Binary F4SelPlot F8PageLeft F9PageRight ESCQuit

185

Tempáááát ÖááNode   Öáááááá Plot Flags (X or Y)

Time	15	16	17	18	19	20	21
0.00	31.72	31.73	31.73	31.72	31.74	30.68	30.69
1.95	31.72	31.74	31.74	31.72	31.71	30.69	30.70
3.95	31.72	31.75	31.75	31.72	31.69	30.69	30.70
5.95	31.71	31.76	31.75	31.71	31.67	30.69	30.71
7.95	31.71	31.76	31.76	31.71	31.65	30.70	30.71
9.95	31.71	31.77	31.76	31.71	31.64	30.70	30.72
11.95	31.70	31.77	31.77	31.70	31.63	30.70	30.72
13.95	31.70	31.77	31.77	31.70	31.62	30.70	30.73
15.95	31.70	31.78	31.77	31.70	31.61	30.71	30.73
17.95	31.70	31.78	31.77	31.70	31.61	30.71	30.73
19.95	31.69	31.78	31.78	31.69	31.60	30.71	30.74
21.95	31.69	31.78	31.78	31.69	31.60	30.71	30.74
23.95	31.69	31.78	31.78	31.69	31.59	30.72	30.74
25.95	31.69	31.78	31.78	31.69	31.59	30.72	30.75
27.95	31.68	31.78	31.78	31.68	31.59	30.72	30.75
29.95	31.68	31.78	31.78	31.68	31.58	30.72	30.75
31.95	31.68	31.78	31.78	31.68	31.58	30.73	30.75

S-F3Save ASCII

F1Plot F2Help F3Save Binary F4SelPlot F8PageLeft F9PageRight ESCQuit

□ Tempááá¢ ÖááNode   Öáááááá Plot Flags (X or Y) □

Time	22	23	24	25	26	27	28
0.00	30.68	30.68	30.68	30.74	33.08	33.08	33.08
1.95	30.69	30.69	30.68	30.74	33.08	33.08	33.08
3.95	30.70	30.70	30.67	30.74	33.08	33.08	33.08
5.95	30.70	30.70	30.67	30.73	33.08	33.08	33.08
7.95	30.71	30.70	30.67	30.73	33.08	33.08	33.08
9.95	30.71	30.71	30.67	30.73	33.08	33.08	33.08
11.95	30.71	30.71	30.67	30.73	33.08	33.08	33.08
13.95	30.72	30.72	30.67	30.73	33.08	33.08	33.08
15.95	30.72	30.72	30.67	30.73	33.08	33.08	33.08
17.95	30.72	30.72	30.67	30.73	33.08	33.08	33.08
19.95	30.73	30.73	30.67	30.73	33.08	33.08	33.08
21.95	30.73	30.73	30.67	30.73	33.08	33.08	33.08
23.95	30.73	30.73	30.67	30.73	33.08	33.08	33.08
25.95	30.74	30.74	30.67	30.73	33.08	33.08	33.08
27.95	30.74	30.74	30.67	30.74	33.08	33.08	33.08
29.95	30.74	30.74	30.67	30.74	33.08	33.08	33.08
31.95	30.74	30.74	30.68	30.74	33.08	33.08	33.08

LIST OF REFERENCES

Agrawal, B.N., *Design of Geosynchronous Spacecraft*, Prentice-Hall, Inc, Englewood Cliffs, NJ, 1986.

Analytix Corporation, *ITAS User's Manual*, Analytix Corporation, 1992.

Gates Energy Products, *Rechargeable Batteries Application Handbook*, Butterworth-Heinemann, 1992.

Kraus, A. D., *User's Guide, Thermal Analysis/Steady State Thermal Analysis*, Kraus, 1990.

Kreith, F. and Bohn, M., *Principles of Heat Transfer*, Harper and Row, 1986.

Larson, W. and Wertz, J., *Space Mission Analysis and Design*, Kluwer Academic Publishers, 1992.

Materials Reference Journal, *Machine Design*, Penton Publishers, 1986.

Space Systems Academic Group, *PANSAT Functional Requirements Document*, Naval Postgraduate School, 1993.

INITIAL DISTRIBUTION LIST

1. Defense Technical Information Center 2
    Cameron Station
    Alexandria, Virginia 22304-6145

2. Library, Code 52 2
    Naval Postgraduate School
    Monterey, California 93943-5002

3. Dr. Rudolph Panholzer 1
    Chairman, Space Systems Academic Group
    Code SP
    Naval Postgraduate School
    Monterey, California 93943-5002

4. Dr. I. Michael Ross 8
    Code AA/RO
    Naval Postgraduate School
    Monterey, California 93943-5002

5. Dr. Allan D. Kraus 1
    Code EC/KS
    Naval Postgraduate School
    Monterey, California 93943-5002

6. LCDR Sheila A. Patterson 4
    Commander, Space and Naval Warfare Systems Command
    Code PMW 177
    2451 Crystal Drive
    Arlington, Virginia 22245